




Samsung Galaxy Tab A 10.1 Charging Port Replacement

How to replace the charging port in the Samsung Galaxy Tab A 10.1.

Written By: Isabella Li




INTRODUCTION

If your tablet is not charging and you have made sure your charger works, you may need to replace your charging port.

TOOLS:

- [iFixit Opening Tools](#) (1)
- [Soldering Iron](#) (1)
- [Solder](#) (1)
- [Desoldering Braid](#) (1)

Step 1 — Back Panel



- Have the front of the device facing you.
- Begin near one of the curved edges of the device (see photo two for visual example).
- Place a plastic opening tool between the front and back panels.

⚠ If a plastic opening tool doesn't work, using a metal spudger may work, but it may damage the plastic on the device.

⚠ Remember to remove the micro SD card (if present) before you begin.


Step 2



- Once the plastic opening tool is fully inserted, wedge it around the device's edges to separate the panels.
- Lift the back panel off of the device.


(i) The back panel will make a clicking noise while being lifted off of the device.

Step 3 — Disconnecting the battery




- Remove the adhesive film and flip up the retaining flap on the ZIF battery connector.
- Slide the orange battery ribbon cable out of the ZIF connector.

Step 4




- Remove the adhesive film, lift the retaining tab and withdraw the white speaker ribbon.

Step 5



- Lift the retaining tab and withdraw the black LCD ribbon.


Step 6 — Battery removal



- Using a Phillips #000 screwdriver, remove the ten 4 mm screws around the battery.
- Slide a plastic opening tool under the bottom of the battery close to the speakers and lift up.


⚠ The large rectangular white and black piece is the entire battery. Be careful not to puncture it.

Step 7 — Motherboard





- Flip up the two ZIF connectors on the motherboard using the plastic opening tool.
- Slide the orange ribbon cables out of the ZIF connectors.
- Remove the front-facing camera.

Step 8




- Disconnect the headphone jack from the motherboard.
- Use a Phillips # 000 to remove six 4mm screws.

Step 9



- Lodge the plastic opening tool under and lift the motherboard out of the tablet.
- ⚠ Be careful not to snag any connectors.
- Remove the metal bracket that was underneath the charging port and set aside.

Step 10 — Charging Port




- Place desoldering braid on one of four holes at top back of motherboard.
- Place soldering iron on top of the desoldering braid on the gray part of hole to lift solder. If confused [here's](#) a reference.

i If desoldering braid gets covered with solder and won't lift anymore, just use a new part of the solder wick.

! Soldering iron will be very hot and can both burn your hand and possibly damage the device.

Step 11



- Follow same steps on other three holes.
- Lift small gray metal piece from the motherboard.

To reassemble your device, place a new metal piece where old one was and solder it to the motherboard in the four holes on the opposite side of the motherboard.