




Sony Vaio PCG-71312I Cooling Fan Replacement

This guide covers the removal of the cooling fan and heat sink for replacement.

Written By: Maxine Filcher



 **TOOLS:**

- [Phillips #000 Screwdriver \(1\)](#)
- [Phillips #1 Screwdriver \(1\)](#)

 **PARTS:**

- [Arctic Silver Thermal Paste \(1\)](#)


Step 1 — Battery



⚠ Power down and disconnect from power supply.

- Use your finger to unlock the tab by pressing the slide away from you.

Step 2



- Hold the release slide, while using thumb to apply upward pressure.

Step 3



- Pull the battery off.

Step 4 — RAM




- Unscrew the RAM case
- The case to pop up once you lose up the case

Step 5




- Use two finger gently to pul the white plastic strap outward with both side.
- Once you pull the strap, the RAM with lose up, you are able to just lift up the RAM
- Once you done with the top, repeat the same step for the bottom

Step 6 — Hard Drive




- Using PH 01 remove two 7mm PH screws.

Step 7




- #1 Use force to push the cap upward.
- #2 Unscrew two 7mm PH screws.
- #3 Pull from the plastic and pull toward the arrow point it direction.

Step 8



- Lift plug side first.


Step 9



ⓘ Skip to next step if accessing other components.

- #1 Remove four 3mm PH01 screws from hard drive bracket.

Step 10 — DVD Drive




- Remove two 7mm PH01 screws

Step 11




- Grasp the DVD drive's face plate with your fingers, and pull out.

Step 12 — Cooling Fan




- Remove ten 7mm PH1 screws
- Remove two 8mm PH1 screws
- Remove two 3mm PH1 screws

Step 13



- Remove SD card slot block.
- Push in until it releases.
- Then pull out to remove.


Step 14



- Start by finding a loose corner, to work you prying tool into.
- Then work the tool around the sides to release cover. You may need a second tool to help keep your loose corner open.
- Lift cover away.


(i) NOTE: If you are attempting to access other components, skip 2 steps.

Step 15



- Remove this plug using a prying tool.
- Remove seven 5mm PH01 screws.

Step 16



- To break the thermal paste, apply gentle constant upward force until it comes free.
- Remove four 3.5mm PH000 screws to access cooling fan.

To reassemble your device, follow these instructions in reverse order.