

Equipment Losses at 1000 Cycles

MISCELLANEOUS EQUIPMENT AND ARRANGEMENTS

<u>Voice Frequency Filters</u>	<u>Code</u>	<u>Loss in db</u>
32 or 128 types used independently	F*	0.2
* Followed by letter suffix indicating cutoff frequency		

<u>Program Transmission Equipment</u>		
Artificial line per dwg. 906-4880(AB26.127)	**	7.8
** Indicated by note on circuit layout card		

<u>Telegraph Suppression Filter</u>		
Inserted between input phantoming and compositing equipment (IPCE) and 4-wire repeater when echo suppressor is assigned	TF	0.6

<u>Autotransformers</u>	<u>Loss in db to</u>	
	<u>Side</u>	<u>Phantom</u>
1-A	.02	.02
2-A or 3-A	.25	.25
D-6440	.02	.02
14-A or 16-A	.18	.25
14-B or 16-B	.15	.25
24-A	.50	.50

<u>Switchboard Cabling and Drop Equipment</u>	<u>Loss in db</u>
New York City No. 1 and No. 2 offices	0.5
Chicago	0.9
All other offices (except as modified locally)	0.3

<u>Echo Suppressors</u>	
553-A	0
44-A	0
1-A	1.8
<u>4-wire 4-way 600-ohm Resistance Bridge (per SD-55647-01)</u>	15.0

<u>Straight Bridge Losses of Multiplied 600-Ohm Circuits</u>					
Number of legs indicated are in addition to the feeding leg					
<u>Number of Legs</u>	<u>Loss in db</u>	<u>Number of Legs</u>	<u>Loss in db</u>	<u>Number of Legs</u>	<u>Loss in db</u>
1	0	5	9.5	9	14.0
2	3.5	6	10.9	10	14.8
3	6.0	7	12.0	11	15.55
4	8.0	8	13.1	12	16.25

<u>Special Arrangements</u>	<u>Loss in db to</u>	
	<u>Side</u>	<u>Phantom</u>
107-A repeating coil with 4000 ohm shunts and two type A composite sets, one 93-A or equivalent coil on phantom	1.8	1.8

Compensating Resistance
With two type A repeating coils installed on one side of an open wire phantom group the loss introduced in the other side by the compensating resistances is 0.6 db. The loss to the phantom circuit is the same as if two type A repeating coils replaced the compensating resistances on the side circuit.