

830- AND 2830-TYPE  
TELEPHONE SETS  
(4-WIRE RELAY CONNECTIONS)

1. GENERAL

1.001 This Addendum supplements Section 503-701-101. Place this sheet ahead of Page 1 of this section.

1.002 This Addendum is issued to show the P-90D145 wiring board used in the modification of the 830- and 2830-Type Telephone Sets for 4-wire operation.

6. OPTIONAL FEATURES

MODIFICATION OF 10 OR 11 BUTTON TELEPHONES  
FOR 4-WIRE OPERATION

6.001 The P-90D145 wiring board enables one or more of the pickup buttons on a 10- or 11-button telephone set to be utilized as a 4-wire circuit.

INSTALLATION

6.002 The 830- and 2830-Type Telephone Sets are to be modified as shown in Exhibits 2 and 3. The P-90D145 wiring board is to be mounted inside the telephone set and wiring should be spliced as required. Spare leads in the 50 pair Mtg. Cord may be used for connecting to the 4-wire circuit equipment if available. A D-180454 Kit-of-Parts may be used if spare leads are not available. (See Section 518-230-101).

6.003 Exhibit 1 shows the wiring schematic for the P-90D145 wiring board. The relay is mounted on a wiring board which contains holes for mounting in the set.


ORDERING INFORMATION

6.004 The following material is required for each telephone set to be modified, and may be ordered via the Order Invoice Plan.

(Qua.) - P-90D145 Printed Wiring Board


NOTE: When modifying an 830-Type set, the 8RA Dial must be replaced with an 8CA Dial.

EXHIBIT 1



**P-90D145 PRINTED WIRING BOARD**

**NOTE 1: FW RELAY TO BE MOUNTED IN TEL. SET. FW RELAY = P90D145 PRINTED WIRING BOARD.**



USE SPARE LEADS IN 50 PAIR MTG. CORD OR D-180454 KIT OF PARTS PER BSP 518-230-101

EXHIBIT 2  
MODIFICATION OF 830-TYPE TELEPHONE SETS  
FOR FOUR-WIRE OPERATION

MODIFICATION OF 2830-TYPE TELEPHONE SETS  
FOR FOUR-WIRE OPERATION

**NOTE 1: FW RELAY TO BE MOUNTED IN  
TEL. SET. FW RELAY = P90D145  
PRINTED WIRING BOARD.**

