

**JC BURIED CLOSURE
DESCRIPTION AND INSTALLATION**

1. GENERAL

- 1.001 This addendum supplements Section 631-600-903PT.
- 1.002 It is issued to provide changes when working with filled core cables.

6. COMPLETING SPLICE

The following changes apply to Part 6 of the section:

- (a) 6.06 - revised
- (b) 6.07 - revised

FILLED CORE CABLE (REENTERABLE)

- 6.06 Cover the exposed metal shield of the buried service wire with three wraps of vinyl tape. This is to protect the worker if there is a difference in electrical potential between the shield of the service wire and the shield of the cable when the closure is reentered.
- 6.07 Clean excess grease from the cable conductors, especially those that have been cut and spliced. Wrap the splice bundle with serving tape (see Section 631-600-216, 16 Type Closures) and fill the clear plastic tube with D Encapsulant or other approved reenterable compounds. Protect the closure as described in 3.02 and Fig. 5 until final grade is established.