

OPEN WIRE  
BRIDLING RUNS

NOTES CONCERNING THIS ADDENDUM

This addendum supplements G31.135.1 and is being issued to cover additional instructions for bridle runs on poles. Also included are instructions for making connections between cable terminals and open wire.

The cross-reference "See Addendum" should be marked in G31.135.1 following Paragraph 1.06 to indicate additional information has been added.

1. GENERAL

1.06 Where drive rings or bridle rings are placed on poles to provide wiring facilities, they shall be spaced at intervals of not more than 24 inches, therefore, when the distance between the rings placed on poles in accordance with Section G31.135.1 or other sections exceeds 24 inches, place an additional ring approximately in line and midway between the two rings.

1.07 When making connections between cable terminals and open wire or between two open wire circuits, place the tracer conductor on the right-hand wire of the open wire circuit selected, with your back to the direction of feed.