

AERIAL CABLE PLACING

PREPARING CABLE FOR PULLING

NOTES CONCERNING THIS ADDENDUM

This addendum supplements G52.105.4 and is being issued to include method of attaching wire to cable grip when wire is used as the pulling in line for pulling cable. "See Addendum" should be marked in G52.105.4 following Paragraph 2.04 to indicate additional information has been added.

2. ATTACHING PULLING LINE TO CABLE

2.04 Note: When wire is to be used as the pulling in line for pulling the cable, the following method will facilitate attaching the wire to the cable grip:

- (a) Attach approximately three feet of the wire permanently in the eye of the cable grip by using half round steel dead end wire with an S sleeve.
- (b) Attach the pulling in wire to the wire on the cable grip with a rolled sleeve.
- (c) Upon completion of a pull the wire should be cut at the rolled sleeve leaving the remaining wire attached to the cable grip for the next pull. Tape the end of the wire as a safety measure.