




HP eStation Zeen Ground Wire Replacement

This guide is used to replace the Ground wire of the HP eStation Zeen MotherBoard.

Written By: dalton hale



INTRODUCTION

If the troubleshooting procedures and all of the previous steps do not work it may be time to change the motherboard ground wire.

TOOLS:

- [Phillips #0 Screwdriver](#) (1)
- [Metal Spudger](#) (1)
- [Soldering Iron](#) (1)
- [Tweezers](#) (1)
- [iFixit Opening Tools](#) (1)

Step 1 — Motherboard Ground Wire




- Remove the screw caps using a metal spudger.
- Remove the four 6 mm screws using a Phillips #0 screwdriver.

Step 2



- Insert a plastic opening tool into the case seam and slide it along the edges.
- Lift and remove the back panel from the device.


Step 3



- Carefully disconnect the battery clip using small plastic spudger.


 The clip is extremely fragile.

Step 4



- Use tweezers to disconnect the ground wire from motherboard terminal.

Step 5



- Use a soldering iron to remove the ground wire.

 Avoid touching or heating the motherboard.

To reassemble your device, follow these instructions in reverse order.