




Panasonic Lumix DMC-FX9 Loose Digitizer Cable Replacement

Use this guide to fix your loose digitizer cable on your Panasonic Lumix DMC-FX9.

Written By: Kim Dung Nguyen



INTRODUCTION

A digitizer cable is important to the camera as it sends the display signals to the camera screen from the motherboard. It is vital for both camera operation and a live view of the lens.

TOOLS:

- [Tweezers \(1\)](#)
- [Phillips #0 Screwdriver \(1\)](#)
- [Phillips #00 Screwdriver](#)
- [iFixit Opening Tool \(1\)](#)

Step 1 — Loose Digitizer Cable



- Power off your device by locating the on/off switch on top of camera.

Step 2



- Remove the screw located on the right side of the camera.
- Remove the screw located on the bottom right of the camera, and remove the cover from the camera.

Step 3



- Remove the screw located on the base of the camera.

Step 4



- Pry the top part of the camera slowly. Be careful not to tear the digitizer cable.

Step 5




- Open the bigger clamp using a spudger or other tools. Repeat for the smaller clamp.

Step 6



- Carefully take the thin ribbon and insert cable end into the latch. Do this for both sides.

Step 7



- Once the ribbon is placed into the latch, carefully close the clamps by lowering the clamp into a down position. Repeat this step for both sides.

To reassemble your device, follow these instructions in reverse order.