



Section 2 - Dial Plan

ine.com



Task 2.1

- HQ site and SB site need to communicate with each other. Provision this request as per the following requirements:
 - Configure HQ cluster and SB cluster to be able to talk to each other. All calls from HQ UCM or SB UCM must route through SME.
 - HQ UCM must send +14082022XXX as the calling number to SME and SB UCM must send +19723033XXX as the calling number to SME.
 - SME must always send 8-digits (82022XXX) as the calling number to SB cluster and 8-digits (83033XXX) as the calling number to HQ cluster.
 - SME must always send 8-digits (83033XXX) as the called number to SB cluster and 8-digits (82022XXX) as the called number to HQ cluster.
 - HQ cluster dials 83033XXX as the called number to call SB cluster.

Task 2.1

- SB cluster dials 82022XXX as the called number to call HQ cluster. For example, when “Tony Stark” dials 83033003, “Steve Rogers” must see 82022003.
- You are only allowed to create one route pattern on HQ UCM and one route pattern on SB UCM. This route pattern must be “\+!”.
- Create a SIP Trunk between HQ UCM and SME and another SIP trunk between SB UCM and SME.
- Use Route Group as “RG-SME” on HQ and SB UCM’s.
- Use Route Lists as “RL-SME” on HQ and SB UCM’s.
- Your task is complete when “Tony Stark” can call “Steve Rogers” and vice-versa.