

Remove Password from User Account

OPERATING INSTRUCTIONS

Copyright

© Ericsson AB 2016, 2017. All rights reserved. No part of this document may be reproduced in any form without the written permission of the copyright owner.

Disclaimer

The contents of this document are subject to revision without notice due to continued progress in methodology, design and manufacturing. Ericsson shall have no liability for any error or damage of any kind resulting from the use of this document.

Trademark List

All trademarks mentioned herein are the property of their respective owners. These are shown in the document Trademark Information.



Contents

1	Description	1
2	Procedure	1
2.1	Remove Password from User Account	1



Remove Password from User Account



1 Description

This instruction describes how to remove the password from a local Operation and Maintenance (O&M) user account.

It is recommended that the local user password is removed when the Secure Shell (SSH) public key is set and if the password authentication is not expected to be used.

2 Procedure

2.1 Remove Password from User Account

Prerequisites

- No documents are required.
- No tools are required.
- The following conditions must apply:
 - The user has sufficient access rights to perform the task, for example, the user has the `LocalAuthenticationAdministrator` role.
 - The username for the local user account is known. In this instruction, the username is `joedoe`.
 - An Ericsson Command-Line Interface (ECLI) session in Exec mode is in progress.

Steps

1. Navigate to the `UserAccountM` MO, for example:

```
>dn ManagedElement=N0DE06ST,SystemFunctions=1,SecM=1,UserManagement=1,LocalAuthenticationMethod=1,UserAccountM=1
```
2. Select the user account, for example:

```
(UserAccountM=1)>UserAccount=joedoe
```
3. Remove the password:

```
(UserAccount=joedoe)>removePassword
```



4. Verify that the password has been removed by checking that the password state has been cleared, for example:

```
(UserAccount=joedoe)>show passwordState
```

The following is an example output:

```
PasswordState=[]
```

5. Optional step: It is recommended to delete the password policy reference when the password is removed, for example:

- a. Enter Config mode:

```
(config-UserAccount=joedoe)>configure
```

- b. Delete the attribute password policy, for example:

```
(config-UserAccount=joedoe)>no passwordPolicy
```

- c. Commit the settings

```
(config-UserAccount=joedoe)>commit
```

- d. Verify the deletion, for example:

```
(config-UserAccount=joedoe)>show passwordPolicy
```

The following is an example output:

```
passwordPolicy=[]
```