

# Remove Health Check Job To Trigger

---

## OPERATING INSTRUCTIONS

**Copyright**

© Ericsson AB 2015. All rights reserved. No part of this document may be reproduced in any form without the written permission of the copyright owner.

**Disclaimer**

The contents of this document are subject to revision without notice due to continued progress in methodology, design and manufacturing. Ericsson shall have no liability for any error or damage of any kind resulting from the use of this document.

**Trademark List**

All trademarks mentioned herein are the property of their respective owners. These are shown in the document Trademark Information.



# Contents

<b>1</b>	<b>Introduction</b>	<b>1</b>
1.1	Prerequisites	1
<b>2</b>	<b>Procedure</b>	<b>3</b>



Remove Health Check Job To Trigger



# 1 Introduction

This document describes how to remove the name of the health check job to be triggered. Deleting the name of the health check job to be triggered, no job is triggered if the job execution detects a Managed Element (ME) status different from `HEALTHY`.

## 1.1 Prerequisites

This section describes the prerequisites, which must be fulfilled before using the procedure.

### 1.1.1 Conditions

The following conditions must apply:

- The name of the health check job for which the job to trigger must be deleted is known.
- An Ericsson Command-Line Interface (ECLI) session in Exec mode is in progress.



Remove Health Check Job To Trigger



## 2 Procedure

To delete a job to trigger:

1. Navigate to the *HealthCheckM* MO:

```
>dn ManagedElement=<node_name>,SystemFunctions=1,HealthCheckM=1
```

**Note:** The string `node_name` is specific for the ME.

2. Navigate to the *HcJob* MO representing the health check job for which the `jobToTrigger` must be deleted, for example:

```
(HealthCheckM=1) >HcJob=jobName
```

3. Check the `jobToTrigger` attribute value:

```
(HcJob=jobName) >show jobToTrigger
```

The `jobToTrigger` attribute value is shown.

The following is an example output:

```
(HcJob=jobName) >jobToTrigger="ManagedElement=1, SystemFunction
s=1, HealthCheckM=1, HcJob=secondJob"
```

4. Enter Config mode:

```
(HcJob=jobName) >configure
```

5. Delete the `jobToTrigger` attribute:

```
(config-HcJob=jobName) >no jobToTrigger
```

6. Commit the operation:

```
(config-HcJob=jobName) >commit
```

7. Show `jobToTrigger` attribute:

```
(HcJob=jobName) >show jobToTrigger
```

The `jobToTrigger` is empty.

The following is an example output:

```
(HcJob=jobName) >jobToTrigger=[]
```