

Update License Information

OPERATING INSTRUCTIONS

Copyright

© Ericsson AB 2014, 2015. All rights reserved. No part of this document may be reproduced in any form without the written permission of the copyright owner.

Disclaimer

The contents of this document are subject to revision without notice due to continued progress in methodology, design and manufacturing. Ericsson shall have no liability for any error or damage of any kind resulting from the use of this document.

Trademark List

All trademarks mentioned herein are the property of their respective owners. These are shown in the document Trademark Information.



Contents

1	Introduction	1
1.1	Prerequisites	1
2	Procedure	3



Update License Information



1 Introduction

This document describes how to update license Information.

The information about available licenses and their use is published in the Management Information Base (MIB) as **CapacityKey** and **FeatureKey** Managed Object (MOs) after a license key file has been installed. This read-only information is updated every 30 minutes.

However, after a license key file has been installed, it is recommended to ensure that the latest information is reflected in the MIB. It is done by triggering an immediate update of the license information.

1.1 Prerequisites

This section describes the prerequisites, which must be fulfilled before using the procedure.

1.1.1 Conditions

The following condition must apply:

- An Ericsson Command-Line Interface (ECLI) session in Exec mode is in progress.





2 Procedure

To update license information:

1. Navigate to the **Lm** MO, for example:

```
>dn ManagedElement=NODE06ST,SystemFunctions=1,Lm=1
```

2. Update license information:

```
(Lm=1)>publishLicenseInventory
```

The system returns `true` if the operation is successful.

3. Verify that the license information has been updated by checking the timestamp:

```
(Lm=1)>show lastInventoryChange
```

The system returns a recent timestamp, for example:

```
lastInventoryChange="2015-05-25T00:00:00"
```