

TRANSVERTERS
USING SENDER TEST FRAME
CROSSBAR TANDEM OFFICES
ARRANGED FOR CAMA

1. GENERAL

1.001 This addendum supplements section 220-501-501.

1.002 It is reissued to change test letters on the ODMU Test, used in offices arranged for ODMU (Optional Detail Billing).

The following changes apply to Part 1 of the section.

(a) Test BA - added

1.03 The tests covered are:

BA. ODMU Test: This test checks that the transverter recognizes ODMU calls and changes a 2 line bulk billed entry into a 4 line detailed entry.

5. PREPARATION OF TEST CHART

The following changes apply to Part 5 of the section.

(a) 5.12 - added

(b) 5.13 - added

5.12 If ODMU is provided, the Rate Class leads are modified in the transverter. The Rate Class switch is set on RC1 to test ODMU features. It must be set on RC2 for all other tests.

5.13 If ODMU is provided, a DET key is added on the sender test frame. The DET key is operated in conjunction with the MUD key to test ODMU features.

TABLE A SELECTION OF SWITCH SETTINGS

The following change applies to Table A of the section.

(a) Test BA - added

Tests

BA

Selection of Switch Settings

For CALLING NUMBER switches select a directory number that originates in an ODMU office. For CALLED NUMBER switches select a called office code which, when combined with the calling office, provides a 2 line entry. Operate the DET and MUD keys. Set the RATE CLASS switch to RC1. Also select settings for all other switches and keys as necessary to complete the test.