

**RESCUE OF PERSON FROM LIVE
WIRE ON GROUND**

1. GENERAL

- 1.01 This practice outlines methods of rescuing a person who is in contact with a live wire that is on the ground or at any location other than on a pole.
- 1.02 In an electric shock accident, quick rescue and prompt artificial respiration (if normal breathing has stopped) are extremely important. In some cases the injured person may remain in contact with the wire because of his inability to let go of the live conductor, or due to his being unconscious.
- 1.03 An attempt to rescue a person from contact with a live wire is dangerous for anyone who does not understand how to proceed, because of the fact that the electric current may be carried through the victim's body to the rescuer, or the live wire may come in contact with the rescuer or other person and shock him unless proper precautions are taken.
- 1.04 If an unconscious person is in contact with a wire and it is not definitely known that the wire has been de-energized, assume that it is a live circuit in proceeding to clear him from contact with the wire.
- 1.05 In all cases where the victim is unconscious, call a physician to the location as soon as possible without delaying the rescue. After the victim has been removed from the contact, begin first aid as is necessary.
- 1.06 All employees should review this practice and other applicable first aid practices as well as the Red Cross First Aid Textbook at frequent intervals so that if it should become necessary to rescue a person in contact with a live wire on the ground, the rescue work will be handled promptly and safely.

2. PLANNING THE RESCUE

- 2.01 Before starting the rescue, consider quickly but carefully how the operation can best be carried out. The most important details to be considered are as follows:
 - a. Position of the injured person with respect to the conductor. His position will influence the method to be employed in clearing the contact; that is, whether to:
 - (1) Cut the wire, or
 - (2) Pull the wire clear of the victim, or
 - (3) Roll him off the wire, or
 - (4) Lift him clear of the wire.
 - b. Presence of a nearby switch so that the wire may be de-energized.
 - c. Rescue equipment available that could be used for cutting or moving the wire or moving the victim, such as:
 - (1) Rubber gloves.
 - (2) Rubber footwear.

- (3) Pliers.
 - (4) Dry rope.
 - (5) Tree pruner.
 - (6) Long handled shovel.
 - (7) Dry board.
 - (8) Dry ladder.
 - (9) Triangular bandage.
 - (10) Other non-conducting material.
- d. Dependable assistants.
 - e. Probable voltage of circuit.
 - f. Presence of bystanders. It may be necessary to modify the rescue methods so that bystanders will not be injured by the energized wire while it is being handled.
- 2.02 Men conducting the rescue must remain calm, think clearly, and avoid impulsive and unsafe operations. Keep in mind the fact that wet ropes, wet wood and wet clothing are not good insulators and severe shocks can be transmitted by them. Avoid standing on wet ground and in water.
- 2.03 Employees should become generally familiar with the types of construction used by the electric companies that operate in the areas where rescue work may be necessary so that they may be able to recognize the different types of circuit voltages to be encountered.
3. **FREING A PERSON FROM CONTACT WITH LIVE WIRE OF LESS THAN 10,000 VOLTS**
- 3.01 In rescuing a person who is in contact with a live wire, wear rubber gloves and rubber footwear. While putting on the protective equipment, take the precaution to look for holes or cuts and signs of wear.
- 3.02 If rubber gloves are available, with or without rubber footwear, proceed in accordance with one of the following methods. They are listed in order of preference:
- a. Pull the wire clear of the victim by means of a rope, or push it clear with a tree pruner, board, or ladder.
 - b. Cut the live wire on both sides of the victim or on the remaining side if the wire is broken.
 - (1) Use pliers or a tree pruner.
 - (2) In cutting the wire, close the eyes or turn the head away so that the eyes will not be exposed to the electrical flash.
 - (3) Warn bystanders to keep clear so that they will not be injured by the ends of the wire after it has been cut.

- (4) In many kinds of electric circuits, voltage may remain on the wires after they have been cut at one place. If possible and if it will not delay the rescue operations, hold the wire down by means of a board or tool handle before it is cut so that the wire ends will stay under control.
 - c. Roll the victim off the wire. Observe the wire closely to avoid accidental contact with it and prevent the ends from hitting bystanders.
 - d. Lift the victim off the wire.
- 3.03 If rubber gloves are not available, extreme care must be exercised to avoid direct contact with the body of the person or the live circuit. Use one of the following methods which are listed in order of preference:

- a. Pull the wire clear of the victim by means of a dry rope, provided that it appears that the wire can easily be freed. A dry tree pruner may also be used in pulling the wire or cutting it clear.

NOTE: *Do not* under any circumstances use a wet rope or other wet materials that may come in contact with the live wire or the body of the victim.

- b. If the live wire cannot be freed readily by pulling it clear, slip a dry rope or other dry material under the shoulder or other part of the victim's body and roll him or lift him off the wire. A dry board, ladder, or dry stick may be used to assist in pushing the rope under his body.
- c. If the victim's clothing is wet, *do not* touch him under any circumstances unless rubber gloves are being worn. If his clothing is dry, it may be touched only if other dry insulating material is not available.
- d. Before grasping any portion of the victim's clothing, touch it lightly to make sure that there is no voltage in it.
 - (1) Preferably stand on a dry board or other insulating material while in contact with the clothing.
 - (2) Remember that under wet weather conditions extreme care must be used to avoid shocks even though rubber gloves and rubber footwear or the equivalent are used.

4. FREEING A PERSON FROM CONTACT WITH LIVE WIRE OF MORE THAN 10,000 VOLTS

- 4.01 If the victim is in contact with a live wire and in the best judgement of the rescuer the voltage exceeds 10,000 volts, the rescuer should for his own protection secure the assistance of a qualified employee of the power company to break the contact before proceeding with the rescue. This precaution is necessary since the rubber gloves are not designed to withstand higher voltages and the rescuer cannot be sure that ropes, tree pruner handles, ladders and such equipment that might be used with rubber gloves are always dry enough to provide the degree of protection required.

5. ARTIFICIAL RESPIRATION AND OTHER FIRST AID

- 5.01 If normal breathing has stopped, start artificial respiration immediately after the rescue. Follow the methods as outlined in the American Red Cross First Aid Book. In CTSP 400-405-001, refer to:

- a. Artificial Respiration, paragraph 7.
- b. Burns, paragraph 10.
- c. Shock, paragraph 6.