

MOUNTING CORDS FOR 10- AND 20-BUTTON TELEPHONE SETS IDENTIFICATION

1. GENERAL

1.01 This section contains information on mounting cords used with 830-, 831-, 832-, 833-, 2830-, 2831-, 2832-, and 2833-type telephone sets. Cords for the 10-button F-code TOUCH-A-MATIC® telephone sets are also included.

1.02 This section is reissued to:

- Show D100K-87 cord (A&M only)

- Add D100AE-87 cord

- Revise Table A to update information.

1.03 The standard length of these cords is 5 feet, 6 inches. They are also available in lengths of 9 feet, 13 feet, and 25 feet when specified on order. Refer to Table A.

◆TABLE A◆

MOUNTING CORDS

CORD	TELEPHONE SETS
D50AD-87(A&M Only)	830A1M, 2830A1M, 2830B1M
D50AP-50	832A, 832B, 832C, 832BM, 832CM, 832DM, 832EM, 2832A, 2832B, 2832C, 2832BM, 2832CM, 2832DM, 2832EM
D50BA-87	F-59796, F-59797, F-59798, F-59799, F-60208, F-60209, F-60210, F-60211, 830C, 830CM, 830CT, 830DM, 830FM, 2830C, 2830CM, 2830CT, 2830DM, 2830FM
D100J-87(A&M Only)	831A1M, 831B1M, 2831A1M, 2831B1M
D100K-87(A&M Only)	831DM, 2831DM
D100P-50	833B, 833C, 833BM, 833CM, 833DM, 833EM, 2833B, 2833C, 2833BM, 2833CM, 2833DM, 2833EM
D100AD-87	831CM, 2831CM
D100AE-87	831FM, 2831FM

NOTICE

Not for use or disclosure outside the
Bell System except under written agreement