

TELEPHONE CONSOLES  
1- THROUGH 6-, 10- THROUGH 12-, AND 14- THROUGH 16-TYPE  
APPARATUS UNITS  
12-, 14-, 31-, AND 32-TYPE  
INSTALLATION AND MAINTENANCE

1. GENERAL

1.001 This addendum supplements Section 504-210-201, Issue 8. Place this pink sheet ahead of Page 1 of the section.

1.002 This addendum is issued to:

- Add information on the D-181052 Kit of Parts for fastening housings of 10- and 11-type consoles
- Show the 10B and 11B telephone consoles rated manufacture discontinued (MD).

2. CHANGES TO SECTION

2.001 On Page 11, revise heading and paragraphs 4.11 and 4.12 as follows:

10- AND 11-TYPE CONSOLES/12- AND 14-TYPE APPARATUS UNITS

4.11 When provided, the conference key (part of the 599A or 657A key) on 10B- and 11B-type consoles and 12B- and 14B-type apparatus units may be modified to a nonlocking key (if not already modified by the factory). Remove the screw pin from the plunger of the button next to the hold (red) button. If the conference function is assigned to another key on the 599A or 657A key assembly,

remove the screw pin from the plunger associated with that key.

4.12 To remove housing on 10- and 11-type consoles, proceed as follows.

- (1) Locate 840154793 clips at lower rear of console, close to each corner.
- (2) Using a screwdriver, pry the clips open to release their grip on console base pan.
- (3) When both clips have been freed, lift housing from base.
- (4) To replace housing, place over base and push down firmly on housing until clips make firm contact with base pan.

**Note:** Current production consoles are equipped with two 997123765 speed nuts and two 996114484 screws instead of the clips, as part of the housing assembly, to reduce breakage of the plastic housing. For existing installations of 10- and 11-type consoles, a damaged plastic housing is repaired by ordering a new housing which will be equipped with two speed nuts, and ordering a D-181052 Kit of Parts, which contains two screws that fit the speed nuts. The screws will fit the holes of the existing base.

NOTICE

Not for use or disclosure outside the  
Bell System except under written agreement