

STATION SETS — MAGNETO
SELECTION FOR GENERAL USE

1.00 INTRODUCTION

This section covers, in table form, the selection of magneto station sets for general use.

2.00 SELECTION

TABLE A — SELECTION OF MAGNETO SETS FOR GENERAL USE

Class of Service	Wall Set	Combined Tel Set	Associated Sub. Set	Hand Tel Set	Desk Stand	Associated Sub. Set
Individual Line, PBX and Nonselective Code Ringing on rural lines having eight or less stations and a loop resistance from central office to any station of 800 ohms or less	417AH	307A 357A	299F or D-176680	202H 211E 213E* 215A*	151AL 152AB	415H
Nonselective Code Ringing on rural lines having more than eight stations or a loop resistance from central office to any station of more than 800 ohms	417P	307A 357A	299F	202H 211E 213E* 215A*	151AL 152AB	400A or 400K
2-Party Selective 4-Party Semiselective Regular Stations	417BS	307A 357A	299F or D-176680	202H 211E 213E* 215A*	151AL 152AB	415E
2-Party Selective 4-Party Semiselective Stations with Inductive Noise	417CD	307A 357A	299F or D-176680	202H 211E 213E* 215A*	151AL 152AB	400CD or 415CD
4-Party Selective Regular Stations	417BS	309A	299F or D-176680	202H 211E 213E* 215A*	151AL 152AB	415E
4-Party Selective Stations with Inductive Noise	417CD	309A	299F or D-176680	202H 211E 213E* 215A*	151AL 152AB	400CD or 415CD
Divided Code	417CD	307A 357A	299F or D-176680	202H 211E 213E* 215A*	151AL 152AB	400CD or 415CD

* For use where more than one hand telephone set is used with one subscriber set.

- 2.01 The 357A telephone set is produced in ivory as well as black. The 307A telephone set is produced in the colors shown in Table B.

TABLE B
COLOR CHART FOR 307A TELEPHONE SET

Color	Code
Ivory	307A—50A
Green	307A—51A
Gray	307A—52A
Red	307A—53A
Brown	307A—54A
Beige	307A—55A
Yellow	307A—56A
Blue	307A—57A

TABLE C—TRANSMISSION ZONING CHART FOR MAGNETO OFFICES

Zone	Class of Service	1st Choice Equipment					Alternate Equipment				
		Handset Stations			Nonhandset Stations		Handset Stations			Nonhandset Stations	
		Type Handle	Trans Unit	Rec Unit	Trans /Unit	Rec /Unit	Type Handle	Trans Unit	Rec Unit	Trans /Unit	Rec /Unit
M1	All	F1	F1	HA1	635/F1	706/HA1	F1	F1	HA1	635/F1	706/HA1
M2	All						F4 or F5	T1	U1	None	None

Note: Use an F5 rather than F4 handset when a 4-conductor cord with an F-type handset is required.