


# Avaya™ M460ML-SPV Installation Guide

The Avaya M460ML-SPV is a Supervisor module for the Avaya™ C460 switch.

Figure 1 M460ML-SPV Front Panel



## Safety Information



**Caution:** The Avaya C460 switch and modules contain components sensitive to electrostatic discharge. Do not touch the circuit boards unless instructed to do so.



**Caution:** Do not leave any slots open. Cover empty slots using the blanking plates supplied.



**Caution:** Do not insert any objects into the C460 chassis other than specifically designed Avaya products.




**Danger:** Keep your fingers and other objects clear of the fan module. The fans are on whenever the power is on in the chassis.

---

## Installing the Supervisor Module in the Avaya C460

① You can install supervisor modules in slots 1 and 2 only.

Figure 2 Installing C460 Supervisor ModulesC460



### Key

- a Open locking handle
- b Closed locking handle

- 1 Remove the existing module or blanking plate (see "Removing the Supervisor Module from the Avaya C460")
- 2 Open the locking handles at the edge of the front panel.
- 3 Position the module in the slot with the module name towards the top left-hand side of the module.
- 4 Gently slide the module in.
- ① Ensure the hooks on the locking handle are aligned with the matching holes on the chassis.
- 5 Close the locking handles.
- ▶ The module slides back and connects to the backplane.
- 6 Gently tighten the screws.

---

## Removing the Supervisor Module from the Avaya C460

- 1 Loosen the screws.
- 2 Open the locking handles.
  - ▶ The module is disconnected from the backplane and slides forward.
- 3 Grasp the handles and pull gently but firmly towards yourself.
- 4 Insert another module or a blanking plate.

## Specifications

### Weight

4.4 lb. (2.0 kg)

### Power Requirement

68 W

### Interfaces

- One 10/100BASE-T port (RJ-45)
- One RS-232 port (RJ-45)

### Ordering Information

Product	Material Code
Avaya M460ML-SPV	700255011

---

**avaya.com**

© 2003 Avaya Inc. All rights reserved. All trademarks identified by the © or TM are registered trademarks or trademarks, respectively, of Avaya Inc. All other trademarks are the property of their respective owners  
Document no. 555-500-115