



585-300-516
Issue 2
April 1993

DEFINITY® AUDIX® System
Announcement Customization

**Copyright © 1993 AT&T
All Rights Reserved
Printed in U.S.A.**

Notice

While reasonable efforts were made to ensure that the information in this document was complete and accurate at the time of printing, AT&T can assume no responsibility for any errors. Changes and corrections to the information contained in this document may be incorporated into future reissues.

Your Responsibility for Your System's Security

You are responsible for the security of your system. AT&T does not warrant that this product is immune from or will prevent unauthorized use of common-carrier telecommunication services or facilities accessed through or connected to it. AT&T will not be responsible for any charges that result from such unauthorized use. Product administration to prevent unauthorized use is your responsibility and your system administrator should read all documents provided with this product to fully understand the features available that may reduce your risk of incurring charges.

Federal Communications Commission Statement

part 15: Class B Statement. This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio-frequency energy and, if not intended and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient the receiving television or radio antenna where this may be done safely.
- To the extent possible, relocate the receiver with respect to the telephone equipment.
- Where the telephone equipment requires ac power, plug the telephone into a different ac outlet so that the telephone equipment and receiver are on different branch circuits.

Part 68: Network Registration Number. This equipment is registered with the FCC in accordance with Part 68 of the FCC Rules. It is identified by FCC registration number AS593M-11185-MF-E.

Trademarks

AUDIX is a registered trademark of AT&T.

DEFINITY is a registered trademark of AT&T. In this document, DEFINITY Communications System Generic 3 is often abbreviated to DEFINITY Generic 3 or Generic 3.

Ordering Information

The ordering number for this document is 585-300-516. To order this document, tail the AT&T Customer Information Center at 1-800-432-6600 (in Canada, 1-800-255-1242). For more information about AT&T documents, refer to the *Business Communications Systems Publications Catalog* (555-000-010).

Comments

To comment on this document, return the comment card at the front of the document.

Acknowledgment

This document was prepared by the GBCS Product Documentation Development group, AT&T Bell Laboratories, Denver, CO 80234-2703.



RECYCLED PAPER

Contents

About This Document	v
INTENDED AUDIENCES	v
PREREQUISITE SKILLS OR KNOWLEDGE	v
HOW THIS DOCUMENT IS ORGANIZED.	v
HOW TO USE THIS DOCUMENT	vi
CONVENTIONS USED IN THIS DOCUMENT	vi
TRADEMARKS AND SERVICE MARKS.	vii
RELATED RESOURCES	vii
HOW TO MAKE COMMENTS ABOUT THIS DOCUMENT	vii
AUDIX Helpline Information	ix
WHO SHOULD CALL THE AUDIX HELPLINE	ix
WHAT TO DO BEFORE YOU CALL	x
WHAT DOES THE HELPLINE COST	x
1. Overview	1-1
2. Announcement Customization Scenarios	2-1
3. Variables in Announcements	3-1
A. Standard Announcements	A-1
B. Standard Fragments	B-1

C. Fragment/Announcement Cross-Reference C-1

About This Document

This document describes how to customize system announcements in the AT&T DEFINITY® AUDIX™ System R1.0. It covers customization strategies and provides three appendixes to allow the DEFINITY AUDIX system administrators to see all of the announcements and fragments in the standard announcement set.

Its focus is on how to perform customization tasks. Use this document with its companion reference, *DEFINITY AUDIX R1.0 Forms Reference* (585-300-207), which contains detailed information about each administration form that is used to perform DEFINITY AUDIX announcement customization.

INTENDED AUDIENCES

This document is intended for the person(s) who administers the DEFINITY AUDIX system and wishes to customize system announcements for his/her company application.

PREREQUISITE SKILLS OR KNOWLEDGE

This document does not assume prerequisite skills or knowledge. However, training for DEFINITY AUDIX administration is available and is strongly recommended.

HOW THIS DOCUMENT IS ORGANIZED

- Chapter 1, *Overview*, provides an overview of announcements fragments and the standard announcement set and how they are used in the DEFINITY AUDIX system.
- Chapter 2, *Announcement Customization Scenarios*, describes the major tasks involved in customizing system announcements and fragments.
- Chapter 3, *Variables in Announcements*, describes the variables encountered in system announcements and how they are used.
- Appendix A, *Standard Announcements*, is an exhaustive list of all the standard announcements and the fragments (both fragment numbers and text) that compose them.
- Appendix B, *Standardized Fragments*, is an exhaustive list of all the fragments in the standard announcement set. The listing includes both the fragment number and the associated text.
- Appendix C, *Fragment/Announcement Cross-Reference*, is an exhaustive list of all the standard fragments and the numbers of the announcements that use them.

HOW TO USE THIS DOCUMENT

This document describes announcement customization procedures for the DEFINITY AUDIX system. Use this document in conjunction with the *DEFINITY AUDIX R1.0 Forms Reference* (585-300-207). The forms reference document contains specific instructions for using each form.

CONVENTIONS USED IN THIS DOCUMENT

The following typographic conventions are used in this document

- Information that appears on your terminal screen — including displays, field names, prompts, and error messages — is shown in constant-width type. Information that you are to type just as it appears in the document is shown in constant-width bold type. Here is an example:

At the **when?** prompt type **now**

If the system is not yet ready to receive your input, you receive the following error message

#1: **System is not ready; try again in five minutes.**

- Terminal keys that you are to press are shown in boxes. For example, an instruction to press the return, carriage return or equivalent key might appear in this document as

Press (RETURN).

- Two or three keys that you are to press at the same time (that is, you are to hold down the first key while pressing the second key and, if appropriate, the third key as well) are enclosed together, separated by hyphens, in a curved-edge box. For example, an instruction to press and hold (ALT) while typing the letter *d* appears in this document as

Press (ALT-d).

- Variables for which you or the system substitute a word specific to your own application are shown in all capital letters. For example, a variable to determine the calling party's extension appears in a system announcement as EXTENSION.

TRADEMARKS AND SERVICE MARKS

The following trademarked products are mentioned in this document:

- AUDIX™ is a trademark of AT&T.
- DEFINITY® Communications System is a registered trademark of AT&T.
- UNIX® is a registered trademark of UNIX System Laboratories Inc.

RELATED RESOURCES

In addition to this document, DEFINITY AUDIX Documentation includes the following:

- *DEFINITY AUDIX System R1.0 System Description (585-300-205)*
- *DEFINITY AUDIX System R1.0 Feature Descriptions (585-300-206)*
- *DEFINITY AUDIX System R1.0 Installation (585-300-111)*
- *Switch Administration for DEFINITY AUDIX System R1.0 (585-300-509)*
- *DEFINITY AUDIX System R1.0 Forms Reference (585-300-207)*
- *DEFINITY AUDIX System R1.0 Administration and Data Acquisition Package (585-302-502)*
- *A Portable Guide to DEFINITY AUDIX Voice Messaging (585-300-701)*
- *DEFINITY AUDIX System Voice Messaging Wallet Card (585-300-704)*
- *AUDIX Business Card Sticker (585-304-705)*
- *DEFINITY AUDIX System R1.0 Quick Reference (585-300-702)*
- *DEFINITY AUDIX System R1.0 Voice Messaging Subscriber. Document Artwork (585-300-703)*
- *DEFINITY AUDIX System R1.0 Maintenance (585-300-110)*
- *DEFINITY AUDIX System R1.0 Documentation Guide (585-300-010)*

HOW TO MAKE COMMENTS ABOUT THIS DOCUMENT

A reader comment card follows the title page. While we have tried to make this document fit your needs, we are interested in your suggestions for improving it and urge you to fill it out.

If the reader comment card has been removed from this document please send your comments to:

AT&T
Technical Publications Department
11900 North Pecos Street
Room 22-2c11
Denver, Colorado 80234

AUDIX Helpline Information

The AT&T AUDIX helpline is a centralized telephone information service that provides a fast and convenient way for DEFINITY AUDIX administrators and technicians to report problems and get information about DEFINITY AUDIX capabilities and administration procedures.

Calls to the AUDIX helpline are handled by AT&T personnel using an automated tracking system. You only need to identify yourself, the name of your company, and the product identification number of your DEFINITY AUDIX system to the support representative who answers your call. (Of course, if your company has multiple locations of DEFINITY AUDIX systems, you may need to provide more identifying details to the support representative such as your location or the name of your system.)

Once you have established your identity, your pertinent information (name product identification number, location, configuration, maintenance contract information, recent system trouble history) is displayed on the support representative's screen. The support representative can then answer your questions or help you isolate and solve your problem either by talking you through a particular troubleshooting procedure or by remotely accessing your system and performing the troubleshooting procedure.

AT&T AUDIX HELPLINE

1-800-56-AUDIX (1-800-562-8349)

8am to 5pm Monday through Friday

(Helpline hours are for the time zone where the call originates.)

WHO SHOULD CALL THE AUDIX HELPLINE

The helpline is intended to provide support for DEFINITY AUDIX administrators and technicians. DEFINITY AUDIX subscribers should not call the helpline directly. Instead subscribers should direct their questions or problems to their DEFINITY AUDIX administrator, who can solve most routine subscriber issues or call the helpline for assistance.

WHAT TO DO BEFORE YOU CALL

Gather all relevant facts prior to calling the helpline. Alarm reporting should include the resource type, location, and fault code found on the DISPLAY ALARMS form. You should also display the Activity Log when reporting a subscriber's problem with his/her mailbox.

WHAT DOES THE HELPLINE COST

Basic helpline service is provided at no extra cost to customers who have warranty or maintenance contracts. The helpline is available to other DEFINITY AUDIX users on a fee-per-call basis.

1• Overview

Announcements are voiced prompts that subscribers hear while using the DEFINITY AUDIX system. Each of these announcements is identified by a number. For instance a10 is announcement 10. Announcements are made of up one or more fragments.

A fragment is a piece of voice text consisting of a word phrase or sentence. Fragments are also identified by number, but not the same numbers as those associated with announcements. For example, system announcement a11, “Previous login incorrect, Please re-enter extension and pound sign,” is composed of fragment f233, “Previous login incorrect Please re-enter extension,” and fragment f224, “and pound sign.” Announcements determine the number and order of fragments as they will be encountered by the user. An announcement set is a complete group of announcements containing all of the prompts that may be encountered by the user.

Two announcement sets, a standard version and a terse version, are available. Both versions are shipped with your system. The terse set of announcements may be optionally used. The terse version contains all of the announcements in the standard version, but individual announcements contain fewer words while conveying the same message. For example, the standard version of announcement a2 is “Partial entry deleted” The terse version is “deleted.” If you want to designate terse as the active announcement set use the third page of the SYSTEM-PARAMETERS FEATURES form and change the entry to terse in the Active announcements field.

The standard announcement set is designated as the *active announcement* set by default. The *active* designation means that this is the announcement set that will be heard by anyone accessing DEFINITY AUDIX. An announcement set may also be designated as the *administrative announcement* set. The *administrative* designation means that this is the announcement set that may be recorded into. The active and administrative versions may or may not point to the same announcement set. If they *do* point to the same announcement set, then any recorded changes made to the administrative version will also be made automatically to the active version.

Once all of the initial announcement-related tasks have been completed you will be working with filesystems that are related to the administration of DEFINITY AUDIX system announcements. These are the *names* and the *announcement* filesystems.

Filesystem	Function
names	Contains all voiced names. These are the names of all subscribers and machines. A backup copy of this filesystem is made weekly if activated on the SYSTEM-PARAMETERS FEATURES form.
announcements	Contains all of the announcement sets in your system.

2. Announcement Customization Scenarios

How you customize announcements depends on the announcement and the global implication of changing its fragments. You can customize announcements in the following ways:

- Re-record a fragment
- Add a fragment
- Eliminate a fragment

These procedures are described individually on the following pages.

Re-recording a Fragment

There are at least two announcements you will most likely want to change when you customize your DEFINITY AUDIX system: the default call answer greeting (the greeting someone hears when they are routed to a subscriber's DEFINITY AUDIX mailbox) and the default voice mail greeting (the greeting a subscriber hears when s/he calls DEFINITY AUDIX directly). However, the procedure for re-recording a fragment is the same for any announcement as described below:

1. Using Appendix A, *Standard Announcements*, note the number of the announcement you want to change. This appendix lists each announcement by number and the text and number of each fragment contained in the announcement. Then decide which fragment(s) you want to change.
2. Using Appendix C, *Fragment/Announcement Cross-reference*, verify that the fragment you want to change is used only by announcements you expect to be affected by your changes. Otherwise, you might change another announcement inadvertently.
3. Use the ANNOUNCEMENT form to verify that the announcement you plan to change is actually composed of the fragments you expect. Refer to *DEFINITY AUDIX System R1.0 Forms Reference (585-300-207)* for a complete description of this form.
4. Use the SYSTEM-PARAMETERS FEATURES form (page 3) to determine if an administrative announcement version is active. You can make recorded changes only to the administrative announcement version. If the active announcement set is *standard* or *terse*, and if it is the version you want to change, make a copy of that announcement set and record the changes to the new copy as follows:
 - a. Enter **add annc-set new-annc-set-name**, where *new-annc-set-name* is the name that you wish to give to the new announcement set.
 - b. Enter **copy annc-set**. Enter the name of the existing announcement set in the From Announcement Set field. Enter the name that you gave to the new announcement set in the To Announcement Set field.
 - c. Enter **change system-parameters features**. Enter the name that you gave to the new announcement set in the Administrative field on page 2 of this form.

2-2 Announcement Customization Scenarios

When you are sure that the correct copy of the announcement set is designated as the administrative version, proceed to the next step.

5. Use the `SUBSCRIBER` form to confirm that you have permission to change announcements (you must have a `y` in the `Announcement control` field).
6. Use your touch-tone phone to login to the `DEFINITY AUDIX` system.
7. At the activity menu, press (9). (For security purposes, this option is not included in the voiced options you hear.) If you hear “Invalid entry. For help at any time, press star H.”, you do not have announcement control permission.
8. When you hear “To record names, press (4). To play names, press (5),” press (1) to change the fragment. (For security purposes, this option is not included in the voiced options you hear, but plays out if you press (*)(H) for help.)
9. Enter the fragment ID as prompted and then (#). For example, for f287, enter (2)(8)(7)(#).
10. Record the changed fragment when prompted. You can use all the normal voice mail editing capabilities on your touch-tone phone to make sure the new fragment is exactly how you want it to sound.
11. When you are satisfied with the recording, press (#) to approve it.
12. If the active and administrative announcement versions are the same, then both versions now contain the new fragment. However, if the administrative version designates a different announcement set than the active version, you will have to specify the administrative version as the active version. Use the `SYSTEM-PARAMETERS FEATURES` form to designate the modified announcement set as the active version.

Eliminating a Fragment from an Announcement

Some announcements can be modified by simply eliminating an existing fragment from that specific announcement. For example, you could modify the default voice mail greeting (*Welcome to AUDIX For help at any time, press *H*) to just say *For help at any time, press *H*. by removing fragment f287 (*Welcome to AUDIX*) from the list of fragments that compose the announcement (in this case, announcement a815).

1. Using appendix C, note the number of the announcement you want to change.
2. Use the `ANNOUNCEMENT` form to eliminate the fragment from appearing in the announcement.
 - A. Enter the announcement set name in the `Announcement Set` field.
 - B. Enter the announcement ID in the `Announcement ID` field, in this case a815.
 - C. Press (Enter) to display the fragment composition of the announcement. For this example, the fragment composition is f287, f97.
 - D. Replace f287 with f0 (f0 replaces f287 with silence) and press (Enter).

Announcement a815 is now composed of fragments f0 and f97; callers will simply hear *For help at any time, press *H*.
3. If the active and administrative announcement versions are the same, then both versions now contain the new fragment. However, if the administrative version designates a different announcement set

than the active version, you will have to specify the administrative version as the active version. Use the SYSTEM-PARAMETERS FEATURES form to designate the modified announcement set as the active version.

Adding a Fragment to an Announcement

The previous examples dealt with modifications where the fragments being changed were not used by other announcements or where the fragment itself was left intact but was eliminated from just specific announcements. If you need to change the contents of a fragment for some announcements but not others, you will need to substitute an existing fragment or create a new fragment for use by the announcements you want to change and leave the old fragment intact for use by existing announcements that you do not want changed.

For example, announcement a812 and announcement a834 are the only announcements that use fragment f87, *This call is experiencing difficulties*. If you want to change this fragment for announcement a812 but not announcement a834, you would need to create a new fragment to associate with announcement a812 instead of fragment f87, and you would leave fragment f87 and its association with announcement a834 intact.

1. Using Appendix B, note the number of the fragments you want to change. Using Appendix C, verify that the fragments are used only by announcements you expect to be affected by your changes. Use the ANNOUNCEMENT form to verify that the announcement you plan to change is actually composed of the fragments you expect.
2. Use the SYSTEM-PARAMETERS FEATURES form to determine if an administrative announcement version is active. You can record or re-record fragments only in the administrative announcement version. If there is an active announcement version and it is the version you want to change, make sure that it is also specified as the administrative version.

When you are sure that the correct copy of the announcement set is designated as the administrative version, go to the next step.

3. Use the SUBSCRIBER form to confirm that you have permission to change announcements (you must have a `y` in the Announcement Control field).
4. Use your touch-tone phone to login to the DEFINITY AUDIX system.
5. At the activity menu, press (9). (For security purposes, this option is not included in the voiced options you hear.) If you hear *Entry not understood. Try again.*, you do not have announcement control permission.
6. When you hear *To record names, press 4. To play names, press 5*, press (1) to change fragments. (For security purposes, this option is not included in the voiced options you hear.)
7. Enter the fragment ID as prompted; in this case enter an unused number such as f4000, for instance, (4)(0)(0)(0)(#).

NOTE

The fragment numbers 4000-4999 have been reserved for customer use. Using other numbers could jeopardize the integrity of your custom fragments and announcements if these numbers are used for new fragments in later versions or updates to DEFINITY AUDIX.

8. Record the fragment when prompted. For example, your new fragment might be *This call is experiencing difficulties and cannot continue at this time*. You can use all the normal voice mail editing capabilities on your touch-tone phone to make sure the new fragment sounds exactly the way you want it to sound.
9. When you are satisfied with the new fragment recording, press (#) to approve it.
10. Use the ANNOUNCEMENT form to add the new fragment in this case f4000, to announcement a812 in place of fragment f87.
 - A. Enter announcement set name in the Announcement Set field.
 - B. Enter the announcement number, in this case **a812**, in the Announcement ID field.
 - C. Press (Enter) to display the fragments that compose the announcement. Displaying an announcement shows the numbers of the fragments only — not the text. To determine the text for each listed fragment refer to Appendix B, *Standard Fragments*. For this example, announcement a812, the fragment composition is as follows:
 - 87: This call is experiencing difficulties.
 - 497: To review your message, press star 1.
 - D. Rewrite the line to reflect the new composition, in this case **4000,497** and press (Enter).

Announcement a812 is now composed of the following fragments:

 - 4000: This call is experiencing difficulties and cannot continue at this time.
 - 497: To review your message, press star 1.

Meanwhile, announcement a834 still uses fragment f87 as before.
11. If the active and administrative announcement versions are the same, then both versions now contain the new fragment. However, if the administrative version designates a different announcement set than the active version, you will have to specify the administrative version as the active version. Use the SYSTEM-PARAMETERS FEATURES form to designate the modified announcement set as the active version.

Alternatively in this example, you could have created a new fragment f4000 with just *and cannot continue at this time*. to use in addition to fragment f87 instead of replacing it in announcement a812. Either way, be careful if you make changes to announcements and fragments and be sure you have thoroughly researched the global ramifications of changes that you plan to make before you actually make them. Next, test your changes to make sure your modifications are accurate. And finally, when in doubt save the announcement sets *before* making changes in the fragments. Be sure to write any changes you make into the appropriate appendix in this manual. Doing this will save you both time and confusion later if you make additional modifications.

3. Variables in Announcements

In the DEFINITY AUDIX system, some announcements are variable — in other words, the contents of an announcement may change depending on changing times, dates, and/or subscriber inputs. Within system announcements, variables are always represented by a word or words in all capital letters. For example announcement 110 (**a110**) is made up of fragment 663 (f663) and DATE :

```
f663 : Message waiting notification is not active and this message
      has an expiration date of
      <DATE>
```

DATE is the variable and will change according to the appropriate date.

Some announcements may have more than one variable. For instance, a287 is

```
f47 : Call from
     <NAME>
f262 : received
     <TIME>
     <DATE>
f86 : extension
     <BUTTONS>
```

NAME is the variable identifying the person who called. TIME is the variable time DEFINITY AUDIX received the call. DATE is the date DEFINITY AUDIX received the call. BUTTONS is the variable extension of the person who called.

In addition, some announcements may include different fragments at different times depending on whether or not certain conditions are met by the variable. Look at a344, for example. It can state three different messages depending on the value of the variable NUMBER

1. If the variable NUMBER is equal to 0, the announcement is:

```
f741: Private, priority message sent to
     <NAME>
```

2. If the variable NUMBER is greater than zero and equal to 1, the announcement is:

```
f741 : Private, priority message sent to
     <NAME>
f2 : and
     <NUMBER>
f602 : other.
```

3-2 Variables in Announcements

3. If the variable `NUMBER` is greater than zero and greater than 1, the announcement is:

```
f741:  Private, priority message sent to  
       <NAME>  
f2 :   and  
       <NUMBER>  
f217 :  others.
```

Occasionally, you will see some announcements that call in other announcements in addition to the fragments they use. For example, many announcements call in `a873`, an announcement that determines the length of a message. This value is used in many announcement scenarios. However, rather than including this involved routine in every announcement that uses this value, it is written as a separate subroutine in a separate announcement. Then the announcements that use this value just call in `a873` to determine message length — a process that actually saves a lot of system space.

A. Standard Announcements

This appendix includes all of the announcements in the DEFINITY AUDIX system announcement set, as well as the associated fragments and their text.

A-2 Standard Announcements

Announcement	Fragment and Text	
a1	f776 f745 f823	the system greeting or active for all calls
a2	f936	Partial entry deleted.
a3 Month & Day]		(f350+NUMBER(3)) — Day of week (f310+NUMBER(1)) — Month a905(NUMBER(2)) — Day of month
a4	f46 f117 f291	To access your mailbox, press star R. To reach the covering extension, press star zero. To transfer to another extension, press star T.
a5	f235 f282	To restart at the activity menu, press star R. To transfer to another extension, press star T. To have system wait, press star W. To access the names or numbers directory, press star star N. If finished please hang up or to disconnect AUDIX, press star star X.
a6	f561 f285 f224 f328 f58	You are addressing your message. To add a member, enter extension and pound sign. To delete the previous entry, press star D. To add a mailing list you have already created or a public list owned by others, press star L. To review or modify the list you are creating, press star 1. To approve the list you are creating and move on to the next step, press pound. For name addressing, press star A.
a7	f561 f286 f224 f328 f148	You are addressing your message. To add a member, enter last name and pound sign. To delete the previous entry, press star D. To add a mailing list you have already created, or a public list owned by others, press star L. To review or modify the list you are creating, press star 1. To approve the list you are creating and move on to the next step, press pound. For extension addressing, press star A.
a8	f46 f291	To access your mailbox, press star R. To transfer to another extension, press star T.

Standard Announcements A-3

Announcement	Fragment and Text
a9	<p>f235 To restart at the activity menu, press star R. To transfer to another extension, press star T.</p> <p>f117 To reach the covering extension, press star zero.</p> <p>f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished please hang up or to disconnect AUDIX, press star star X.</p>
a10	<p>f306 You are Changing your password.</p> <p>f212 Please enter password again for confirmation. To delete the password you just entered press *D</p> <p>f235 To restart at the activity menu, press star R To transfer to another extension, press star T.</p> <p>f282 To have system wait press star W. To access the names or numbers directory, press star star N. If finished please hang up or to disconnect AUDIX, press star star X.</p>
a11	<p>f233 Previous login incorrect. Please re-enter extension</p> <p>f224 and pound sign.</p>
a12	<p>f233 Previous login incorrect. Please re-enter extension</p> <p>f224 and pound sign.</p> <p>f330 Or enter just the pound sign if it's your phone.</p>
a13	<p>f105 To restart at the activity menu, press star R.</p> <p>f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished please hang up or to disconnect AUDIX, press star star X.</p>
a14	<p>f306 You are Changing your password.</p> <p>f210 Please enter a new password.</p> <p>f224 and pound sign.</p> <p>f80 To have system wait, press star W. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a15	<p>f555 To access your mailbox, press star R.</p> <p>f117 To reach the covering extension, press star zero.</p> <p>f291 To transfer to another extension, press star T.</p> <p>f80 To have system wait, press star W. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a16	<p>f306 You are changing your password.</p> <p>f212 Please enter password again for confirmation. To delete the password you just entered, press *D</p> <p>f80 To have system wait, press star W. If finished, please hang up or to disconnect AUDIX, press star star X.</p>

A-4 Standard Announcements

Announcement	Fragment and Text
a17	f555 To access your mailbox, press star R. f80 To have system wait, press star W. If finished, please hang up or to disconnect AUDIX, press star star X.
a18	f555 To access your mailbox, press star R. f291 To transfer to another extension, press star T. f80 To have system wait, press star W. If finished, please hang up or to disconnect AUDIX, press star star X.
a19	f327 You are creating a mailing list. f285 To add a member, enter extension f224 and pound sign. f328 To delete the previous entry, press star D. To add a mailing list you have already created, or a public list owned by others, press star L. To review or modify the list you are creating, press star 1. To approve the list you are creating and move on to the next step, press pound. f58 For name addressing, press star A f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a20	f327 You are creating a mailing list. f286 To add a member, enter last name f224 and pound sign. f328 To delete the previous entry, press star D. To add a mailing list you have already created, or a public list owned by others, press star L. To review or modify the list you are creating, press star 1. To approve the list you are creating and move on to the next step, press pound. f148 For extension addressing, press star A. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a21	f821 You are administering call types.
a22	f821 You are administering call types. f798 Prime time is TIME f524 to TIME(2) f788 To Identify calls as out-of-hours, press 3. f789 Otherwise, press 4.

Standard Announcements A-5

Announcement	Fragment and Text
a23	<p>f821 You are administering call types. f785 Same greeting used for all calls. f786 To identify calls as internal and external, press 1. f787 To identify calls as busy and no answer, press 2.</p>
a24	<p>f503 You are administering your attendant menu. f502 To record attendant menu, press 1. To listen to attendant menu, press 0. f550 To rewind your attendant menu, press two. To delete it, press star D. To stop playback of your attendant menu, press three. f339 To replay the last few seconds, press 5. To advance a few seconds, press 6. f292 Louder, press 4. Softer, press 7. Faster, press 9. Slower, press, 8. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a25	<p>f373 You are choosing whether to attach a copy of original message to your reply. To include the original, press Y for yes. To send only your reply, press N for no. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the name or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a26	<p>f299 You are administering your greeting. f5 To record personal greeting, press 1. To listen to personal greeting, press 0. To select which greeting to use, press star pound. f39 To delete, press star D. To stop playback, press 3. f339 To replay the last few seconds, press 5. To advance a few seconds, press 6. f292 Louder, press 4. Softer, press 7. Faster, press 9. Slower, press 8. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a27	<p>f46 To access your mailbox, press star R.</p>

A-6 Standard Announcements

Announcement	Fragment and Text
a28	f529 You are changing your outcalling options. f527 To change number, press 1. To change times, press 2. For instructions on entering your outcalling number, press 3. f528 To turn on, press y. To turn off, press n. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a29	f347 You are adding a list. f111 Please enter list id f224 and pound sign. f366 To specify a different owner by extension, press star D. f363 To approve the list you are creating, press pound.
a30	f302 You are recording announcement fragments. Enter fragment id followed by pound sign. Refer to admin manual for correct id. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a31	f347 You are adding a list. f111 Please enter list id f224 and pound sign. f367 To specify a different owner by name, press star D. f363 To approve the list you are creating, press pound.
a32	f303 You are recording names. Enter extension. f224 and pound sign. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a33	f382 You are scheduling your message for delivery. f341 Enter the number of the month, one through twelve, then two digits for the day of the month, then the pound sign. f487 To delete time, press star D. To default rest of the delivery time, press pound.

Standard Announcements A-7

Announcement	Fragment and Text
a34	<p>f108 You are recording a message. f167 To approve, press pound. To record from here, press 1. To playback, press 2-3. f296 To delete, press star D. f339 To replay the last few seconds, press 5. To advance a few seconds, press 6. f292 Louder, press 4. Softer, press 7. Faster, press, 9. Slower, press 8. f497 To review your message, press star 1.</p>
a35	<p>f816 You are listening to a personal greeting. f753 Enter greeting number. f913 If finished, press pound.</p>
a36	<p>f817 You are recording a personal greeting. f753 Enter greeting number. f913 If finished, press pound.</p>
a37	<p>f820 You are selecting which greeting to activate.</p>
a38	<p>f368 You are entering the number for a new list. Please enter a number up to six digits long and pound sign. f224 To replace an existing list, enter that list's number, and pound sign. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a39	<p>f358 You are identifying a list as private or public. f14 To make private, press 1. To make public, press 2. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hangup or to disconnect AUDIX, press star star X.</p>

A-8 Standard Announcements

Announcement	Fragment and Text
a40	<p>f370 These are entries in your list. f294 To add entries, press 1. f371 To rewind to current entry, press 2. To rewind to previous entries, press 2 as many times as necessary. To continue playback of list, press 3. f292 Louder, press 4. Softer, press 7. Faster, press 9. Slower, press 8. f372 To skip to next entry, press pound. To delete current entry, press star D. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a41	<p>f360 You are scanning mailing lists. To review list members, press 0. To rewind to previous list, press 2. To continue scanning lists, press 3. f292 Louder, press 4. Softer, press 7. Faster, press 9. Slower, press 8. f361 To skip to next list, press pound. To delete list, press star D. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a42	<p>f587 You are reviewing a list. f586 To skip, press pound. f371 To rewind to current entry, press 2. To rewind to previous entries, press 2 as many times as necessary. To continue playback of list, press 3. f292 Louder, press 4. Softer, press 7. Faster, press 9. slower, press 8. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a43	<p>f359 You are changing the status of your list. To modify status press Y for yes or N for no. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>

Standard Announcements A-9

Announcement	Fragment and Text
a44	<p>f370 These are entries in your list.</p> <p>f333 To add entries to the list or to change status of list, press 1.</p> <p>f371 To rewind to current entry, press 2. To rewind to previous entries, press 2 as many times as necessary. To continue playback of list, press 3.</p> <p>f292 Louder, press 4. Softer, press 7. Faster, press 9. Slower, press 8.</p> <p>f372 To skip to next entry, press pound. To delete current entry, press star D.</p> <p>f235 To restart at the activity menu, press star R. To transfer to another extension, press star T.</p> <p>f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a45	<p>f327 You are creating a mailing list</p> <p>f329 You have not yet entered enough characters to identify a specific subscriber. To enter the letter Q, press 7; for Z press 9.</p> <p>f484 Enter more characters followed by the pound sign, if you just completed entering the last name, enter the first name.</p> <p>f225 and pound sign.</p> <p>f235 To restart at the activity menu, press star R. To transfer to another extension, press star T.</p> <p>f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a46	f815 You are administering your personal greetings.
a47	<p>f339 To replay the last few seconds, press 5. To advance a few seconds, press 6.</p> <p>f292 Louder, press 4. Softer, press 7. Faster, press 9. Slower, press 8.</p>
a48	<p>f549 You are administering your attendant menu. To create attendant menu, press 1.</p> <p>f235 To restart at the activity menu, press star R. To transfer to another extension, press star T.</p> <p>f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a49	<p>f108 You are recording a message.</p> <p>f13 To record, press 1. After recording, press 1 again.</p> <p>f292 Louder, press 4. Softer, press 7. Faster, press 9. Slower, press 8.</p>

A-10 Standard Announcements

Announcement	Fragment and Text
a50	f299 You are administering your greeting. f36 To record a personal greeting, press 1. f235 To restart at the activity menu press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a51	f306 You are changing your password. f210 Please enter a new password f224 and pound sign. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a52	f591 To change your outcalling phone number, press one. To hear further instructions on programming a pager, press y. To return to outcalling administration, press n.
a53	f566 You are responding to an outcall notifying you of new messages. f551 To access your messages, f278 Please enter extension. f224 and pound sign. f543 To avoid further notification of these messages, press star pound. f567 Either logging m or pressing star pound will result in the outcall being canceled for the new messages currently in your mailbox. If additional new messages arrive, another outcall will be scheduled.
a54	f347 You are adding a list. f362 If you own the list, press pound. If someone else owns the list f364 enter owner's extension f224 and pound sign. f298 To specify owner by name, press star A.
a55	f347 You are adding a list. f362 If you own the list, press pound. If someone else owns the list f365 enter owner's name f224 and pound sign. f297 To specify owner by extension, press star A.
a56	f220 Enter password f224 and pound sign.

Announcement	Fragment and Text
a57	<p>f307 You are playing announcements.</p> <p>f221 Enter announcement id and pound sign. Refer to admin manual for correct id.</p> <p>f235 To restart at the activity menu, press star R. To transfer to another extension, press star T.</p> <p>f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a58	<p>f308 You are playing announcement fragments.</p> <p>f222 Enter fragment id and pound sign. Refer to admin manual for correct id.</p> <p>f235 To restart at the activity menu, press star R. To transfer to another extension, press star T.</p> <p>f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a59	<p>f309 You are playing names.</p> <p>f223 Please enter extension</p> <p>f224 and pound sign.</p> <p>f235 To restart at the activity menu, press star R. To transfer to another extension, press star T.</p> <p>f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a60	<p>f278 Please enter extension</p> <p>f224 and pound sign.</p>
a61	<p>f357 You are choosing between subscribers whose names match your entry. To indicate no subscribers match, delete entry by pressing star D. To change to extension addressing and delete your entry, press star A.</p> <p>f235 To restart at the activity menu, press star R. To transfer to another extension, press star T.</p> <p>f80 To have system wait, press star W. If finished, please hang up or to disconnect AUDIX, press star star X.</p>

A-12 Standard Announcements

Announcement	Fragment and Text
a62	f323 You are responding to a piece of incoming mail. f486 To reply to sender by voice mail, press 1. f41 To forward message with comment at beginning, press 2. f126 To forward message with comment at end, press 3. f8 To record a new message, press 4. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a63	f348 You are specifying a mailing list to review. f111 Please enter list id f224 and pound sign. f366 To specify a different owner by extension, press star D. f363 To approve the list you are creating, press pound. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a64	f348 You are specifying a mailing list to review. f111 Please enter list id f224 and pound sign. f367 To specify a different owner by name, press star D. f363 To approve the list you are creating, press pound. f235 To restart at the activity menu press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a65	f348 You are specifying a mailing list to review. f362 If you own the list press pound. If someone else owns the list f364 enter owner's extension f224 and pound sign. f298 To specify owner by name, press star A. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.

Announcement	Fragment and Text
a66	<p>f348 You are specifying a mailing list to review.</p> <p>f362 If you own the list, press pound. If someone else owns the list</p> <p>f365 enter owner's name</p> <p>f224 and pound sign.</p> <p>f297 To specify owner by extension, press star A.</p> <p>f235 To restart at the activity menu, press star R. To transfer to another extension, press star T.</p> <p>f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a67	<p>f348 You are specifying a mailing list to review.</p> <p>f329 You have not yet entered enough characters to identify a specific subscriber. To enter the letter Q, press 7; for Z press 9.</p> <p>f484 Enter more characters followed by the pound sign; if you just completed entering the last name, enter the first name.</p> <p>f225 and pound sign.</p> <p>f148 For extension addressing, press star A.</p> <p>f235 To restart at the activity menu, press star R. To transfer to another extension, press star T.</p> <p>f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a68	<p>f518 You are creating a voice message which will be delivered to the person specified in your message as soon as possible. Please be aware that in order to forward this message to the recipient, someone will listen to the name and number portion.</p> <p>f13 To record, press 1. After recording, press 1 again.</p> <p>f304 To playback message, press 2-3. To delete your message, press star D. To approve your message, press pound.</p> <p>f292 Louder, press 4. Softer, press 7. Faster, press 9. Slower, press 8.</p> <p>f497 To review your message, press star 1.</p> <p>f46 To access your mailbox, press star R.</p> <p>f117 To reach the covering extension, press star zero.</p> <p>f291 To transfer to another extension, press star T.</p> <p>f80 To have system wait, press star W. If finished, please hang up or to disconnect AUDIX, press star star X.</p>

A-14 Standard Announcements

Announcement	Fragment and Text
a69	<p>f517 You are entering the number of the person for whom you are leaving a message. This may be the complete number you dialed or simply the extension. For a faster response, terminate your entry with a pound sign.</p> <p>f46 To access your mailbox, press star R.</p> <p>f117 To reach the covering extension, press star zero.</p> <p>f291 To transfer to another extension, press star T.</p> <p>f80 To have system wait, press star W. If finished, please hang up or to disconnect AUDIX, press star star X.</p> <p>f516 To leave a message that will be delivered as soon as possible,</p> <p>f380 Please Wait.</p>
a70	<p>f517 You are entering the number of the person for whom you are leaving a message. This may be the complete number you dialed or simply the extension. For a faster response, terminate your entry with a pound sign.</p> <p>f46 To access your mailbox, press star R.</p> <p>f117 To reach the covering extension, press star zero.</p> <p>f291 To transfer to another extension, press star T.</p> <p>f80 To have system wait, press star W. If finished, please hang up or to disconnect AUDIX, press star star X.</p> <p>f274 Please make entry soon. or be disconnected</p>
a71	<p>f517 You are entering the number of the person for whom you are leaving a message. This may be the complete number you dialed or simply the extension. For a faster response, terminate your entry with a pound sign.</p> <p>f46 To access your mailbox, press star R.</p> <p>f117 To reach the covering extension, press star zero.</p> <p>f291 To transfer to another extension, press star T.</p> <p>f80 To have system wait, press star W. If finished, please hangup or to disconnect AUDIX, press star star X.</p> <p>f515 To be transferred to an operator,</p> <p>f380 Please wait.</p>
a72	<p>f375 You are getting your incoming messages. To listen to the message, press 0. To respond to the message press 1.</p> <p>f376 To skip to the next header, press the pound sign. To listen to the header, rewind by pressing two, then play by pressing three. To skip to the next category, press star pound.</p> <p>f577 To hold the message in its current category, press star star H</p> <p>f339 To replay the last few seconds press 5. To advance a few seconds, press 6.</p> <p>f292 Louder, press 4. Softer, press 7. Faster, press 9. Slower, press 8.</p> <p>f377 To delete message, press star D.</p>

Announcement	Fragment and Text
a73	<p>f378 You are checking the status of your outgoing messages.</p> <p>f474 To listen, press 0. To change or send again, press 1.</p> <p>f376 To skip to the next header, press the pound sign. To listen to the header, rewind by pressing two, then play by pressing three. To skip to the next category, press star pound.</p> <p>f339 To replay the last few seconds, press 5. To advance a few seconds, press 6.</p> <p>f292 Louder, press 4. Softer, press 7. Faster, press 9. Slower, press 8.</p> <p>f377 To delete message, press star D.</p>
a74	<p>f819 You are scanning your personal greetings.</p> <p>f781 To skip to the next greeting, press the pound sign.</p> <p>f756 To listen to greeting NUMBER press 0.</p> <p>f760 To delete press star D.</p> <p>f758 To rewind to the previous greeting, press 2.</p> <p>f839 If finished, press star pound.</p> <p>f707 To replay the last few seconds, press 5. To advance a few seconds, press 6.</p> <p>f339 Louder, press 4. Softer, press 7. Faster, press 9. Slower, press 8.</p>
a75	<p>f385 To approve delivery time, press pound. To modify delivery time, press star D and listen for further instructions.</p>
a76	<p>f305 You are at the activity menu.</p> <p>f983 To record and send voice mail messages, press 1. To get messages, press 2. To record or change the greeting heard by callers, press 3.</p> <p>f48 To check your outgoing messages, press 4. To administer other personal options, press 5. To change outcalling information, press 6. To automatically scan incoming messages, press 7. To re-logon, press star star R.</p> <p>f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a77	<p>f305 You are at the activity menu.</p> <p>f984 To record and send voice mail messages, press one. To get messages, press two. To administer attendant menu, press 3.</p> <p>f48 To check your outgoing messages, press 4. To administer other personal options, press 5. To change outcalling information, press 6. To automatically scan incoming messages, press 7. To re-logon, press star star R.</p> <p>f291 To transfer to another extension, press star T.</p> <p>f282 To have system wait press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>

A-16 Standard Announcements

Announcement	Fragment and Text
a78	<p>f324 You are selecting which greeting will be played to callers. If you want your personal greeting to be played, press Y for yes. If you press N for no, the system greeting will be used.</p> <p>f235 To restart at the activity menu, press star R. To transfer to another extension, press star T.</p> <p>f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a79	<p>f536 You are specifying your outcalling time period. The time you specify will be restricted by the times allowed by the system administrator.</p> <p>f545 To delete own time press star D.</p> <p>f235 To restart at the activity menu, press star R. To transfer to another extension, press star T.</p> <p>f117 To reach the covering extension, press star zero.</p> <p>f282 To have system wait, press star W. To access the names or number directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a80	<p>f536 You are specifying your outcalling time period. The time you specify will be restricted by the times allowed by the system administrator.</p> <p>f535 For outcalling any time, press 1. For outcalling during prime time, press 2. To specify your times, press 3. For system outcalling schedule, press 4.</p> <p>f235 To restart at the activity menu, press star R. To transfer to another extension, press star T.</p> <p>f117 To reach the covering extension, press star zero.</p> <p>f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a81	<p>f378 You are checking the status of your outgoing messages.</p> <p>f376 To skip to the next header, press the pound sign. To listen to the header, rewind by pressing two, then play by pressing three. To Skip to the next category, press star pound.</p> <p>f292 Louder, press 4. Softer, press 7. Faster, press 9. Slower, press 8.</p> <p>f379 To delete status information, press star D.</p>
a82	<p>f374 You are choosing whether to file this message. To file a copy, press Y for yes. To send without filing a copy, press N for no.</p> <p>f235 To restart at the activity menu, press star W. To transfer to another extension, press star T.</p> <p>f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>

Announcement	Fragment and Text
a83	<p>f326 You are doing system administration. To record names press 4. To play names, press 5. To record a machine name, press 6. To play a machine name press 7. To record fragments, press 1. To play fragments, press 2. To play announcements, press 3.</p> <p>f235 To restart at the activity menu, press star R. To transfer to another extension, press star T.</p> <p>f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a84	<p>f382 You are scheduling your message for delivery.</p> <p>f488 To specify immediate delivery, press pound.</p> <p>f340 Otherwise Enter the hour, one through twelve, then two digits for the minutes, then A for AM or P for PM, and the pound sign.</p>
a85	<p>f323 You are responding to a piece of incoming mail.</p> <p>f486 To reply to sender by voice mail, press 1.</p> <p>f41 To forward message with comment at beginning, press 2.</p> <p>f126 To forward message with comment at end, press 3.</p> <p>f8 To record a new message, press 4.</p> <p>f163 To call sender, press zero.</p> <p>f235 To restart at the activity menu press star R. To transfer to another extension, press star T.</p> <p>f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang Up or to disconnect AUDIX, press star star X.</p>
a86	<p>f378 You are checking the status of your outgoing messages.</p> <p>f381 To listen to the message, press 0. To re-record message before delivery, press 1.</p> <p>f376 To skip to the next header, press the pound sign. To listen to the header, rewind by pressing two, then play by pressing three. To skip to the next category, press star pound.</p> <p>f339 To replay the last few seconds press 5. To advance a few seconds, press 6.</p> <p>f292 Louder, press 4. Softer, press 7. Faster, press 9. Slower, press 8.</p> <p>f377 To delete message, press star D.</p>
a87	<p>f278 Please enter extension</p> <p>f224 and pound sign.</p> <p>f330 Or enter just the pound sign if it's your phone.</p>

A-18 Standard Announcements

Announcement	Fragment and Text
a88	f818 You have just recorded f754 Greeting NUMBER f766 To use this greeting for all calls, press 1. f913 If finished, press pound.
a89	f818 You have just recorded f754 Greeting NUMBER f767 To use this greeting for all calls, press 0. For busy calls, press 1. For no answer calls, press 2.
a90	f384 Please enter number of month, then two digits for day, and pound sign.
a91	f818 You have just recorded f754 Greeting NUMBER f764 To use this greeting for all calls, press 0. For internal calls, press 1. For external calls, press 2.
a92	f910 You are playing an announcement which needs additional input before it can be played. f384 Please enter number of month, then two digits for day, and pound sign.
a93	f307 You are playing announcements. f254 To play the active version, press 1. f338 To play the admin version, press 2 f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a94	f308 You are playing announcement fragments. f254 To play the active version, press 1. f338 To play the admin version, press 2. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.

Announcement	Fragment and Text
a95	f309 You are playing names. f279 Enter announcement set and pound sign. f280 For admin version, press 2. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a96	f503 You are administering your attendant menu. f502 To record attendant menu, press 1. To listen to attendant menu, press 0. f550 To rewind your attendant menu, press two. To delete it, press star D. To stop playback of your attendant menu, press three. f339 To replay the last few seconds, press 5. To advance a few seconds, press 6. f292 Louder, press 4. Softer, press 7. Faster, press 9. Slower, press 8. f105 To restart at the activity menu, press star R. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a97	f529 You are changing your outcalling options. f527 To change number, press 1. To change times, press 2. For instructions on entering your outcalling number, press 3. f528 To turn on, press y. To turn off, press n. f105 To restart at the activity menu, press star R. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a98	f11 You are recording machine names. f6 Enter machine voice ID. f224 and pound sign. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a99	f549 You are administering your attendant menu. To create attendant menu, press 1. f105 To restart at the activity menu, press star R. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.

A-20 Standard Announcements

Announcement	Fragment and Text
a100	<p>f138 You are listening to machine names. f6 Enter machine voice ID. f224 and pound sign. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a101	<p>f518 You are creating a voice message which will be delivered to the person specified in your message as soon as possible. Please be aware that in order to forward this message to the recipient, someone will listen to the name and number portion. f13 To record, press 1. After rerecording, press 1 again. f304 To playback message, press 2-3. To delete your message, press star D. To approve your message, press pound. f292 Louder, press 4. Softer, press 7. Faster, press 9. Slower, press 8. f497 To review your message, press star 1. f555 To access your mailbox, press star R. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a102	<p>f517 You are entering the number of the person for whom you are leaving a message. This maybe the complete number you dialed or simply the extension. For a faster response, terminate your entry with a pound sign. f555 To access yur mailbox, press star R. f80 To have system wait, press star W. If finishe, please hang up or to disconnect AUDIX, press star star X. f516 To leave a message that will be delivered as soon as possible, f380 Please wait.</p>
a103	<p>f517 You are entering the number of the person for whom you are leaving a message. This may be the complete number you dialed or simply the extension. For a faster response, terminate your entry with a pound sign. f555 To access your mailabox, press star R. f80 To have system wait, press star W. If finished, please hang up or to disconnect AUDIX, press star star X. f274 Please make entry soon, or be disconnected.</p>

Announcement	Fragment and Text
a104	<p>f517 You are entering the number of the person for whom you are leaving a message. This may be the complete number you dialed or simply the extension. For a faster response, terminate your entry with a pound sign.</p> <p>f555 To access your mailbox, press star R.</p> <p>f80 To have system wait, press star W. If finished, please hang up or to disconnect AUDIX, press star star X.</p> <p>f515 To be transferred to an operator,</p> <p>f380 Please wait.</p>
a105	<p>f536 You are specifying your outcalling time period. The time you specify will be restricted by the times allowed by the system administrator.</p> <p>f545 To delete own time, press star D.</p> <p>f105 To restart at the activity menu, press star R.</p> <p>f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a106	<p>f536 You are specifying your outcalling time period. The time you specify will be restricted by the times allowed by the system administrator.</p> <p>f535 For outcalling any time, press 1. For outcalling during prime time, press 2. To specify your times, press 3. For system outcalling schedule, press 4.</p> <p>f105 To restart at the activity menu, press star R.</p> <p>f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a107	<p>f138 You are listening to machine names.</p> <p>f279 Enter announcement set and pound sign.</p> <p>f280 For admin version, press 2.</p> <p>f235 To restart at the activity menu, press star R. To transfer to another extension, press star T.</p> <p>f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a108	<p>f529 You are changing your outcalling options.</p> <p>f527 To change number, press 1. To change times, press 2. For instructions on entering your outcalling number, press 3.</p> <p>f528 To turn on, press y. To turn off, press n.</p> <p>f235 To restart at the activity menu, press star R. To transfer to another extension, press star T.</p> <p>f117 To reach the covering extension, press star zero.</p> <p>f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>

A-22 Standard Announcements

Announcement	Fragment and Text
a109	f669 With the current settings, this login announcement will be interruptible and the login announcement has an expiration date of. DATE
a110	f663 Message waiting notification is not active and this message has an expiration date of. DATE
a111	f668 With the current settings, this login announcement will be non-interruptible and the login announcement has an expiration date of. DATE
a112	f664 Message waiting notification is active and this message has an expiration date of. DATE
a113	f305 You are at the activity menu. f23 To record messages, press 1. To get messages, press 2. To administer your greeting, press 3. f48 To check your outgoing messages, press 4. To administer other personal options, press 5. To change outcalling information, press 6. To automatically scan incoming messages, press 7. To re-logon, press star star R. f291 To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a114	f305 You are at the activity menu. f984 To record and send voice mail messages, one. To get messages, press two. To administer attendant menu, press 3. f48 To check your outgoing messages, press 4. To administer other personal options, press 5. To change outcalling information, press 6. To automatically scan incoming messages, press 7. To re-logon, press star star R. f291 To transfer to another extension, press star T. f117 To reach the covering extension, press star zero. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.

Announcement	Fragment and Text
a115	<p>f305 You are at the activity menu.</p> <p>f986 To record and send voice mail messages, press one. To get messages, press two. To administer personal greetings, press 3.</p> <p>f48 To check your outgoing messages, press 4. To administer other personal options, press 5. To change outcalling information, press 6. To automatically scan incoming messages, press 7. To re-logon, press star star R</p> <p>f291 To transfer to another extension, press star T.</p> <p>f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a116	<p>f493 You are requesting a transfer.</p> <p>f562 Enter the NUMBER</p> <p>f563 digit extension</p> <p>f119 you wish to call</p> <p>f224 and pound sign.</p> <p>f115 To transfer using names instead, press star A.</p> <p>f105 To restart at the activity menu, press star R.</p> <p>f117 To reach the covering extension, press star zero.</p> <p>f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a117	<p>f493 You are requesting a transfer.</p> <p>f562 Enter the NUMBER</p> <p>f563 digit extension</p> <p>f119 you wish to call</p> <p>f224 and pound sign.</p> <p>f115 To transfer using names instead, press star A.</p> <p>f105 To restart at the activity menu, press star R.</p> <p>f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>

Announcement	Fragment and Text
al18	<p>f847 You are automatically scanning your incoming messages. To listen to the message, press zero. To respond to or forward the message, press one.</p> <p>f849 To skip to the next message, press the pound sign. To listen to the header, rewind by pressing two, then play by pressing three. To skip to the next category, press star pound.</p> <p>f577 To hold the message in its current category, press star star H</p> <p>f339 To replay the last few seconds, press 5. To advance a few seconds, press 6.</p> <p>f292 Louder, press 4. Softer, press 7. Faster, press 9. Slower, press 8.</p> <p>f377 To delete message, press star D.</p>
al19	<p>f305 You are at the activity menu.</p> <p>f985 To record and send voice mail messages, press 1. To get messages, press 2.</p> <p>f48 To check your outgoing messages, press 4. To administer other personal options, press 5. To change outcalling information, press 6. To automatically scan incoming messages, press 7. To re-logon, press star star R.</p> <p>f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a120	<p>f305 You are at the activity menu.</p> <p>f984 To record and send voice mail messages, press one. To get messages, press two. To administer attendant menu, press 3.</p> <p>f48 To check your outgoing messages, press 4. To administer other personal options, press 5. To change outcalling information, press 6. To automatically scan incoming messages, press 7. To re-logon, press star star R.</p> <p>f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a121	<p>f305 You are at the activity menu.</p> <p>f986 To record and send voice mail messages, press one. To get messages, press two. To record or change the greetings heard by callers, press 3.</p> <p>f48 To check your outgoing messages, press 4. To administer other personal options, press 5. To change outcalling information, press 6. To automatically scan incoming messages, press 7. To re-logon, press star star R.</p> <p>f291 To transfer to another extension, press star T.</p> <p>fl17 To reach the covering extension, press star zero.</p> <p>f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>

Announcement	Fragment and Text
a122	f848 You are automatically scanning your incoming messages. To listen to the message, press zero. To respond to the message, press one. f849 To skip to the next message, press the pound sign. To listen to the header, rewind by pressing two, then play by pressing three. To skip to the next category, press star pound. f577 To hold the message in its current category, press star star H f339 To replay the last few seconds, press 5. To advance a few seconds, press 6. f292 Louder, press 4. Softer, press 7. Faster, press 9. Slower, press 8. f377 To delete message, press star D.
a123	f323 You are responding to a piece of incoming mail. f41 To forward message with comment at beginning, press 2. f126 To forward message with comment at end press 3. f8 To record a new message, press 4. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a124	f491 You are getting your incoming messages. To listen to the message, press 0. To respond to the message, press 1. f376 To skip to the next header, press the pound sign. To listen to the header, rewind by pressing two, then play by pressing three. To skip to the next category, press star pound. f577 To hold the message in its current category, press star star H. f339 To replay the last few seconds, press 5. To advance a few seconds, press 6. f292 Louder, press 4. Softer, press 7. Faster, press 9. Slower, press 8. f377 To delete message, press star D.
a125	f305 You are at the activity menu. f985 To record and send voice mail messages, press 1. To get messages, press 2. f48 To check your outgoing messages, press 4. To administer other personal options, press 5. To change outcalling information, press 6. To automatically scan incoming messages, press 7. To re-logon, press star star R. f291 To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.

A-26 Standard Announcements

Announcement	Fragment and Text
a126	<p>f323 You are responding to a piece of incoming mail.</p> <p>f486 To reply to sender by voice mail, press 1.</p> <p>f8 To record a new message, press 4.</p> <p>f235 To restart at the activity menu, press star R. To transfer to another extension, press star T.</p> <p>f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a127	<p>f305 You are at the activity menu.</p> <p>f983 To record and send voice mail messages, press 1. To get messages press 2. To record or change the greeting heard by callers, press 3.</p> <p>f48 To check your outgoing messages, press 4. To administer other personal options, press 5. To change outcalling information, press 6. To automatically scan incoming messages, press 7. To re-logon, press star star R.</p> <p>f291 To transfer to another extension, press star T.</p> <p>fl17 To reach the covering extension, press star zero.</p> <p>f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a128	<p>f323 You are responding to a piece of incoming mail.</p> <p>f8 To record a new message, press 4.</p> <p>f235 To restart at the activity menu, press star R. To transfer to another extension, press star T.</p> <p>f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a129	<p>f305 You are at the activity menu.</p> <p>f985 To record and send voice mail messages, press 1. To get messages press 2.</p> <p>f48 To check your outgoing messages, press 4. To administer other personal options, press 5. To change outcalling information, press 6. To automatically scan incoming messages, press 7. To re-logon, press star star R.</p> <p>f291 To transfer to another extension, press star T.</p> <p>fl17 To reach the covering extension, press star zero.</p> <p>f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>

Announcement	Fragment and Text
a130	f659 Message waiting notification will alert all local subscribers of this message. This option should be used sparingly, for it can impact system performance.
a131	f725 You are adding entries to your personal directory. f832 Please enter extension and pound sign. f833 To delete current entry, press star D. f58 For name addressing, press star A. f913 If finished, press pound.
a132	f725 you are adding entries to your personal directory. f799 Enter last name f224 and pound sign. f833 To delete current entry, press star D. f148 For extension addressing, press star A. f913 If finished, press pound.
a133	f657 You are choosing options for this broadcast message.
a134	f654 the message will be broadcast and private.
a135	f649 the message will be broadcast.
a136	f723 You are administering your personal directory. f706 To add entries, press 1. To review all entries, press 2. To review a specific entrie, press 3. f913 If finished, press pound.
a137	f325 You are administering your lists. To create a mailing list, press 1. To play a summary of all your lists, press 2. To review a particular list, press 3.
a138	f665 You are choosing options for this login announcement.
a139	f650 the message will be a login announcement.
a140	f652 A broadcast message is delivered to every subscriber on this machine. You may also address a broadcast message to subscribers on other machines.
a141	f655 A login announcement will be played each time any subscriber logs onto this machine. You may also address a login message to subscribers on other machines.
a142	f670 Non-interruptible status forces each subscriber to listen to the entire login announcement every time they log onto this machine.

A-28 Standard Announcements

Announcement	Fragment and Text
a143	<p>f670 Non-interruptible status forces each subscriber to listen to the entire login announcement every time they log onto this machine.</p> <p>f626 To specify expiration date, press 2.</p> <p>f671 Expiration date specifies the last day this login announcement will be available to subscribers. The default expiration date is the second day after the scheduled delivery date.</p> <p>f661 To approve these options, press pound.</p> <p>f774 If you have addressed this message and wish to deliver it immediately, press star star pound.</p>
a144	<p>f646 A priority message will be delivered before other messages and will be flagged for special attention in the recipient's mailbox.</p>
a145	<p>f645 Private messages cannot be forwarded by the recipients.</p>
a146	<p>f662 Message waiting notification is active.</p> <p>f628 To deactivate message waiting notification, press 1.</p> <p>f659 Message waiting notification will alert all local subscribers of this message. This option should be used sparingly, for it can impact system performance.</p> <p>f626 To specify expiration date press 2.</p>
a147	<p>f288 You are in the names directory. To find a subscriber's extension, enter the last name followed by the pound sign. To enter the letter Q, press 7; for Z press 9. To lookup by extension instead press star A.</p> <p>f277 To exit directory, press pound.</p> <p>f105 To restart at the activity menu, press star R.</p> <p>f80 To have system wait, press star W. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a148	<p>f666 With the current settings, this login announcement will be non-interruptible.</p>
a149	<p>f643 You are choosing options for this message. There are no options currently set.</p> <p>f612 To make private, press 1.</p> <p>f645 Private messages cannot be forwarded by the recipients.</p>
a150	<p>f610 You are recoding your name. After you record your name, you can access other AUDIX features. As you use AUDIX your name will be included in system announcements that you and other people will hear. Press 1 and at the tone, please speak your first and last name as you would like others to hear it. After speaking your name press 1 again.</p>

Announcement	Fragment and Text
a151	f611 You are recording your name. To record your name, press 1. After recording, press 1 again. To playback name press 2-3. To approve, press pound.
a152	f322 You are in the numbers directory. To find a subscriber's name enter the extension followed by the pound sign. To look up by name instead, press star A. f277 To exit directory, press pound. f105 To restart at the activity menu, press star R. f80 To have system wait, press star W. If finished, please hang up or to disconnect AUDIX, press star star X.
a153	f838 You are selecting which messages will receive outcalls.
a154	f916 To send message, press pound. Or enter a delivery option. To hear a list of options press zero.
a155	f644 You are choosing options for this message. With the current settings,
a156	f648 the message will be priority.
a157	f726 You are reviewing all entries in your personal directory. f372 To skip to next entry, press pound. To delete current entry, press star D. f852 To rewind to the current entry, press two. To rewind to previous entries, press two as many times as necessary.
a158	f729 You are reviewing a specific entry in your personal directory. To delete the current entry, press star D. To review another entry, enter the alias followed by the pound sign.
a159	f305 You are at the activity menu. f986 To record and send voice mail messages, press one. To get messages, press two. To record or change the greetings heard by callers, press 3. f48 To check your outgoing messages, press 4. To administer other personal options, press 5. To change outcalling information, press 6. To automatically scan incoming messages, press 7. To re-logon, press star star R. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.

A-30 Standard Announcernents

Announcement	Fragment and Text
a160	<p>f660 Expiration date specifies the last day this broadcast message will be available to subscribers. The expiration date does not apply to a broadcast message already received by a subscriber and saved in their mailbox. The default expiration date is the second day after the scheduled delivery date.</p> <p>f661 To approve these options, press pound.</p> <p>f774 If you have addressed this message and wish to deliver it immediately, press star star pound.</p>
a161	<p>f800 You are specifying the expiration date.</p> <p>f660 Expiration date specifies the last day this broadcast message will be available to subscribers. The expiration date does not apply to a broadcast message already received by a subscriber and saved in their mailbox. The default expiration date is the second day after the scheduled delivery date.</p> <p>f384 Please enter number of month, then two digits for day, and pound sign.</p> <p>f831 To exit the expiration date options, press star pound.</p> <p>f774 If you have addressed this message and wish to deliver it immediately, press star star pound.</p>
a162	<p>f800 You are specifying the expiration date.</p> <p>f671 Expiration date specifies the last day this login announcement will be available to subscribers. The default expiration date is the second day after the scheduled delivery date.</p> <p>f384 Please enter number of month, then two digits for day, and pound sign.</p> <p>f831 To exit the expiration date options, press star pound.</p> <p>f774 If you have addressed this message and wish to deliver it immediately, press star star pound.</p>
a163	<p>f671 Expiration date specifies the last day this login announcement will be available to subscribers. The default expiration date is the second day after the scheduled delivery date.</p> <p>f661 To approve these options, press pound.</p> <p>f774 If you have addressed this message and wish to deliver it immediately, press star star pound.</p>
a164	<p>f651 the message will be private and priority.</p>
a165	<p>f703 You are at subscriber administration.</p> <p>f700 To administer mailing list press 1. To administer personal directory, press 2.</p> <p>f701 To change your password, press 4.</p>

Announcement	Fragment and Text
a166	f703 You are at subscriber administration. f700 To administer mailing lists, press 1. To administer personal directory, press 2. f701 To change your password, press 4. f702 To record your name, press 5.
a167	f736 You are recording your name. As you use AUDIX your name will be included in system announcements that you and other people will hear. f608 At the tone, please speak your name. After speaking your name, press 1.
a168	f323 You are responding to a piece of incoming mail. f486 To reply to sender by voice mail, press 1. f8 To record a new message, press 4. f163 To call sender, press zero. f235 To re-start at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a169	f323 You are responding to a piece of incoming mail. f8 To record a new message, press 4. f163 To call sender, press zero. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a170	f323 You are responding to a piece of incoming mail. f41 To forward message with comment at beginning, press 2. f126 To forward message with comment at end, press 3. f8 To record a new message, press 4. f163 To call sender, press zero. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.

A-32 Standard Announcements

Announcement	Fragment and Text
a171	f493 You are requesting a transfer. f987 Enter last name of the person f119 you wish to call f224 and pound sign. f290 If you wish to specify a non-AUDIX subscriber, first change to extension addressing by pressing star A. f105 To restart at the activity menu, press star R. f117 To reach the covering extension, press star zero. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a172	f493 You are requesting a transfer. f987 Enter last name of the person f119 you wish to call f224 and pound sign. f290 If you wish to specify a non-AUDIX subscriber, first change to extension addressing by pressing star A. f105 To restart at the activity menu, press star R. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hangup or to disconnect AUDIX, press star star X.
a173	NAME
a174	f822 NAME As you use AUDIX your name will be included in system announcements that you and other people will hear. At the tone, please speak your name. After speaking your name, press one.
a175	NAME f146 To continue, press pound. f143 To step back again, press 2.
a176	NAME f146 To continue, press pound.
a177	f680 NAME is busy. Sorry, you cannot leave a message now because this user's mailbox is full.
a178	f197 NAME cannot step back
a179	f75 NAME To skip, press pound. To delete, press star D. f294 To add entries, press 1.

Announcement	Fragment and Text	
a180	f586	NAME To skip, press pound.
a181	f218	NAME deleted
a182	f679	NAME is not available. Sorry, you cannot leave a message now because this user's mailbox is full.
a183 f168	f63 f601 f160 ELSE messages. ENDIF	NAME NUMBER new Priority IF (Number==1) THEN message ELSE messages. ENDIF
a184	f63 f345 f160 F168 f17 f601 f160 f168	NAME NUMBER + NUMBER(2) — NUMBER= priority number new — NUMBER(2) non-priority number Voice mail IF (NUMBER +NUMBER(2) ==1) THEN message ELSE messages. ENDIF including NUMBER Priority IF (NUMBER ==1) THEN message ELSE messages. ENDIF

A-34 Standard Announcements

Announcement	Fragment and Text
a185	NAME NUMBER f63 new f345 Voice mail IF (NUMBER=1) THEN f160 message ELSE f168 messages. ENDIF
a186	NAMEEXT
a187	NAMEEXT f74 deleted.
a188	NAMEEXT f722 was not added to your personal directory.
a189	NAMEEXT f728 deleted.
a190	NUMBER + NUMBER(2) — NUMBER = priority number f63 new — NUMBER(2) = non-priority number f345 Voice mail IF (NUMBER + NUMBER(2) ==1) THEN f160 message ELSE f168 messages. ENDIF f17 including NUMBER f601 Priority IF(NUMBER==1) THEN f160 message ELSE f168 messages. ENDIF
a191	f158 Transfer cannot be completed. f236 Try again f109 later. f95 Please disconnect.

Announcement	Fragment and Text	
a192	f234 f389 f388	To respond or forward press 1. To delete, press star D. To skip, press pound.
a193	f562 f563 f224 f117 f115	Enter the NUMBER digit extension and pound sign. To reach the covering extension, press star zero. To transfer using names instead, press star A.
a194	f562 f563 f224 f117 f115 f335	Enter the NUMBER digit extension and pound sign. To reach the covering extension, press star zero. To transfer using names instead, press star A. when finished, press pound.
a195	f562 f563 f224 f115	Enter the NUMBER digit extension and pound sign. To transfer using names instead, press star A.
a196	f562 f563 f224 f115 f335	Enter the NUMBER digit extension and pound sign. To transfer using names instead, press star A. when finished, press pound.
a197	f547	Good-bye
a198	f71	To leave a message, wait for the tone.
a199	f592 f81 f593 f81 f173 f224	AUDIX passwords must now be NUMBER digits. Please choose a new password of NUMBER(2) digits. Please enter new password and pound sign.
a200	f105 f238	To restart at the activity menu, press star R. To review another list,

A-36 Standard Announcements

Announcement	Fragment and Text	
a201	f213 f224	Reenter password and pound sign.
a202	f18 f8	To forward with comment, press 2. To record a new message, press 4.
a203	f41 f126 f8	To forward message with comment at beginning, press 2. To forward message with comment at end, press 3. To record a new message, press 4.
a204	f486 f8	To reply to sender by voice mail, press 1. To record a new message, press 4.
a205	f8	To record a new message, press 4.
a206	f252 f389 f388	To respond to this message, press 1. To delete, press star D. To skip, press pound.
a207	f930	Accessed Messages
a208	f625	To activate message waiting notification, press 1.
a209	f625 f659 f626	To activate message waiting notification, press 1. Message waiting notification will alert all local subscribers of this message. This option should be used sparingly, for it can impact system performance. To specify expiration date, press 2.
a210	f246 f2 f602 f217	Message addressed to NAME IF (NUMBER>0) THEN and NUMBER IF (NUMBER=1) THEN other ELSE others ENDIF ENDIF
a211	f336 f247	To review addressees, press star 1. To add to list,
a212	f334	When finished addressing, press pound.

Announcement	Fragment and Text	
a213	f464 f224	Enter extensions and pound sign.
a214	f465 f224	Enter last name and pound sign.
a215	f832 f708	Please enter extension and pound sign. If finished adding entries, press pound.
a216	f799 f224 f708	Enter last name and pound sign. If finished adding entries, press pound.
a217	f464 f135	Enter extensions and pound sign.
a218	f464 f135 f335	Enter extensions and pound sign. when finished, press pound.
a219	f464 f135 f121	Enter extensions and pound sign. When finished, approve list by pressing pound.
a220	f131	To send to others not on your list,
a221	f465 f135	Enter last name and pound sign.
a222	f465 f135 f335	Enter last name and pound sign. When finished, press pound.
a223	f465 f135 f121	Enter last name and pound sign. When finished, approve list by pressing pound.
a224	f711 f712	Alias BUTTONS defined for NAME
a225	f711 f712 f728	Alias BUTTONS defined for NAMEEXT deleted.

Announcement	Fragment and Text
a226	f711 Alias BUTTONS f712 defined for NAMEEXT f197 cannot step back
a227	f631 Message waiting notification activated. f632 Expiration date will be DATE
a228	f711 Alias BUTTONS f712 defined for NAMEEXT f372 To skip to next entry, press pound. To delete current entry, press star D.
a229	f711 Alias BUTTONS f185 not found.
a230	f744 For all calls,... IF (NUMBER==0) THEN f776 the system greeting ELSE f754 Greeting NUMBER ENDIF f745 active.
a231	f716 Alias must be ten or fewer numerals.
a232	f716 Alias must be ten or fewer numerals. f727 Enter alias and pound sign.
a233	f717 Alias already defined.
a234	f709 Enter alias for NAME f224 and pound sign.

Announcement	Fragment and Text	
a235	f2 f63 f601 f160 f168	and NUMBER new Priority IF (NUMBER==1) THEN message ELSE messages. ENDIF
a236	f2 f602 f63 f345 f160 f168	and NUMBER other new Voice mail IF (NUMBER==1) THEN message ELSE messages. ENDIF
a237	f540 f524	and from TIME to TIME(2)
a238	f16 f224	Enter announcement id and pound sign.
a239	f627	To approve broadcast options press pound.
a240	f634	To approve login announcement options, press pound.
a241	f606	To re-record your name, press 1. To approve, press pound.
a242	f791 f792	Calls identified as busy and no answer. Calls identified as out-of-hours.
a243	f791 f793	Calls identified as busy and no answer. Calls not identified as out-of-hours.
a244	f790 f792	Calls identified as internal and external. Calls identified as out-of-hours.

A 4 0 **Standard Announcements**

Announcement	Fragment and Text	
a245	f790 f793	Calls identified as internal and external. Calls not identified as out-of-hours.
a246	f502 f105	To record attendant menu, press 1. To listen to attendant menu, press 0. To restart at the activity menu, press star R.
a247	f506	Menu approved and activated.
a248	f505	You have selected an invalid option.
a249	f27	To attach original, press Y for yes or N for no.
a250	f580	Cannot attach a private message
a251	f580 f581	Cannot attach a private message Press N now
a252	f504	Transferring to an operator,
a253	f508 f95	Attendant Service not available, try again later. Please disconnect.
a254	f843	To scan headers and messages press 1. To scan headers only, press 2. To scan messages only, press 3.
a255	f29	Returned to checking status of outgoing messages.
a256	f640	Message cannot be both a login announcement and priority.
a257	f641	Message cannot be both a login announcement and private.
a258	f272 f95	Contact administrator for help. Please disconnect.
a259	f642	Message cannot be both broadcast and a login announcement
a260	f639	Message cannot be both broadcast and priority.
a261	f31 f384	Date not understood. Please enter number of month, then two digits for day, and pound sign.

Announcement	Fragment and Text	
a262	f32	You must enter your extension to logon.
a263	f100	Invalid Entry.
a264	f35	Login incorrect
a265	f35 f236	Login incorrect. Try again
a266	f40 f383	Time not understood. Please enter hour, then two digits for minutes, then A for am or P for pm and pound sign.
a267	f13	To record, press 1. After recording, press 1 again.
a268	f683	Broadcaster has deleted this broadcast message.
a269	f682 f262	Broadcast message from NAME received TIME DATE a873(NUMBER) — Length of message in seconds
a270	f682 f262 f689	Broadcast message from NAME received TIME DATE a873(NUMBER) — Length of message in seconds Expiration time is TIME(2) DATE(2)
a271	f682 f262	Broadcast message from NAME received TIME DATE a873(NUMBER) — Length of message in seconds EXTENSION

A-42 Standard Announcements

Announcement	Fragment and Text	
a272	f682 f262 f689	Broadcast message from NAME received THEN DATE a873(NUMBER) — Length of message in seconds EXTENSION Expiration time is TIME(2) DATE(2)
a273	f693 f2 f602 f217	Broadcast message to all local subscribers IF (NUMBER>0) THEN and NUMBER IF (NUMBER-1) THEN other ELSE others ENDIF ENDIF
a274	f653	For broadcast options, press star M.
a275	f623	Broadcast
a276	f21 f389 f388	To listen, press 0. To delete, press star D. To skip, press pound.
a277	f917	To schedule delivery, press 3.
a278	f749 f776 f754 f745	For busy calls... IF (NUMBER==()) THEN the system greeting ELSE Greeting NUMBER ENDIF active.

Announcement	Fragment and Text	
a279	f513	Begin your message by saying the name and telephone number of the person you are calling. Someone will listen to the start of your message, and then forward the complete message to the person you called.
a280	f51	Entries deleted, please re-enter delivery time.
a281	f76	Deleted
a282	f43 f507 f239	Your call is being answered by AUDIX. The person you called is not available. To leave a message, use touch tones to re-enter the number you called. followed by the pound sign.
a283	f5	To record personal greeting, press 1. To listen to personal greeting, press 0. To select which greeting to use, press star pound.
a284	f42	Can only reply to messages from other subscribers.
a285	f56 f46 f973	Thank you for leaving your message. To access your mailbox, press star R. If you are finished, please hang up.
a286	f47 f262	Call from NAME received TIME DATE a873(NUMBER) — Length of message in seconds
a287	f47 f262 f86	Call from NAME received TIME DATE extension BUTTONS a873(NUMBER) — Length of message in seconds
a288	f43 f680	Your call is being answered by AUDIX. NAME is busy. Sorry, you cannot leave a message now because this user's mailbox is full.

A-44 Standard Announcements

Announcement	Fragment and Text	
A289	f43 f44	Your call is being answered by AUDIX. NAME is not available. To leave a message, wait for the tone.
a290	f43 f45	Your call is being answered by AUDIX. NAME is busy. To leave a message, wait for the tone.
a291	f43 f45 f112	Your call is being answered by AUDIX. NAME is busy. To leave a message, wait for the tone. Otherwise, for assistance, press zero now.
a292	f43 f44 f112	Your call is being answered by AUDIX. NAME is not available. To leave a message, wait for the tone. Otherwise, for assistance, press zero now.
a293	f43 f679	Your call is being answered by AUDIX. NAME is not available. Sorry, you cannot leave a message now because this user's mailbox is full.
a294	f156	Maximum length recorded.
a295	f50 f262 f86	Call NAME received TIME DATE extension BUTTONS a873(NUMBER) — Length of message in seconds
a296	f50 f262	Call received TIME DATE a873(NUMBER) — Length of message in seconds
a297	f507	The person you called is not available. To leave a message, use touch tones to re-enter the number you called.

Announcement	Fragment and Text	
a298	f507 f274	The person you called is not available. To leave a message, use touch tones to re-enter the number you called. Please make entry soon, or be disconnected.
a299	f511 f380	If you do not have a touch tone phone, Please wait.
a300	f794	To change identification to busy and no answer, press 2.
a301	f911	Enter buttons followed by pound
a302	f912	Enter number followed by pound.
a303	f630 f762	To change expiration date from DATE press 2.
a304	f795	To change to identification internal and external, press 1.
a305	f910 f911	You are playing an announcement which need additional input before it can be played Enter buttons followed by pound
a306	f910 f912	You are playing an announcement which need additional input before it can be played. Enter number followed by pound.
a307	f527 f528	To change number, press 1. To change times, press 2. For instructions on entering your outcalling number, press 3. To turn on, press y. To turn off, press n.
a308	f60	Changed
a309	f565	Outcall canceled for new messages currently in mailbox.
a310	f12	To re-record press 1. After recording, press 1 again. To delete, press star D. To playback press 2-3. To approve as is, press pound.
a311	f628	To deactivate message waiting notification, press 1.
a312	f76	Deleted.
a313	f931	Delivered Messages
a314	f801	To respond to this notification, press one. To delete, press star D. To Skip, press pound.

A-46 Standard Announcements

Announcement	Fragment and Text	
a316	f77	Deleted.
a317	f77 f173 f224	Deleted. Please enter new password and pound sign.
a318	f77 f22	Deleted To deliver now, press pound. To schedule delivery time enter hour, minutes, A or P, and pound sign.
a319	f706 f913	To add entries, press 1. To review all enteries, press 2. To review a specific entry, press 3. If finished, press pound.
a320	f705 f84 f83	Directory contains NUMBER IF (NUMBER==1) THEN entry. ELSE entries. ENDIF
a321	f724	Personal directory review completed.
a322	f140	Entry already deleted. To delete more entries, press star 1.
a323	f79	Deleted.
a324	f145	List has no entries.
a325	f538	Enter the ending hour, minutes, A or P, and pound sign.
a326	f472 f389	To approve, press pound. To record from here, press 1. To delete, press star D.
a327	f727 f833 f148 f913	Enter alias and pound sign. To delete current entry, press star D. For extension addressing, press star A. If finished, press pound.

Announcement	Fragment and Text	
a328	f77 f833 f58 f913	Enter alias and pound sign. To delete current entry, press star D. For name addressing, press star A. If finished, press pound.
a329	f727 f913	Enter alias and pound sign. If finished, press pound.
a330	f713 f708	Enter next extension and pound sign. If finished adding entries, press pound.
a331	f710 f708	Enter next name and pound sign. If finished adding entries, press pound.
a332	f85 f13	Erased To record, press 1. After recording, press 1 again.
a333	f632	Expiration date will be DATE
a334	f86 f552	extension BUTTONS is not authorized to receive messages.
a335	f86 f552 f553	extension BUTTONS is not authorized to receive messages. You may enter another number
a336	f86 f552 f95	extension BUTTONS is not authorized to receive messages. Please disconnect
a337	f86 f841	extension BUTTONS not defined
a338	f86 f202	extension not valid.

Announcement	Fragment and Text
a339	f748 For external calls... IF (NUMBER==()) THEN f776 the system greeting ELSE f754 Greeting NUMBER ENDIF f745 active.
a340	f971 To send, press #.
a341	f971 To send, press #. f774 If you have addressed this message and wish to deliver it immediately, press star star pound.
a342	f739 Message sent to all local subscribers. IF (NUMBER>0) THEN f2 and NUMBER IF (NUMBER==1) THEN f602 other ELSE f217 others ENDIF ENDIF
a343	f740 Private message sent to all local subscribers IF (NUMBER>0) THEN f2 and NUMBER IF (NUMBER==1) THEN f602 other ELSE f217 others ENDIF ENDIF

Announcement	Fragment and Text
a344	f741 Private, priority message sent to NAME IF (NUMBER>0) THEN f2 and NUMBER IF (NUMBER==1) THEN f602 other ELSE f217 others ENDIF ENDIF
a345	f743 Priority message sent to NAME IF (NUMBER>0) THEN f2 and NUMBER IF (NUMBER==1) THEN f602 other ELSE f217 others ENDIF ENDIF
a346	f474 To listen, press 0. To change or send again, press 1. f388 To skip, press pound.
a347	f932 Filed Messages
a348	f89 First message. f197 Cannot step back f142 To listen to the header, press 3.
a349	f118 Enter last name f224 and pound sign. f175 Please note only AUDIX subscribers can be specified by name.

Announcement	Fragment and Text
a350	f807 For busy... f2 and f812 no answer f814 calls. IF (NUMBER==0) THEN f776 the system greeting ELSE f754 Greeting NUMBER ENDIF f745 active.
a351	f807 For busy... f812 no answer f813 and out-of-hours f814 calls. IF (NUMBER==0) THEN f776 the system greeting ELSE f754 Greeting NUMBER ENDIF f745 active.
a352	f805 For internal... f2 and f810 external f814 calls. IF (NUMBER==0) THEN f776 the system greeting ELSE f754 Greeting NUMBER ENDIF f745 active.

Announcement	Fragment and Text	
a353	f805 f810 f813 f814 f776 f754 f745	For internal... external and out-of-hours calls. IF (NUMBER==0) THEN the system greeting ELSE Greeting NUMBER ENDIF active.
a354	f90 f224	Enter fragment id and pound sign.
a355	f684 f262	Private, broadcast message from NAME received TIME DATE a873(NUMBER)
a356	f684 f262 f689	Private, broadcast message from NAME received TIME DATE a873(NUMBER) Expiration time is TIME(2) DATE(2)
a357	f684 f262	Private, broadcast message from NAME received TIME DATE a873(NUMBER) EXTENSION

A-52 Standard Announcements

Announcement	Fragment and Text	
a358	f684 f262 f689	Private, broadcast message from NAME received TIME DATE a873(NUMBER) EXTENSION Expiration time is TIME(2) DATE(2)
a359	f267 f224	Please enter extension and pound sign.
a360	f715	Cannot add new entries because your directory is full.
a361	f715 f722	Cannot add new entries because your directory is full. NAMEEXT was not added to your personal directory.
a362	f93	You have no personal greeting, system greeting used.
a363	f94	Good-bye.
a364	f243	Rewound.
a365	f754 f771 f823	Greeting NUMBER approved and active for all calls
a366	f754 f771 f827 f2 f812 f814	Greeting NUMBER approved and active for busy and no answer calls.
a367	f754 f771 f827 f813 f814	Greeting NUMBER approved and active for busy and out-of-hours calls.

Announcement	Fragment and Text	
a368	f754 f771 f827 f814	Greeting NUMBER approved and active for busy calls.
a369	f754 f771 f827 f812 f813 f814	Greeting NUMBER approved and active for busy no answer and out-of-hours calls.
a370	f754 f771 f826 f813 f814	Greeting NUMBER approved and active for external and out-of-hours calls.
a371	f754 f771 f826 f814	Greeting NUMBER approved and active for external calls.
a372	f754 f771 f825 f2 f810 f814	Greeting NUMBER approved and active for internal and external calls.
a373	f754 f771 f825 f813 f814	Greeting NUMBER approved and active for internal and out-of-hours calls.
a374	f754 f771 f825 f814	Greeting NUMBER approved and active for internal calls.

A-54 Standard Announcements

Announcement	Fragment and Text	
a375	f754 f771 f825 f810 f813 f814	Greeting NUMBER approved and active for internal external and out-of-hours calls.
a376	f754 f771 f828 f813 f814	Greeting NUMBER approved and active for no answer and out-of-hours calls.
a377	f754 f771 f829 f814	Greeting NUMBER approved and active for no answer calls.
a378	f754 f771 f829 f814	Greeting NUMBER approved and active for out-of-hours calls.
a379	f754 f74	Greeting NUMBER deleted.
a380	f754 f74 f332 f823	Greeting NUMBER deleted. System greeting used. for all calls
a381	f754 f74 f332 f827 f2 f812 f814	Greeting NUMBER deleted. System greeting used. for busy and no answer calls.

Announcement	Fragment and Text	
a382	f754 f74 f332 f827 f813 f814	Greeting NUMBER deleted. System greeting used. for busy and out-of-hours calls.
a383	f754 f74 f332 f827 f814	Greeting NUMBER deleted System greeting used. for busy calls.
a384	f754 f74 f332 f827 f812 f813 f814	Greeting NUMBER deleted. System greeting used. for busy no answer and out-of-hours calls.
a385	f754 f74 f332 f826 f813 f814	Greeting NUMBER deleted. System greeting used. for external and out-of-hours calls.
a386	f754 f74 f332 f826 f814	Greeting NUMBER deleted. System greeting used. for external calls.
a387	f754 f74 f332 f825 f2 f810 f814	Greeting NUMBER deleted. system greeting used. for internal and external calls.

A-56 Standard Announcements

Announcement	Fragment and Text	
a388	f754 f74 f332 f825 f813 f814	Greeting NUMBER deleted. System greeting used. for internal and out-of-hours calls.
a389	f754 f74 f332 f825 f814	Greeting NUMBER deleted. System greeting used. for internal calls.
a390	f754 f74 f332 f825 f810 f813 f814	Greeting NUMBER deleted. System greeting used. for internal external and out-of-hours calls.
a391	f754 f74 f332 f828 f813 f814	Greeting NUMBER deleted. System greeting used. for no answer and out-of-hours calls.
a392	f754 f74 f332 f828 f814	Greeting NUMBER deleted. System greeting used. for no answer calls.
a393	f754 f74 f332 f829 f814	Greeting NUMBER deleted. System greeting used. for out-of-hours calls.

Announcement	Fragment and Text	
a394	f754 f768	Greeting NUMBER approved.
a395	f754 f755	Greeting NUMBER not recorded.
a396	f754 f765	Greeting NUMBER recorded, but not active
a397	f754 f770 f823	Greeting NUMBER recorded and active for all calls
a398	f754 f770 f827 f2 f812 f814	Greeting NUMBER recorded and active for busy and no answer calls.
a399	f754 f770 f827 f813 f814	Greeting NUMBER recorded and active for busy and out-of-bourn calls.
a400	f754 f770 f827 f814	Greeting NUMBER recorded and active for busy calls.

A-58 Standard Announcements

Announcement	Fragment and Text
a401	f754 Greeting NUMBER f770 recorded and active f827 for busy f812 no answer f813 and out-of-hours f814 calls.
a402	f754 Greeting NUMBER f770 recorded and active f826 for external f813 and out-of-hours f814 calls.
a403	f754 Greeting NUMBER f770 recorded and active f826 for external f814 calls.
a404	f754 Greeting NUMBER f770 recorded and active f825 for internal f2 and f810 external f814 calls.
a405	f754 Greeting NUMBER f770 recorded and active f825 for internal f813 and out-of-hours f814 calls.
a406	f754 Greeting NUMBER f770 recorded and active f825 for internal f814 calls.
a407	f754 Greeting NUMBER f770 recorded and active f825 for internal f810 external f813 and out-of-hours f814 calls.

Announcement	Fragment and Text	
a408	f754 f770 f828 f813 f814	Greeting NUMBER recorded and active for no answer and out-of-hours calls.
a409	f754 f770 f828 f814	Greeting NUMBER recorded and active for no answer calls.
a410	f754 f770 f829 f814	Greeting NUMBER recorded and active for Out-of-born calls.
a411	f754 f745 f823	Greeting NUMBER active. for all calls
a412	f754 f745 f827 f2 f812 f814	Greeting NUMBER active. for busy and no answer calls.
a413	f754 f745 f827 f813 f814	Greeting NUMBER active. for busy and out-of-hours calls.
a414	f754 f745 f827 f814	Greeting NUMBER active. for busy calls.

A-60 Standard Announcements

Announcement	Fragment and Text	
a415	f754 f745 f827 f812 f813 f814	Greeting NUMBER active. for busy no answer and out-of-hours calls.
a416	f754 f745 f826 f813 f814	Greeting NUMBER active. for external and out-of-hours calls.
a417	f754 f745 f826 f814	Greeting NUMBER active. for external calls.
a418	f754 f745 f825 f2 f810 f814	Greeting NUMBER active. for internal and external calls.
a419	f754 f745 f825 f813 f814	Greeting NUMBER active. for internal and out-of-hours calls.
a420	f754 f745 f825 f814	Greeting NUMBER active. for internal calls.
a421	f754 f745 f825 f810 f813 f814	Greeting NUMBER active. for internal external and out-of-hours calls.

Announcement	Fragment and Text	
a422	f754 f745 f828 f813 f814	Greeting NUMBER active. for no answer and out-of-hours calls.
a423	f754 f745 f828 f814	Greeting NUMBER active. for no answer calls.
a424	f754 f745 f829 f814	Greeting NUMBER active. for out-of-hours calls.
a425	f752	To listen to a greeting, press 0. To create, change or delete a greeting, press 1. To scan all your greetings, press 2. To activate a greeting, press 3. To administer call types, press 4. If finished, press pound.
	f756 f772 f760	To listen to greeting NUMBER again press 0.
a427	f756 f760	To listen to greeting NUMBER press 0.
a428	f753	Enter greeting number.
a429	f757 f913	To re-record, press 1. If finished, press pound.
a430	f757 f759 f758 f913	To re-record, press 1. To review status, press 2. To delete, press star D. If finished, press pound.
a431	f88 f173 f224	Cannot use the guest password Please enter new password and pound sign.
a432	f788	To identify calls as out-of-hours, press 3.

A-62 Standard Announcements

Announcement	Fragment and Text
a433	f747 For internal calls,... IF (NUMBER==0) THEN f776 ELSE f754 Greeting NUMBER ENDIF f745 active.
a434	f737 Login announcement will be interruptible.
a435	f136 Line busy.
a436	f149 All circuits busy.
a437	f99 Invalid announcement.
a438	f637 Invalid date.
a439	f637 Invalid date. DATE f678 is past the expiration date, please reschedule.
a440	f637 Invalid date. DATE f638 is prior to delivery date, please re-schedule.
a441	f101 Invalid fragment
a442	f10 That is not a valid machine voice ID.
a443	f579 Password must be NUMBER f211 digits. f173 Please enter new password f224 and pound sign.
a444	f579 Password must be NUMBER f211 to fifteen digits f173 Please enter new password f224 and pound sign.
a445	f102 That is not a valid extension.

Announcement	Fragment and Text	
a446	f128 f129	To request another transfer, press star T. or leave a message for NAME
a447	f104	Message delivered, cannot listen to a delivered message.
a448	f492	Owner erased.
a449	f110	list BUTTONS
a450	f110 f142	list BUTTONS To listen to the header, press 3.
a451	f110 f65 f84 f83	list BUTTONS contains NUMBER IF (NUMBER<=l) THEN entry. ELSE entries. ENDIF
a452	f110 f65 f159 f150	list BUTTONS contains NUMBER IF (NUMBER<=l) THEN member. ELSE members. ENDIF
a453	f110 f74	list BUTTONS deleted.
a454	f110 f197 f142	list BUTTONS cannot step back. To listen to the header, press 3.

A-64 Standard Announcements

Announcement	Fragment and Text
a455	f110 list BUTTONS f45 has NUMBER IF (NUMBER<=1) THEN f159 member. ELSE f150 members. ENDIF f15 and is f226 private
a456	f110 list BUTTONS f485 has NUMBER IF (NUMBER<=1) THEN f159 member. ELSE f150 members. ENDIF f15 and is f227 public
a457	f110 list BUTTONS f494 private. f61 To modify status, press Y for yes or N for no.
a458	f110 list BUTTONS f495 public. f61 To modify status, press Y for yes or N for no.
a459	f110 list BUTTONS f144 deleted f130 because there were no entries.

Announcement	Fragment and Text	
a460	f110 f120 f132 f139	list BUTTONS too large to include. You can store your list as is by pressing star pound or add up to NUMBER additional members,
a461	f110 f120 f132 f139	list BUTTONS too large to include. You can store your list as is by pressing star pound or add up to NUMBER additional members,
a462	f110 f120 f134	list BUTTONS too large to include. You can store your list or delete members, but you cannot add members.
a463	f110 f120 f124 f349 f241	list BUTTONS too large to include. No more list space. To approve list as is, press pound. To review list, press star 1.
a464	f110 f144	list BUTTONS deleted
a465	f110 F208	list BUTTONS is not a public list.
a466	f110 f202 f498 f224	list BUTTONS not valid. Please enter a new list id and pound sign.
a467	f110 f185	list not found.
a468	f110 f185 f295	list not found. To re-enter list, press star L.

A-66 Standard Announcements

Announcement	Fragment and Text
a469	f110 list BUTTONS f219 owned by NAME f65 contains NUMBER f150 members.
a470	f110 list BUTTONS f219 owned by NAME f120 too large to include. f132 You can store your list as is by pressing star pound or add up to NUMBER f139 additional members,
a471	f110 list BUTTONS f219 owned by NAME f120 too large to include. f134 You can store your list or delete members, but you cannot add members.
a472	f110 list BUTTONS f219 owned by NAME f120 too large to include. f124 No more list space. f349 To approve list as is, press pound. f241 To review list, press star 1.
a473	f110 list BUTTONS f219 owned by NAME f144 deleted,
a474	f110 list BUTTONS f219 owned by NAME f208 is not a public list.

Announcement	Fragment and Text	
a475	f110 f185	list not found.
a476	f124 f970	No more list space. To continue reviewing, press 3. To delete an entry, press star D. If finished reviewing, press pound.
a477	f110 f219 f208 f295	list BUTTONS owned by NAME is not a public list. To re-enter list, press star L.
a478	f111 f224	Please enter list id and pound sign.
a479	f141	No more lists.
a480	f124 f133	No more list space. To continue reviewing, press 3. To delete an entry, press star D. If finished reviewing, press star pound.
a481	f116 f133	List is full. To continue reviewing, press 3. To delete an entry, press star D. If finished reviewing, press star pound.
a482	f116 f349 f241	List is full. To approve list as is, press pound. To review list, press star 1.
a483	f124 f349 f241	No more list space. To approve list as is, press pound. To review list, press star 1.
a484	f113 f114 f224	You already have a list BUTTONS To replace list, re-enter id and pound sign. To create a new list enter new list id and pound sign.
a485	f154	Cannot create new list, you have maximum lists allowed. To select lists to be deleted, press 5-1-2 and follow instructions.
a486	f155	Cannot create new list, total number of members in all your lists equals maximum allowed

A-68 Standard Announcements

Announcement	Fragment and Text	
a487	f122 f123	List space nearly full. You may enter NUMBER new members.
a488	f468	To continue playing, press 3.
a489	f691 f262	Login announcement from NAME received TIME DATE a873(NUMBER) — Length of message in seconds
a490	f691 f262 f689	Login announcement from NAME received TIME DATE a873(NUMBER) — Length of message in seconds Expiration time is TIME(2) DATE(2)
a491	f691 f262	Login announcement from NAME received TIME DATE a873(NUMBER) — Length of message in seconds EXTENSION
a492	f691 f262 f689	Login announcement from NAME received TIME DATE a873(NUMBER) — Length of message in seconds EXTENSION Expiration time is TIME(2) DATE(2)

Announcement	Fragment and Text	
a493	f697 f2 f602 f217	Login announcement to all local subscribers IF (NUMBER >0) THEN and NUMBER IF (NUMBER==1) THEN other ELSE others ENDIF ENDIF
a494	f656	For login announcement options, press star M.
a495	f624	Login announcement.
a496	f100 f96	Invalid Entry. For help, press star H.
a497	f469 f224 f471	Enter owner's extension and pound sign. If it's your list, press pound.
a498	f470 f224 f471	Enter owner's last name and pound sign. If it's your list, press pound.
a499	f469 f224 f471	Enter owner's extension and pound sign. If it's your list, press pound.
a500	f470 f224 f471	Enter owner's last name and pound sign. If it's your list, press pound.

A-70 Standard Announcements

Announcement	Fragment and Text	
a501	f240 f296	To skip, press pound. To listen, press 0. To delete, press star D.
a502	f14	To make private, press 1. To make public, press 2.
a503	f704	To create lists, press 1. To scan lists, press 2. To review and modify lists, press 3.
a504	f82	Please leave a message for NAME
a505	f152 f262	Leave Word Calling from NAME received TIME DATE
a506	f152 f262 f86	Leave Word Calling from NAME received TIME DATE extension BUTTONS
a507	f474 f389 f388	To listen, press 0. To change or send again, press 1. To delete, press star D. To skip, press pound.
a508	f30 f24 f388	To change, press 1. To delete, press star D. To skip, press pound.
a509	f6 f224	Enter machine voice ID. and pound sign.
a510	f153	Maximum length recorded. To re-record, press 2-1. To approve as is, press pound.
a511	f125 f111 f224	Must be six or fewer numerals. Please enter list id and pound sign.
a512	f570	Recorded name too long
a513	f156 f157	Maximum length recorded. To approve as is, press pound.

Announcement	Fragment and Text
a514	f582 AUDIX passwords must now be at least NUMBER f81 digits. f593 Please choose a new password of NUMBER(2) f588 or more digits. f173 Please enter new password f224 and pound sign.
a515	f614 To make broadcast, press 8.
a516	f615 To make a login announcement, press 9.
a517	f633 To make non-interruptible, press 1.
a518	f613 To make priority, press 2.
a519	f612 To make private, press 1.
a520	f386 Cannot change a delivered message.
a521	f484 Enter more characters followed by the pound sign; if you just completed entering the last name, enter the first name f225 and pound sign.
a522	f777 Cannot listen to system greeting.
a523	f778 Cannot modify system greeting.
a524	f780 Personal greetings review completed
a525	f781 To skip to the next greeting, press the pound sign. f756 To listen to greeting NUMBER f760 press 0. f758 To delete, press star D. f707 If finished, press star pound.
a526	f243 Rewound.
a527	f165 Returned to getting messages. f21 To listen, press 0. f389 To delete, press star D. f851 To Skip, press pound.

A-72 Standard Announcements

Announcement	Fragment and Text	
a528	f91	At end.
a529	f844	End of message.
a530	f165 f21 f255 f388	Returned to getting messages. To listen, press 0. To delete this message, press star D. To skip, press pound.
a531	f166	At end, To playback press 2-3.
a532	f496	Filed.
a533	f167	To approve, press pound. To record from here, press 1. To playback, press 2-3.
a534	f170	Delivery scheduled
a535	f170 f66	Delivery scheduled TIME DATE If correct, press pound. If not, press star D and re-enter time.
a536	f631	Message waiting notification activated.
a537	f198	Partial name deleted.
a538	f603 f34 f168	You also have Electronic Text messages.
a539	f172 f343 f168	You have new Leave word calling messages.
a540	f603 f343 f2 f34 f168	You also have Leave word calling and Electronic Text messages.
a541	f603 f343 f2 f342 f168	You also have Leave word calling and Electronic document communication messages.

Announcement	Fragment and Text	
a542	f172 f343 f2 f342 f168	You have new have word calling and Electronic document communication messages.
a543	f603 f343 f2 f342 f168	You also have Leave word calling and Message Center Service messages.
a544	f172 f343 f2 f344 f168	You have new Leave word calling and Message Center Service messages.
a545	f603 f343 f344 f2 f342 f168	You also have Leave word calling Message Center Service and Electronic document communication messages.
a546	f172 f343 f344 f2 f342 f168	You have new Leave word calling Message Center Service and Electronic document communication messages.
a547	f603 f34 f168	You also have Electronic Text messages.
a548	f172 f34 f168	You have new Electronic Text messages.
a549	f603 f342 f168	You also have Electronic document communication messages.

A-74 Standard Announcements

Announcement	Fragment and Text	
a550	f172 f342 f168	You have new Electronic document communication messages.
a551	f603 f344 f168	You also have Message Center Service messages.
a552	f172 f344 f168	You have new Message Center Service messages.
a553	f603 f344 f2 f342 f168	You also have Message Center Service and Electronic document communication messages.
a554	f172 f344 f2 f342 f168	You have new Message Center Service and Electronic document communication messages.
a555	f603 f343 f168	You also have Leave word calling messages.
a556	f928	New Messages
a557	f600	new Broadcast messages.
a558	f845	Next message.
a559	f105 f67 f111 f224	To restart at the activity menu, press star R. To create another list, Please enter list id and pound sign.
a560	f830 f167	You must approve your recording. To approve, press pound. To record from here, press 1. To playback press 2-3.
a561	f53	Message deleted, no delivery will occur.
a562	f181	Nothing to approve.
a563	f850	Broadcast and Login Message services are not available.

Announcement	Fragment and Text	
a564	f636	Login announcement will be non-interruptible.
a565	f842 f95	Announcement not recorded. Try again later. Please disconnect.
a566	f203 f62	No room in your mailbox for a recording. Please delete unneeded messages.
a567	f203 f62	No room in your mailbox for a recording. Please delete unneeded messages.
a568	f203 f62	No room in your mailbox for a recording. Please delete unneeded messages.
a569	f215 f62	No room to retain a copy. Please delete unneeded messages.
a570	f559	A name cannot be recorded until the size of the names file system is increased.
a571	f207	Message too long to add comment. To record a new message, press star R-1.
a572	f209	Cannot modify another subscriber's list.
a573	f92	Nothing to advance.
a574	f177	Cannot listen to a delivered message.
a575	f178	No addressees identified.
a576	f178 f76	No addressees identified. Deleted
a577	f169	Admin version not specified, please do so using administrator's terminal.
a578	f180	Nothing to approve.

A-76 Standard Announcements

Announcement	Fragment and Text	
a579	f750 f776 f754 f745	For no answer calls,... IF (NUMBER==0) THEN the system greeting ELSE Greeting NUMBER ENDIF active.
a580	f181	Nothing to approve.
a581	f181 f13	Nothing to approve. To record, press 1. After recording, press 1 again.
a582	f548	You have no attendant menu.
a583	f609	No room to save Broadcast message so it will be retained in the new message category.
a584	f186	To record messages, press 1. To get messages, press 2. To check your outgoing messages, press 4.
a585	f182	Nothing to delete.
a586	f182 f173 f224	Nothing to delete. Please enter new password and pound sign.
a587	f714	Directory has no entries.
a588	f183	Nothing to delete.
a589	f184 f13	Nothing to erase. To record, press 1. After recording, press 1 again.
a590	f575	Cannot forward a private message
a591	f769	Nothing to approve.
a592	f188 f224	Passwords do not match. Please re-enter new password and pound sign.
a593	f189 f272	You have no mailbox. Contact administrator for help.

Standard Announcements A-77

Announcement	Fragment and Text	
a594	f190	Message delivered. you cannot change it now.
a595	f191	No more messages.
a596	f779	No greetings recorded,
a597	f192	No messages.
a598	f193	No name recorded.
a599	f193 f608	No name recorded. At the tone, please speak your name. After speaking your name, press 1.
a600	f194	No new messages.
a601	f509	System not administered for outcalling.
a602	f195	No messages.
a603	f49	No operator defined.
a604	f196	You have no personal greeting.
a605	f199	Nothing to rewind.
a606	f199 f256	Nothing to rewind. At beginning. To re-record, press 1. To playback, press 2-3.
a607	f199 f142 f143	Nothing to rewind. To listen to the header, press 3. To step back again, press 2.
a608	f3	No new remote subscribers can be addressed.
a609	f200 f22	No time entered, nothing to delete. To deliver now, press pound. To schedule delivery time enter hour, minutes, A or P, and pound sign.
a610	f571	Non-existent subscriber
a611	f232 f181	Recording stopped. Nothing to approve.
a612	f173 f224	Please enter new password and pound sign.

A-78 Standard Announcements

Announcement	Fragment and Text	
a613	f267 f224 f237	Please enter extension and pound sign. Or press star R.
a614	f510 f202	Number not valid.
a615	f510 f202 f95	Number not valid. Please disconnect.
a616	f535	For outcalling any time, press 1. For outcalling during prime time, press 2. To specify your times, press 3. For system outcalling schedule, press 4.
a617	f530 f522	Outcalling turned off. To restart at the activity menu, press star R
a618	f530 f521 f835	Outcalling turned on for all new messages
a619	f530 f521 f836	Outcalling turned on only for new priority messages
a620	f532 f557 f560	To change your outcalling phone number, press 1 and enter the number to be called followed by the pound sign. Anything you enter will be interpreted as a part of the called number. No global commands such as star H will be accepted at this time. In most cases, entering a star or pound as the first digit will result in the star or pound being outpulsed. A star entered as part of the digit string will be interpreted as a pause of one and a half seconds. If a longer pause is required, use multiple stars in a row. If you are programming a number to call a pager that requires a pound sign termination, press y to hear further help. Otherwise, press n to return to outcalling administration.
a621	f531 f224 f556	Enter outcalling number and pound sign. To exit, press star pound now.

Announcement	Fragment and Text	
a622	f589	For pagers requiring a pound sign termination, start your number with a double pound sign. This will result in a single pound being outpulsed at the end of the digit string. Then, a star or pound in the next position will be interpreted as part of the outcalling number.
	f590	A star entered as part of the digit string will be interpreted as a pause of one and a half seconds. If a longer pause is required, use multiple stars in a row.
a623	f534	Your outcalling number is DIALSTR
a624	f544 f525 f526	Outcalling specified for any time subject to administrator restrictions
a625	f544 f524 f526	Outcalling specified for TIME to TIME(2) subject to administrator restrictions
a626	f544 f524 f526 f66	Outcalling specified for TIME to TIME(2) subject to administrator restrictions If correct, press pound. If not, press star D and re-enter time.
a627	f500 f172 f168 f551 f278 f224 f543	This is AUDIX. NAME You have new messages. To access your messages, Please enter extension and pound sign. To avoid further notification of these messages, press star pound.
a628	f519	You are not authorized for outcalling.
a629	f520 f522 f527 f528	Your outcalling number, DIALSTR turned off. To restart at the activity menu, press star R. To change number, press 1. To change times, press 2. For instructions on entering your outcalling number, press 3. To turn on, press y. To turn off, press n.

A-80 Standard Announcements

Announcement	Fragment and Text
a630	f520 Your outcalling number, DIALSTR f521 turned on f835 for all new messages f523 for f525 any time f526 subject to administrator restrictions f527 To change number, press 1. To change times, press 2. For instructions on entering your outcalling number, press 3. f528 To turn on, press y. To turn off, press n.
a631	f520 Your outcalling number, DIALSTR f521 turned on f835 for all new messages f523 for TIME f524 to TIME(2) f526 subject to administrator restrictions f527 To change number, press 1. To change times, press 2. For instructions on entering your outcalling number, press 3. f528 To turn on, press y. To turn off, press n.
a632	f520 Your outcalling number, DIALSTR f521 turned on f836 only for new priority messages f523 for f525 any time f526 subject to administrator restrictions f527 To change number, press 1. To change times, press 2. For instructions on entering your outcalling number, press 3. f528 To turn on, press y. To turn off, press n.

Announcement	Fragment and Text
a633	f520 Your outcalling number, DIALSTR f521 turned on f836 only for new priority messages f523 for TIME f524 to TIME(2) f526 subject to administrator restrictions f527 To change number, press 1. To change times, press 2. For instructions on entering your outcalling number, press 3. f528 To turn on, press y. To turn off, press n.
a634	f837 To turn on Outcalling for all new messages, press 1. To turn on outcalling only for new priority messages, press 2.
a635	f929 Old Messages
a636	f840 Option f841 not defined
a637	f216 originally f260 scheduled for TIME DATE f261 rescheduled for TIME(2) DATE(2) IF (NUMBER-1) THEN f264 Message not delivered because mailbox was full. ELSE f265 Message not delivered because their mailboxes were full. ENDIF

A-82 Standard Announcements

Announcement	Fragment and Text
a638	f216 originally f260 scheduled for TIME DATE f261 rescheduled for TIME(2) DATE(2) f265 Message not delivered because their mailboxes were full. f689 Expiration time is TIME(3) DATE(3)
a639	f216 originally f260 scheduled for TIME DATE f261 rescheduled for TIME(2) DATE(2) f98 Message not delivered due to transmission problems.
a640	f216 originally f260 scheduled for TIME DATE f261 rescheduled for TIME(2) DATE(2) f98 Message not delivered due to transmission problems. f689 Expiration time is TIME(3) DATE(3)
a641	f216 originally f260 scheduled for TIME DATE f261 rescheduled for TIME(2) DATE(2) f387 Message not delivered because recipient not found.

Announcement	Fragment and Text	
a642	f216 f260 f261 f387 f689	Originally scheduled for TIME DATE rescheduled for TIME(2) DATE(2) Message not delivered because recipient not found. Expiration time is TIME(3) DATE(3)
a643	f216 f260 f261 f584	originally scheduled for TIME DATE rescheduled for TIME(2) DATE(2) Message not delivered because special feature denied on recipients machine.
a644	f216 f260 f261 f584 f689	originally scheduled for TIME DATE rescheduled for TIME(2) DATE(2) Message not delivered because special feature denied on recipients machine. Expiration time is TIME(3) DATE(3)
a645	f751 f776 f754 f745	For out-of-hours calls,... IF (NUMBER==0) THEN the system greeting ELSE Greeting NUMBER ENDIF active.

A-84 Standard Announcements

Announcement	Fragment and Text	
a646	f220 f224	Enter password and pound sign.
a647	f681	Sorry, cannot leave a message now because this user's mailbox is full.
a648	f214	Approved
a649	f1	Someone is changing your greeting, please try again later.
a650	f607	Name cannot be saved at this time, please continue
a651	f720	Alias entered not followed by pound and not added to the directory.
a652	f719	Extension entered not followed by pound and not added to the directory.
a653	f718	Name entered not followed by pound and not added to the directory.
a654	f37 f187 f464 f135 f349	Extension entered not followed by pound and not added to the list. Enter extensions and pound sign. To approve list as is, press pound.
a655	f38 f187 f465 f135 f349	Name entered not followed by pound and not added to the list. Enter last name and pound sign. To approve list as is, press pound.
a656	f798 f524	Prime time is TIME to TIME(2)
a657	f798 f524 f788 f789	Prime time is TIME to TIME(2) To identify calls as out-of-hours, press 3. Otherwise, press 4.
a658	f226 f47 f262	private Call from NAME received TIME DATE a873(NUMBER) — Length of message in seconds

Standard Announcements A-85

Announcement	Fragment and Text	
a659	f226 f47 f262 f86	private Call from NAME received TIME DATE extension BUTTONS a873(NUMBER) — Length of message in seconds
a660	f226 f50 f262 f86	private Call NAME received TIME DATE extension BUTTONS a873(NUMBER) — Length of message in seconds
a661	f226 f50 f262	private Call received TIME DATE a873(NUMBER) — Length of message in seconds
a662	f226 f110	private list
a663	f686 f262	Private message from NAME received TIME DATE a873(NUMBER) — Length of message in seconds

A-86 Standard Announcements

Announcement	Fragment and Test
a664	f686 Private message from NAME f262 received TIME DATE a873(NUMBER) — Length of message in seconds F689 Expiration time is TIME(2) DATE(2)
a665	f686 Private message from NAME f262 received Text DATE a873(NUMBER) — Length of message in seconds EXTENSION
a666	f686 Private message from NAME f262 received TIME DATE a873(NUMBER) — Length of message in seconds EXTENSION f689 Expiration time is TIME(2) DATE(2)
a667	f918 To re-schedule delivery, press 3.
a668	f690 Priority message from NAME f262 received TIME DATE a873(NUMBER) — Length of message in seconds

Announcement	Fragment and Text	
a669	f690 f262 f689	Priority message from NAME received TIME DATE a873(NUMBER) — Length of message in seconds Expiration time is TIME(2) DATE(2)
a670	f690 f262	Priority message from NAME received TIME DATE a873(NUMBER) — Length of message in seconds EXTENSION
a671	f690 f262 f689	Priority message from NAME received TIME DATE a873(NUMBER) — Length of message in seconds EXTENSION Expiration time is TIME(2) DATE(2)
a672	f919	To file a copy, press 4.
a673	f698 f2 f602 f217	Priority message to NAME IF (NUMBER>0 TIME and NUMBER IF (NUMBER==1) TIME other ELSE others ENDIF ENDIF

A-88 Standard Announcements

Announcement	Fragment and Text	
a674	f227 f110	public list
a675	f694 f2 f602 f217	Private, broadcast message to all local subscribers IF (NUMBER>0) THEN and NUMBER — Length of message m seconds IF (NUMBER==1) THEN other ELSE others ENDIF ENDIF
a676	f685 f262	Private, priority message from NAME received TIME DATE a873(NUMBER) — Length of message in seconds
a677	f685 f262 f689	Private, priority message from NAME received TIME DATE a873(NUMBER) — Length of message in seconds Expiration time is TIME(2) DATE(2)
a678	f685 f262	Private, Priority message from NAME received TIME DATE a873(NUMBER) — Length of message in seconds EXTENSION

Announcement	Fragment and Text	
a679	f685 f262 f689	Private, priority message from NAME received TIME DATE a873(NUMBER) — Length of message in seconds EXTENSION Expiration time is TIME(2) DATE(2)
a680	f242 f57 f164 f142	Returned to the accessed category. To listen to the header, press 3.
a681	f242 f59 f164 f142	Returned to the delivered category. To listen to the header, press 3.
a682	f242 f473 f164 f142	Returned to the filed category. To listen to the header, press 3.
a683	f242 f63 f164 f142	Returned to the new category. To listen to the header, press 3.
a684	f242 f64 f164 f142	Returned to the old category. To listen to the header, press 3.
a685	f242 f68 f164 f142	Returned to the undeliverable category. To listen to the header, press 3.

A-90 Standard Announcements

Announcement	Fragment and Text	
a686	f242 f69 f164 f142	Returned to the undelivered category. To listen to the header, press 3.
a687	f242 f70 f164 f142	Returned to the unopened category. To listen to the header, press 3.
a688	f228	Record at the tone.
a689	f229 f230	You will have up to NUMBER seconds to record.
a690	f604	As you use AUDIX your name will be included in system announcements that you and other people will hear. Press 1, and at the tone, please speak your name. After speaking your name, press 1 again.
a691	f232	Recording stopped.
a692	f232 f193 f608	Recording stopped. No name recorded. At the tone, please speak your name. After speaking your name, press 1.
a693	f486 f18 f8	To reply to sender by voice mail, press 1. To forward with comment, press 2. To record a new message, press 4.
a694	f127 f96	Returned to previous activity. For help, press star H.
a695	f19	To review from beginning, press star 1. If finished, press star pound.
a696	f147	Review completed.
a697	f147 f569	Review completed To modify, press one. If finished, press star pound
a698	f147 f19	Review completed. To review from beginning, press star 1. If finished, press star pound.
a699	f256	At beginning. To re-record, press 1. To playback, press 2-3.
a700	f619	To remove broadcast status, press 8.

Announcement	Fragment and Text	
a701	f620	To remove login announcement status, press 9.
a702	f635	To remove non-interruptible status, press 1.
a703	f796	To remove out-of-hours identification, press 4.
a704	f618	To remove priority status, press 2.
a705	f617	To remove private status, press 1.
a706	f244 f142	Rewound to previous message. To listen to the header, press 3.
a707	f802	Cannot send a message to the broadcast mailbox.
a708	f245	Please return call.
a709	f245 f86	Please return call. extension BUTTONS
a710	f785	Same greeting used for all calls.
a711	f785 f786 f787	Same greeting used for all calls. To identify calls as internal and external, press 1. To identify calls as busy and no answer, press 2.
a712	f511 f236 f109 f514 f274	If you do not have a touch tone phone, Try again later. otherwise Please make entry soon, or be disconnected.
a713	f248 f249	scheduled TIME DATE To change delivery time, press star D
a714	f250	To change delivery time, press star D.
a715	F22	To deliver now, press pound. To schedule delivery time enter hour, minutes, A or P, and pound sign.
a716	f629	Please enter month, day, and pound sign.
a717	f477	Press 1 to select NAME

Announcement	Fragment and Text
a718	f478 2 to select NAME
a719	f479 3 to select NAME
a720	f480 4 to select NAME
a721	f481 5 to select NAME
a722	f23 To record messages, press 1. To get messages, press 2. To administer your greeting, press 3.
a723	f501 To record messages, press one. To get messages, press two. To administer attendant menu, press 3.
a724	f482 Press pound to select NAME f483 or enter more characters f225 and pound sign. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a725	f482 Press pound to select NAME f483 or enter more characters f225 and pound sign.
a726	f482 Press pound to select NAMEEXT f483 or enter more characters f225 and pound sign. f235 To restart at the activity menu, press star R. To transfer to another extension, press star T. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a727	f257 To use personal greeting, press Y. To use system greeting, press N.
a728	f775 To record messages, press one. To get messages, press two. To administer personal greetings, press 3 ₀

Announcement	Fragment and Test	
a729	f674	Due to sending restriction you cannot send messages to NAME
a730	f388	To skip, press pound.
a731	f626	To specify expiration date, press 2.
a732	f626 f634	To specify expiration date, press 2. To approve login announcement options, press pound.
a733	f243 f142 f143	Rewound. To listen to the header, press 3. To step back again, press 2.
a734	f537	Enter the starting hour, minutes, A or P, and pound sign.
a735	f466	created TIME DATE
a736	f259	scheduled for TIME DATE
a737	f259 f689	scheduled for TIME DATE Expiration time is TIME(2) DATE(2)
a738	f260 f730	scheduled for TIME DATE Message not delivered because the broadcast mailbox was not defined.
a739	f260 f699	scheduled for TIME DATE Message not delivered because another login announcement is active.
a740	f260 f738	scheduled for TIME DATE Message not delivered due to sending restrictions.

A-94 Standard Announcements

Announcement	Fragment and Text	
a741	f260 f98	scheduled for TIME DATE Message not delivered due to transmission problems.
a742	f260 f387	scheduled for TIME DATE Message not delivered because recipient not found.
a743	f260 f584	scheduled for TIME DATE Message not delivered because special feature denied on recipients machine.
a744	f260 f264	scheduled for TIME DATE Message not delivered because mailbox was full.
a745	f262	received TIME DATE
a746	f262 f689	received TIME DATE Expiration time is TIME(2) DATE(2)
a747	f21 f24 f388	To listen, press 0. To delete, press star D. To skip, press pound.
a748	f920	To not file a copy, press 4.
a749	f472 f468	To approve, press pound. To record from here, press 1. To continue playing, press 3.
a750	f499	When finished recording, press # to approve, or 1 to edit your message.

Announcement	Fragment and Text	
a751	f475	To file a copy, press Y for yes or N for no.
a752	f977	Name not found.
a753	f270 f202	subscriber id BUTTONS not valid.
a754	f270 f202	subscriber id not valid.
a755	f700 f701	To administer mailing lists, press 1. To administer personal directory, press 2. To change your password, press 4.
a756	f702 f701 f702	To administer mailing lists, press 1. To administer personal directory, press 2. To change your password, press 4. To record your name, press 5.
a757	f26	To record names, press 4. To play names, press 5. To record machine names, press 6. To play machine names, press 7.
a758	f539 f524	The system allows outcalls from TIME to TIME(2)
a759	f18 f8 f163	To forward with comment, press 2. To record a new message, press 4. To call sender, press zero.
a760	f486 f8 f163	To reply to sender by voice mail, press 1. To record a new message, press 4. To call sender, press zero.
a761	f8 f163	To record a new message, press 4. To call sender, press zero.
a762	f274	Please make entry soon, or be disconnected.
a763	f96 f80 f274	For help, press star H. To have system wait, press star W. If finished, please hangup or to disconnect AUDIX, press star star W. Please make entry soon, or be disconnected,
a764	f533	Too many digits.

Announcement	Fragment and Text	
a765	f276 f22	Time requested has passed, please re-schedule delivery. To deliver now, press pound. To schedule delivery time enter hour, minutes, A or P, and pound sign.
a766	f275 f95	Cannot get your messages now, due to multiple logins to your mailbox. Please disconnect.
a767	f695 f2 f602 f217	Private, priority message to NAME IF (NUMBER>0) THEN and NUMBER IF (NUMBER==1) THEN other ELSE others ENDIF ENDIF
a768	f486 f18 f8 f163	To reply to sender by voice mail, press 1. To forward with comment, press 2. To record a new message, press 4. To call sender, press zero.
a769	f128	To request another transfer, press star T.
a770	f118 f224 f175 f117 f251	Enter last name and pound sign. Please note only AUDIX subscribers can be specified by name. To reach the covering extension, press star zero. To transfer using extension instead, press star A.
a771	f118 f224 f175 f117 f251 f335	Enter last name and pound sign. Please note only AUDIX subscribers can be specified by name. To reach the covering extension, press star zero. To transfer using extension instead, press star A. when finished, press pound.
a772	f512	Your call is being transferred to an operator.
a773	f118 f224 f251	Enter last name and pound sign. To transfer using extension instead, press star A.

Announcement	Fragment and Text	
a774	f118 f224 f251 f335	Enter last name and pound sign. To transfer using extension instead, press star A. when finished, press pound.
a775	f515 f380	To be transferred to an operator, Please wait.
a776	f933	Undeliverable Messages
a777	f934	Undelivered Messages
a778	f688	An undeliverable message was returned to your outgoing mailbox. To access your outgoing mailbox, press star R 4.
a779	f687	Undeliverable message notification received TIME DATE
a780	f935	Unopened Messages
a781	f541 f542	Up to NUMBER digits may be used.
a782	f278 f224	Please enter extension and pound sign.
a783	f766 f913	To use this greeting for all calls, press 1. If finished, press pound.
a784	f783 f784 f913	To activate another greeting, enter greeting number. To deactivate a greeting, activate a different greeting in its place. To activate system greeting, enter zero. If finished, press pound.
a785	f767	To use this greeting for all calls, press 0. For busy calls, press 1. For no answer calls, press 2.
a786	f767 f913	To use this greeting for all calls, press 0. For busy calls, press 1. For no answer calls, press 2. If finished, press pound.
a787	f764	To use this greeting for all calls, press 0. For internal calls, press 1. For external calls, press 2.

A-98 Standard Announcements

Announcement	Fragment and Text	
a788	f764 f913	To use this greeting for all calls, press 0. For internal calls, press 1. For external calls, press 2. If finished, press pound.
a789	f782 f784 f913	To activate a greeting, enter greeting number. To deactivate greeting, activate a different greeting in its place. To activate system greeting, enter zero. If finished, press pound.
a790	f331	Personal greeting used.
a791	f797 f913	To use same greeting for all calls, press 5. If finished, press pound.
a792	f332	System greeting used.
a793	f332 f823	System greeting used. for all calls
a794	f332 f827 f2 f812 f814	system greeting used. for busy and no answer calls.
a795	f332 f827 f813 f814	System greeting used. for busy and out-of-hours calls.
a796	f332 f827 f814	system greeting used. for busy calls.
a797	f332 f827 f812 f813 f814	system greeting used. for busy no answer and out-of-hours calls.
a798	f332 f826 f813 f814	System greeting used. for external and out-of-hours calls.

Announcement	Fragment and Text	
a799	f332 f826 f814	system greeting used. for external calls.
a800	f332 f825 f2 f810 f814	system greeting used. for internal and external calls.
a801	f332 f825 f813 f814	system greeting used. for internal and out-of-hours calls.
a802	f332 f825 f814	system greeting used. for internal calls.
a803	f332 f825 f810 f813 f814	system greeting used. for internal external and out-of-hours calls.
a804	f332 f828 f813 f814	system greeting used. for no answer and out-of-hours calls.
a805	f332 f828 f814	System greeting used. for no answer calls.
a806	f332 f829 f814	system greeting used. for out-of-hours calls.
a807	f279	Enter announcement set and pound sign.
a808	f281 f262	Message from NAME received TIME DATE a873(NUMBER) — Length of message in seconds

A-100 Standard Announcements

Announcement	Fragment and Text	
a809	f281 f262 f689	Message from NAME received TIME DATE a873(NUMBER) — Length of message in seconds Expiration time is TIME(2) DATE(2)
a810	f281 f262	Message from NAME received TIME DATE a873(NUMBER) — Length of message in seconds EXTENSION
a811	f281 f262 f689	Message from NAME received TIME DATE a873(NUMBER) EXTENSION Expiration time is TIME(2) DATE(2)
a812	f87 f497	This call is experiencing difficulties. To review your message, press star 1.
a813	f380	Please wait.
a814	f283 f284	Your mailbox is more than NUMBER percent full. Please delete unneeded messages or greetings.
a815	f287 f97	Welcome to AUDIX. For help at anytime, press star H.
a816	f179	Warning, if you do not supply an addressee list, message will be deleted immediately.

Announcement	Fragment and Text	
a817	f293	Nothing to playback.
a818 [Voice out a time]		a902(NUMBER(1)) — Hour of day a903(NUMBER(2)) — Minute of hour a904(NUMBER(1)) NUMBER(2))
a819	f253 f224	TIME Please enter month, day and pound sign.
a820 [Voice out a number]		IF (NUMBER<=60) THEN (f390+NUMBER) ELSE IF (NUMBER<=100) THEN (f450+((NUMBER-60)/10)) IF (NUMBER%10>0) THEN (f390+(NUMBER%10)) ENDIF ELSE a901(NUMBER) ENDIF ENDIF
a821	f86	extension BUTTONS
a822	f20	Remote extension BUTTONS
a823	f463	star
a824	f462	pound
a825	f546	pause
a826	f277	To exit directory, press pound.
a827	f482 f483	Press pound to select NAMEEXT or enter more characters

A-102 Standard Announcements

Announcement	Fragment and Text	
a828	f764 f773 f913	To use this greeting for all calls, press 0. For internal calls, press 1. For external calls, press 2. To activate for out-of-hours calls, press 3. If finished, press pound.
a829	f767 f773 f913	To use this greeting for all calls, press 0. For busy calls, press 1. For no answer calls press 2. To activate for out-of-hours calls, press 3. If finished, press pound.
a830	f818 f754	You have just recorded Greeting NUMBER
a831	f658 f625 f659 f626	Message waiting notification is currently not active. To activate message waiting notification, press 1. Message waiting notification will alert all local subscribers of this message. This option should be used sparingly, for it can impact system performance. To specify expiration date, press 2.
a832	f628 f626 f627	To deactivate message waiting notification, press 1. To specify expiration date, press 2. To approve broadcast options, press pound.
a833	f625 f626 f627	To activate message waiting notification, press 1. To specify expiration date, press 2. To approve broadcast options, press pound.
a834	f87 f236 f109 f95	This call is experiencing difficulties. Try again later. Please disconnect
a835	f267 f224 f237	Please enter extension and pound sign. Or press star R.
a836	f110 f142 f143	list BUTTONS To listen to the header, press 3. To step back again, press 2.
a837	f846 f843	You are selecting an option for Automatic Message Scan. To scan headers and messages, press 1. To scan headers only, press 2. To scan messages only, press 3.

Announcement	Fragment and Text
a838	f258 Message to NAME IF (NUMBER>0) THEN f2 and NUMBER IF (NUMBER==1) THEN f602 other ELSE f217 others ENDIF ENDIF
a839	f258 Message to NAME IF (NUMBER>0) THEN f2 and NUMBER IF (NUMBER==1) THEN f602 other ELSE f217 others ENDIF ENDIF
a840	f742 Private message sent to NAME IF (NUMBER>0) THEN f2 and NUMBER IF (NUMBER==1) THEN f602 other ELSE f217 others ENDIF ENDIF

A-104 Standard Announcements

Announcement	Fragment and Text	
a841	f696 f2 f602 f217	Private message to NAME IF (NUMBER>0) THEN and NUMBER IF (NUMBER==1) THEN other ELSE others ENDIF ENDIF
a842	f647	the message will be private.
a843	f390	oh
a844	f391	one
a845	f392	two
a846	f393	three
a847	f394	four
a848	f395	five
a849	f396	six
a850	f397	seven
a851	f398	eight
a852	f399	nine
a853	f308 f279	You are playing announcement fragments. Enter announcement set and pound sign.
a854	f307 f279	You are playing announcements. Enter announcement set and pound sign.
a855	f900	Standard

Announcement	Fragment and Text	
a856	f901	Announcement set does not exist
a857	f902	Announcement set
a858	f909 f906	Announcement BUTTONS (1.0 second pause)
a859	f910 f832 f58	You are playing an announcement which need additional input before it can be played. Please enter extension and pound sign. For name addressing, press star A.
a860	f910 f710 f148	You are playing an announcement which needs additional input before it can be played. Enter next name and pound sign. For extension addressing, press star A.
a861	f910 f329	You are playing an announcement which needs additional input before it can be played. You have not yet entered enough characters to identify a specific subscriber. To enter the letter Q, press 7; for Z press 9. ;f484;T{ Enter more characters followed by the pound sign; if you just completed entering the last name, enter the first name. ;f225;and pound sign. a862;f383;T{ Please enter hour, then two digits for minutes, then A for am or P for pm, and pound sign.
a863	f910 f383	You are playing an announcement which need additional input before it can be played. Please enter hour, then two digits for minutes, then A for am or P for pm, and pound sign.
a864	f914	not filed.
a865	f915	No options menu available.
a866	f621	Private.
a867	f969	You are choosing between announcement sets whose names match your entry. To indicate no announcement sets match, delete entry by pressing star D.
a868	f921	To make private, press 1. To send, press #.
a869	f922	To access the Delivery Options Menu, press # after recording your message.

A-106 Standard Announcements

Announcement	Fragment and Text	
a870	f923	Press # to approve your message and access the Delivery Options Menu
a871	f926	(error sound)
a872	f937 f547	Sorry you are having difficulty. Please get help and try again later. Good-bye
a873 Voice out length of message]	f585 f924 f924 f925	IF (NUMBER<100) THEN IF (NUMBER%10==0) THEN IF (NUMBER==0) THEN Zero seconds ELSE a820(NUMBER) — Length of message in seconds seconds ENDIF ELSE a972(NUMBER) ENDIF ELSE a820((NUMBER+30)/60) minutes ENDIF
a874	f4	not private.
a875	f601	Priority
a876	f622	not Priority.
a877	f158 f236 f109	Transfer cannot be completed. Try again later.
a878	f263 f980 f979	You are recording a subscriber name. To record from here, press 1 After recording, press 1 again
a879	f346 f13	You are recording a machine name. To record, press 1. After recording, press 1 again.

Announcement	Fragment and Text	
a880	f263 f980 f979 f304 f339 f292 f497	You are recording a subscriber name. To record from here, press 1 After recording, press 1 again To playback message, press 2-3. To delete your message, press star D. To approve your message, press pound. To replay the last few seconds, press 5. To advance a few seconds, press 6. Louder, press 4. Softer, press 7. Faster, press 9. Slower, press 8. To review your message, press star 1.
a881	f346 f13 f304 f339 f292 f497	You are recording a machine name. To record, press 1. After recording, press 1 again. To playback message, press 2-3. To delete your message, press star D. To approve your message, press pound. To replay the last few seconds, press 5. To advance a few seconds, press 6. Louder, press 4. Softer, press 7. Faster, press 9. Slower, press 8. To review your message, press star 1.
a882	f73 f854	You have NUMBER seconds to finish recording.
a883	f232 f570 f608	Recording stopped. Recorded name too long At the tone, please speak your name. After speaking your name, press 1.
a884	f861 f281 f262	AMIS Message from NAME received TIME DATE a873(NUMBER) — Length of message in seconds
a885	f861 f160 f262	AMIS message received TIME DATE a873(NUMBER) — Length of message in seconds
a886	f978 f861 f510	Unknown AMIS Number

A-108 Standard Announcements

Announcement	Fragment and Text	
a887	f696 f861 f2 f217	Private message to AMIS IF (NUMBER>1) THEN and NUMBER others ENDIF
a888	f86	BUTTONS extension BUTTONS(2)
a889	f25 f498 f224	List id not followed by pound. Please enter a new list id and pound sign.
a890	f37 f49 f224 f471	Extension entered not followed by pound Enter owner's extension and pound sign. If it's your list, press pound.
a891	f38 f470 f224 f471	Name entered not followed by pound Enter owner's last name and pound sign. If it's your list, press pound.
a892	f856 f21 f389	This is a recorded message from NAME To listen, press 0. To delete press star D.
a893	f856 f21 f389 f80	This is a recorded message from NAME To listen, press 0. To delete, press star D. To have system wait, press star W. If finished, please hang up or to disconnect AUDIX, press star star X.
a894	f562 f855 f224	Enter the remote AMIS mailbox id and pound sign.
a895	f867 f855 f868 f833	You are entering the remote AMIS mailbox id Mailbox id must be less than or equal to 16 digits. To delete current entry, press star D.

Announcement	Fragment and Text	
a896	f260 f862	scheduled for TIME DATE It could not be delivered because the recipient appears to be a wrong number.
a897	f260 f863	scheduled for TIME DATE It could not be delivered after multiple attempts to deliver the message.
a898	f864	Automated call, please press 1 to disconnect.
a899	f865	Your number was dialed by mistake. We are sorry for this inconvenience. To prevent this from recurring, this call has been reported as a misdialed call.
a900		
a901 Voice out a number]	f454	IF (NUMBER>1000) — NUMBER = 100 or greater THEN a906(NUMBER) ELSE a820(NUMBER/100) hundred IF (NUMBER%100>0) THEN a820(NUMBER%100) ENDIF ENDIF
a902 Voice out an hour of day]		IF (NUMBER==0) — NUMBER=0 to 59 THEN a820(12) ELSE IF (NUMBER>12) THEN a820(NUMBER-12) ELSE a820(NUMBER) ENDIF ENDIF

A-110 Standard Announcements

Announcement	Fragment and Text
<p>a903 [Voice out minute of hour]</p>	<p>f390 IF (NUMBER>0) THEN IF (NUMBER<10) THEN oh ENDIF a820(NUMBER) ENDIF</p>
<p>a904 [Voice out "A.M." "PM.", "noon",or "midnight"]</p>	<p>f301 IF (NUMBER>12) — Hour of day THEN P.M. ELSE IF (NUMBER==12) THEN IF NUMBER(2)==0) — Minute of hour THEN f201 noon. ELSE f301 P.M. ENDIF ELSE IF (NUMBER==0&&NUMBER(2)==0 THEN f161 midnight ELSE f300 A.M. ENDIF ENDIF ENDIF</p>
<p>a905</p>	<p>(f938 + (NUMBER - 1))</p>
<p>a906 [Voice out large numbers]</p>	<p>f456 IF (NUMBER(1)>1000000) — NUMBER = 1000 or greater THEN million ELSE a820(NUMBER/1000) f455 thousand IF ((NUMBER%1000)>0) THEN a820(NUMBER%1000) ENDIF ENDIF</p>

Announcement	Fragment and Text	
a907	f858 f389	To replay, press 0. To delete, press star D.
a908	f76 f95	Deleted. Please disconnect.
a909	f859	Mailbox id not followed by pound.
a910	f860	Mailbox id not valid
a911	f866	AMIS casual subscribers cannot be added to your list.
a912	f561 f285 f224 f869 f868 f328 f58	You are addressing your message. To add a member, enter extension and pound sign. If the extension entered belongs to a casual AMIS subscriber, you will be prompted for a mailbox id. Mailbox id must be less than or equal to 16 digits. To delete the previous entry, press star D. To add a mailing list you have already created, or a public list owned by others, press star L. To review or modify the list you are creating, press star 1. To approve the list you are creating and move on to the next step, press pound. For name addressing, press star A.
a913	f75 f333	NAME To skip, press pound. To delete, press star D. To add entries to the list or to change status of list, press 1.
a914	f9	star R not available.
a915	f861 f86	AMIS BUTTONS extension BUTTONS(2)
a916		TIME
a917	f711 f712	Alias BUTTONS defined for NAMEEXT
a918		DATE

A-112 Standard Announcements

Announcement	Fragment and Text
a919	f617 To remove private status, press 1. f971 To send, press #.
a920	f56 Thank you for leaving your message. f46 To access your mailbox, press star R. f291 To transfer to another extension, press star T. f973 If you are finished, please hang up.
a921	f56 Thank you for leaving your message. f46 To access your mailbox, press star R. f291 To transfer to another extension, press star T. f972 To reach the covering extension, press zero. f973 If you are finished, please hang up.
a922	f974 Not broadcast.
a923	f975 Not login announcement.
a924	f491 You are getting your incoming messages. To listen to the message, press 0. To respond to the message, press 1. f388 To skip, press pound. f142 To listen to the header, press 3. f143 To step back again, press 2. f578 To skip to the next category, press star pound. f577 To hold the message in its current category, press star star H f377 To delete message, press star D. f339 To replay the last few seconds, press 5. To advance a few seconds, press 6.
a925	f848 You are automatically scanning your incoming messages. To listen to the message, press zero. To respond to the message, press one. f851 To skip, press pound. f142 To listen to the header, press 3. f143 To step back again, press 2. f578 To skip to the next category, press star pound. f577 To hold the message in its current category, press star star H f339 To replay the last few seconds, press 5. To advance a few seconds, press 6. f292 Louder, press 4. Softer, press 7. Faster, press 9. Slower, press 8. f377 To delete message, press star D.

Announcement	Fragment and Text
a926	f375 You are getting your incoming messages. To listen to the message, press 0. To respond to the message, press L f388 To skip, press pound. f142 To listen to the header, press 3. f143 To step back again, press 2. f578 To skip to the next category, press star pound. f577 To hold the message in its current category, press star star H f339 To replay the last few seconds, press 5. To advance a few seconds, press 6. f292 Louder, press 4. Softer, press 7. Faster, press 9. Slower, press 8. f377 To delete message, press star D.
a927	f847 You are automatically scanning your incoming messages. To listen to the message, press zero. To respond to or forward the message, press one. f851 To Skip, press pound. f142 To listen to the header, press 3. f143 To step back again, press 2. f578 To skip to the next category, press star pound. f557 In most cases, entering a star or pound as the first digit will result in the star or pound being outpulsed. A star entered as part of the digit string will be interpreted as a pause of one and a half seconds. If a longer pause is required, use multiple stars in a row. f339 To replay the last few seconds, press 5. To advance a few seconds, press 6. f292 Louder, press 4. Softer, press 7. Faster, press 9. Slower, press 8. f377 To delete message, press star D.
a928	f378 You are checking the status of your outgoing messages. f381 To listen to the message, press 0.. To re-record message before delivery, press 1. f388 To skip, press pound. f142 To listen to the header, press 3. f143 To step back again, press 2. f578 To skip to the next category, press star pound. f339 To replay the last few seconds, press 5. To advance a few seconds, press 6. f292 Louder, press 4. Softer, press 7. Faster, press 9. slower, press 8. f377 To delete message, press star D.

A-114 Standard Announcements

Announcement	Fragment and Text
a929	f378 You are checking the status of your outgoing messages. f474 To listen, press 0. To change or send again, press 1. f388 To Skip, press pound. f142 To listen to the header, press 3. f143 To step back again, press 2. f578 To skip to the next category, press star pound. f339 To replay the last few seconds, press 5. To advance a few seconds, press 6. f292 Louder, press 4. Softer, press 7. Faster, press 9. Slower, press 8. f377 To delete message, press star D.
a930	f378 You are checking the status of your outgoing messages. f388 To skip, press pound. f142 To listen to the header, press 3. f143 To step back again, press 2. f578 To skip to the next category, press star pound. f292 Louder, press 4. Softer, press 7. Faster, press 9. Slower, press 8. f379 To delete status information, press star D.
a931	f674 Due to sending restrictions you cannot send messages to f861 AMIS BUTTONS
a932	f493 You are requesting a transfer. f562 Enter the NUMBER f563 digit extension fl19 you wish to call f224 and pound sign. fl15 To transfer using names instead, press star A. fl17 To reach the covering extension, press star zero. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
a933	f493 You are requesting a transfer. f562 Enter the NUMBER f563 digit extension fl19 you wish to call f224 and pound sign. fl15 To transfer using names instead, press star A. f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.

Announcement	Fragment and Text	
a934	f288 f277 f80	<p>You are in the names directory. To find a subscriber's extension, enter the last name followed by the pound sign. To enter the letter Q, press 7; for Z press 9. To lookup by extension instead press star A.</p> <p>To exit directory, press pound.</p> <p>To have system wait, press star W. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a935	f322 f277 f80	<p>You are in the numbers directory. To find a subscriber's name enter the extension followed by the pound sign. To look up by name instead, press star A.</p> <p>To exit To exit directory, press pound.</p> <p>To have system wait, press star W. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a936	f493 f987 f119 f224 f290 f117 f282	<p>You are requesting a transfer.</p> <p>Enter last name of the person you wish to call and pound sign.</p> <p>If you wish to specify a non-AUDIX subscriber, first change to extension addressing by pressing star A.</p> <p>To reach the covering extension, press star zero.</p> <p>To have system wait, star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, pres star star X.</p>
a937	f493 f987 f119 f224 f290 f282	<p>You are requesting a transfer.</p> <p>Enter last name of the person you wish to call and pound sign.</p> <p>If you wish to specify a non-AUDIX subscriber, first change to extension addressing by pressing star A.</p> <p>To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a938	f291 Q82	<p>To transfa to another extension, press star T.</p> <p>To have system wai~ press star W. To access the names or numbers directory, press star star N. If iinisheG please hangup or to disconnect AUDIX, press star star X.</p>
a939	f357 f291 f80	<p>You are choosing between subscribers whose names match your entry. To indicate no subscribers rnateQ delete entry by pressing star D. To change to extension addressing and delete your entry, press star A.</p> <p>To transfer to another extension, press star T.</p> <p>To have system wait, press star W. If finished, please hang up or to disconnect AUDIX, press star star X.</p>

A-116 Standard Announcements

Announcement	Fragment and Text
a940	<p>f482 Press pound to select NAME</p> <p>f483 or enter more characters</p> <p>f225 and pound sign.</p> <p>f291 To transfer to another extension, press star T.</p> <p>f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star starX.</p>
a941	<p>f482 press pound to select NAMEEXT</p> <p>f483 or enter more characters</p> <p>f225 and pound sign.</p> <p>f291 To transfer to another extension, press star T.</p> <p>f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, Please hang up or to disconnect AUDIX, press star star X.</p>
a942	<p>f291 To transfer to another extension, press star T.</p> <p>f117 To reach the covering extension, press star zero.</p> <p>f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a943	<p>f518 You are creating a voice message which will be delivered to the person specified m your message as soon as possible. Please be aware that in order to forward this message to the recipient, someone will listen to the name and number portion.</p> <p>f13 To record, press 1. After recording, press 1 again.</p> <p>f304 To playback message, press 2-3. To delete your message, press star D. To approve your message, press pound.</p> <p>f292 Louder, press 4. softer, press 7. Faster, press 9. Slower, press 8.</p> <p>f497 To review your message, press star 1.</p> <p>f282 To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star 2.</p>
a944	<p>f517 You are entering the number of the person for whom you are leaving a message. This may be the complete number you dialed or simply the extension. For a faster response, terminate your entry with a pound sign.</p> <p>f80 To have system wait, press star W. If finished, please hang up or to disconnect AUDIX, press star star X.</p> <p>f516 To leave a message that will be delivered as soon as possible,</p> <p>f380 Please wait.</p>

Announcement	Fragment and Text	
a945	f517 f80 f274	<p>You are entering the number of the person for whom you are leaving a message. This may be the complete number you dialed or simply the extension. For a faster response, terminate your entry with a pound sign.</p> <p>To have system wait, press star W. If finished, please hang up or to disconnect AUDIX, press star star X.</p> <p>Please make entry soon, or be disconnected.</p>
a946	f517 f80 f515 f380	<p>You are entering the number of the person for whom you are leaving a message. This may be the complete number you dialed or simply the extension.. For a faster response, terminate your entry with a pound sign.</p> <p>To have system wait, press star W. If finished, please hang up or to disconnect AUDIX, press star star X.</p> <p>To be transferred to an operator, Please wait.</p>
a947	f117 f291 f80	<p>To reach the covering extension, press star zero.</p> <p>To transfer to another extension, press star T.</p> <p>To have system wait, press star W. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a948	f80	<p>To have system wait, press star W. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a949	f291 f80	<p>To transfer to another extension, press star T.</p> <p>To have system wait, press star W. If finished, please hang up or to disconnect AUDIX, press star star X.</p>
a950	f95	<p>Please disconnect.</p>
a951	f517 f117 f291 f80 f515 f380	<p>You are entering the number of the person for whom you are leaving a message. This may be the complete number you dialed or simply the extension. For a faster response, terminate your entry with a pound sign.</p> <p>To reach the covering extension, press star zero.</p> <p>To transfer to another extension, press star T.</p> <p>To have system wait, press star W. If finished, please hang up or to disconnect AUDIX, press star star X.</p> <p>To be transferred to an operator, Please wait.</p>

A-118 Standard Announcements

Announcement	Fragment and Text	
a952	f517 f117 f291 f80 f516 f380	<p>You are entering the number of the person for whom you are leaving a message. This may be the complete number you dialed or simply the extension. For a faster response, terminate your entry with a pound sign.</p> <p>To reach the covering extension, press star zero.</p> <p>To transfer to another extension, press star T.</p> <p>To have system wait, press star W. If finished, please hang up or to disconnect AUDIX, press star star X.</p> <p>To leave a message that will be delivered as soon as possible, Please wait.</p>
a953	f517 f117 f291 f80 f274	<p>You are entering the number of the person for whom you are leaving a message. This may be the complete number you dialed or simply the extension. For a faster response, terminate your entry with a pound sign.</p> <p>To reach the covering extension, press star zero.</p> <p>To transfer to another extension, press star T.</p> <p>To have system wait, press star W. If finished, please hang up or to disconnect AUDIX, press star star X.</p> <p>Please make entry soon, or be disconnected.</p>
a954	f56 f95	<p>Thank you for leaving your message.</p> <p>Please disconnect.</p>
a955	f56 f291 f973	<p>Thank you for leaving your message.</p> <p>To transfer to another extension, press star T.</p> <p>If you are finished, please hang up.</p>
a956	f56 f291 f972 f973	<p>Thank you for leaving your message.</p> <p>To transfer to another extension, press star T.</p> <p>To reach the covering extension, press zero.</p> <p>If you are finished, please hang up.</p>
a957	f291	<p>To transfer to another extension, press star T.</p>
a958	f117 f291	<p>To reach the covering extension, press star zero.</p> <p>To transfer to another extension, press star T.</p>
a959	f95	<p>Please disconnect.</p>
a960	f282	<p>To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.</p>

Announcement	Fragment and Text
a961	f518 You are creating a voice message which will be delivered to the person specified in your message as soon as possible. Please be aware that in order to forward this message to the recipient, someone will listen to the name and number portion. f13 To record, press 1. After recording, press 1 again. f304 To playback message, press 2-3. To delete your message, press star D. To approve your message, press pound. f292 Louder, press 4. Softer, press 7. Faster, press 9. Slower, press 8. f497 To review your message, press star 1. f117 To reach the covering extension, press star zero. f291 To transfer to another extension, press star T. f80 To have system wait, press star W. If finished, please hang up or to disconnect AUDIX, press star star X.
a962	f853 Messages skipped, retained as new.
a963	f477 Press 1 to select
a964	f478 2 to select
a965	f479 3 to select
a966	f480 4 to select
a967	f481 5 to select
a968	f96 For help, press star H.
a969	f99 IF (NUMBER/1000>12) THEN Invalid announcement. ELSE a973(NUMBER) ENDIF a971(NUMBER)
a970	f(0 + (NUMBER / 100)) f(0 + (NUMBER % 100))
a971	f(0 + ((NUMBER/10)%100))

A-120 Standard Announcements

Announcement	Fragment and Text	
<p>a972 Voice out message length]</p>	<p>f400 f924 f924 f924</p>	<pre>IF (NUMBER<10) — Less than 100 seconds THEN ten seconds ELSE IF (NUMBER%10>=5) THEN a820((NUMBER+10)-(NUMBER%10)) seconds ELSE a820((NUMBER)-(NUMBER%10)) seconds ENDIF ENDIF</pre>
<p>a973 [Parse time of day (not voiced)]</p>	<p>f99</p>	<pre>IF(NUMBER%10==2) THEN f(0 + ((NUMBER/ 1000) % 12)) ELSE IF (NUMBER % 10 == 7) THEN IF (NUMBER / 1000 != 12) THEN f(12 + (NUMBER / 1000)) ELSE f(0 + (NUMBER / 1000)) ENDIF ELSE Invalid announcement. ENDIF ENDIF</pre>
<p>a974</p>	<p>f260 f981</p>	<pre>scheduled for TIME DATE Message not delivered because it was longer than the 8 minute AMIS message limit.</pre>

B. Standard Fragments

This appendix includes all of the standard fragments and the text associated with each.

B-2 Standard Fragments

Fragment	Text
f1	Someone is changing your greeting, please try again later.
f2	and
f3	No new remote subscribers can be addressed.
f4	not private.
f5	To record personal greeting, press 1. To listen to personal greeting, press 0. To select which greeting to use, press star pound.
f6	Enter machine voice ID.
f7	Cannot listen to an undeliverable message.
f8	To record a new message, press 4.
f9	star R not available.
f10	That is not a valid machine voice ID.
f11	You are recording machine names.
f12	To re-record, press 1. After recording, press 1 again. To delete, press star D. To playback, press 2-3. To approve as is, press pound.
f13	To record, press 1. After recording, press 1 again.
f14	To make private, press 1. To make public, press 2.
f15	and is
f16	Enter announcement id
f17	including
f18	To forward with comment, press 2.
f19	To review from beginning, press star 1. If finished, press star pound.
f20	Remote extension
f21	To listen, press 0.
f22	To deliver now, press pound. To schedule delivery time enter hour, minutes, A or P, and pound sign.
f23	To record messages, press 1. To get messages, press 2. To administer your greeting, press 3.

Standard Fragments B-3

Fragment	Text
f24	To delete, press star D.
f25	List id not followed by pound.
f26	To record names, press 4. To play names, press 5. To record machine names, press 6. To play machine names, press 7.
f27	To attach original, press Y for yes or N for no.
f29	Returned to checking status of outgoing messages.
f30	To change, press 1.
f31	Date not understood.
f32	You must enter your extension to log on.
f33	To delete, press star D.
f34	Electronic Text
f35	Login incorrect.
f36	To record a personal greeting, press 1.
f37	Extension entered not followed by pound
f38	Name entered not followed by pound
f39	To delete, press star D. To stop playback, press 3.
f40	Time not understood.
f41	To forward message with comment at beginning, press 2.
f42	Can only reply to messages from other subscribers.
f43	Your call is being answered by AUDIX.
f44	is not available. To leave a message, wait for the tone.
f45	is busy. To leave a message, wait for the tone.
f46	To access your mailbox, press star R.
f47	Call from

B 4 Standard Fragments

Fragment	Text
f48	To check your outgoing messages, press 4. To administer other personal options, press 5. To change outcalling information, press 6. To automatically scan incoming messages, press 7. To re-logon, press star star R.
f49	No operator defined.
f50	Call
f51	Entries deleted, please re-enter delivery time.
f53	Message deleted, no delivery will occur.
f54	was only partially recorded due to a system problem.
f55	The message was delivered at
f56	Thank you for leaving your message.
f57	accessed
f58	For name addressing, press star A.
f59	delivered
f60	changed
f61	To modify status, press Y for yes or N for no.
f62	Please delete unneeded messages.
f63	new
f64	old
f65	contains
f66	If correct, press pound. If not, press star D and re-enter time.
f67	To create another list,
f68	undeliverable
f69	undelivered
f70	unopened
f71	To leave a message, wait for the tone.
f72	defaulted to

Fragment	Text
f73	You have
f74	deleted.
f75	To skip, press pound To delete, press star D.
f76	Deleted.
f77	Deleted.
f78	delivered at
f79	Deleted.
f80	To have system wait, press star W. If finished, please hang up or to disconnect AUDIX, press star star X.
f81	digits.
f82	Please leave a message for
f83	entries.
f84	entry.
f85	Erased
f86	extension
f87	This call is experiencing difficulties.
f88	Cannot use the guest password
f89	First message.
f90	Enter fragment id
f91	At end.
f92	Nothing to advance.
f93	You have no personal greeting, system greeting used.
f94	Good-bye.
f95	Please disconnect.
f96	For help, press star H.

B-6 Standard Fragments

Fragment	Text
f97	For help at anytime, press star H.
f98	Message not delivered due to transmission problems.
f99	Invalid announcement.
f100	Invalid Entry.
f101	Invalid fragment.
f102	That is not a valid extension.
f103	Invalid version, re-enter number
f104	Message deliver@ cannot listen to a delivered message.
f105	To restart at the activity menu, press star R.
f106	Last list.
f107	Last member of list.
f108	You are recording a message.
f109	later.
f110	list
f111	Please enter list id
f112	Otherwise, for assistance, press zero now.
f113	You already have a list
f114	To replace list, re-enter id and pound sign. To create a new list, enter new list id
f115	To transfer using names instead, press star A.
f116	List is full.
f117	To reach the covering extension, press star zero.
f118	Enter last name
f119	you wish to call
f120	too large to include.
f121	When finished, approve list by pressing pound.
f122	List space nearly full. You may enter

Standard Fragments B-7

Fragment	Text
f123	new members.
f124	No more list space.
f125	Must be six or fewer numerals.
f126	To forward message with comment at end press 3.
f127	Returned to previous activity.
f128	To request another transfer, press star T.
f129	or leave a message for
f130	because there were no entries.
f131	To send to others not on your list,
f132	You can store your list as is by pressing star pound or add up to
f133	To continue reviewing, press 3. To delete an entry, press star D. If finished reviewing, press star pound.
f134	You can store your list or delete members, but you cannot add members.
f135	and pound sign.
f136	Line busy.
f138	You are listening to machine names.
f139	additional members,
f140	Entry already deleted. To delete more entries, press star 1.
f141	No more lists.
f142	To listen to the header, press 3.
f143	To step back again, press 2.
f144	deleted,
f145	List has 110 entries.
f146	To continue, press pound.
f147	Review completed.
f148	For extension addressing, press star A.
f149	All circuits busy.

B-8 Standard Fragments

Fragment	Text
f150	members.
f151	Try again after the tone.
f152	Leave Word Calling from
f153	Maximum length redorded. To re-record, press 2-1. To approve as is, press pound.
f154	Cannot create new list, you have maximum lists allowed. To select lists to be deleted, press 5-1-2 and follow instructions.
f155	Cannot create new list, total number of members in all your lists equals maximum allowed.
f156	Maximum length recorded
f157	To approve as is, press pound.
f158	Transfer cannot be completed.
f159	member.
f160	message
f161	midnight.
f163	To call sender, press zero.
f164	category.
f165	Returned to getting messages.
f166	At end. To playback, press 2-3.
f167	To approve, press pound. To record from here, press 1. To playback, press 2-3.
f168	messages.
f169	Admin version not specified, please do so using administrator's terminal.
f170	Delivery scheduled
f171	message summary.
f172	You have new
f173	Please enter new password
f175	Please note only AUDIX subscribers can be specified by name.

Standard Fragments B-9

Fragment	Text
f176	Enter fragment id
f177	Cannot listen to a delivered message.
f178	No addressees identified.
f179	Warning, if you do not supply an addressee list, message will be deleted immediately.
f180	Nothing to approve.
f181	Nothing to approve.
f182	Nothing to delete.
f183	Nothing to delete.
f184	Nothing to erase.
f185	not found.
f186	To record messages, press 1. To get messages, press 2. To check your outgoing messages, press 4.
f187	and not added to the list.
f188	Passwords do not match. Please re-enter new password
f189	You have no mailbox.
f190	Message delivered, you cannot change it now.
f191	No more messages.
f192	No messages.
f193	No name recorded
f194	No new messages.
f195	No messages.
f196	You have no personal greeting.
f197	cannot step back.
f198	Partial name deleted.
f199	Nothing to rewind.
f200	No time entered, nothing to delete.

B-10 Standard Fragments

Fragment	Text
f201	noon.
f202	not valid.
f203	No room in your mailbox for a recording.
f207	Message too long to add comment. To record a new message, press star R-1.
f208	is not a public list.
f209	Cannot modify another subscriber's list.
f210	Please enter a new password
f211	to fifteen digits
f212	Please enter password again for confirmation. To delete the password you just entered, press *D
f213	Re-enter password
f214	Approved.
f215	No room to retain a copy.
f216	originally
f217	others
f218	deleted.
f219	owned by
f220	Enter password
f221	Enter announcement id and pound sign. Refer to admin manual for correct id.
f222	Enter fragment id and pound sign. Refer to admin manual for correct id.
f223	Please enter extension
f224	and pound sign.
f225	and pound sign.
f226	private
f227	public
f228	Record at the tone.

Fragment	Text
f229	You will have up to
f230	Seconds to record
f231	cannot be found.
f232	Recording stopped.
f233	Previous login incorrect. Please re-enter extension
f234	To respond or forward, press 1.
f235	To restart at the activity menu, press star R. To transfer to another extension, press star T.
f236	Try again
f237	Or press star R.
f238	To review another list,
f239	followed by the pound sign.
f240	To skip, press pound. To listen, press 0.
f241	To review list, press star 1.
f242	Returned to the
f243	Rewound.
f244	Rewound to previous message.
f245	Please return call.
f246	Message addressed to
f247	To add to list,
f248	scheduled
f249	To change delivery time, press star D
f250	To change delivery time, press star D.
f251	To transfer using extension instead, press star A.
f252	To respond to this message, press 1.
f253	Please enter month, day

B-12 Standard Fragments

Fragment	Text
f254	To play the active version, press 1.
f255	To delete this message, press star D.
f256	At beginning. To re-record, press 1. To playback, press 2-3.
f257	To use personal greeting, press Y. To use system greeting, press N.
f258	Message to
f259	scheduled for
f260	scheduled for
f261	rescheduled for
f262	received
f263	You are recording a subscriber name.
f264	Message not delivered because mailbox was full.
f265	Message not delivered because their mailboxes were full.
f267	Please enter extension
f270	subscriber id
f272	contact administrator for help.
f274	Please make entry soon, or be disconnected.
f275	Cannot get your messages now, due to multiple logins to your mailbox.
f276	Time requested has passed, please re-schedule delivery.
f277	To exit directory, press pound.
f278	Please enter extension
f279	Enter announcement set and pound sign.
f280	For admin version, press 2.
f281	Message from
f282	To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up or to disconnect AUDIX, press star star X.
f283	Your mailbox is more than

Fragment	Text
f284	percent full. Please delete unneeded messages or greetings.
f285	To add a member, enter extension
f286	To add a member, enter last name
f287	Welcome to AUDIX.
f288	You are in the names directory. To find a subscriber's extension, enter the last name followed by the pound sign. To enter the letter Q, press 7; for Z press 9. To lookup by extension instead press star A.
f290	If you wish to specify anon-AUDIX subscriber, first change to extension addressing by pressing star A.
f291	To transfer to another extension, press star T.
f292	Louder, press 4. Softer, press 7. Faster, press 9. Slower, press 8.
f293	Nothing to playback.
f294	To add entries, press 1.
f295	To re-enter list, press star L.
f296	To delete, press star D.
f297	To specify owner by extension, press star A.
f298	To specify owner by name, press star A.
f299	You are administering your greeting.
f300	A.M.
f301	P.M.
f302	You are recording announcement fragments. Enter fragment id followed by pound sign. Refer to admin manual for correct id.
f303	You are recording names. Enter extension
f304	To playback message, press 2-3. To delete your message, press star D. To approve your message, press pound.
f305	You are at the activity menu.
f306	You are changing your password.

B-14 Standard Fragments

Fragment	Text
f307	You are playing announcements.
f308	You are playing announcement fragments.
f309	You are playing names.
f310	January
f311	February
f312	March
f313	April
f314	May
f315	June
f316	July
f317	August
f318	September
f319	October
f320	November
f321	December
f322	You are in the numbers directory. To find a subscriber's name enter the extension followed by the pound sign. To look up by name instead, press star A.
f323	You are responding to a piece of incoming mail.
f324	You are selecting which greeting will be played to callers. If you want your personal greeting to be played, press Y for yes. If you press N for no, the system greeting will be used.
f325	You are administering your lists. To create a mailing list, press 1. To play a summary of all your lists, press 2. To review a particular list, press 3.
f326	You are doing system administration. To record names, press 4. To play names, press 5. To record a machine name, press 6. To play a machine name, press 7. To record fragments, press 1. To play fragments, press 2. To play announcements, press 3.
f327	You are creating a mailing list.

Fragment	Text
f328	To delete the previous entry, press star D. To add a mailing list you have already created, or a public list owned by others, press star L. To review or modify the list you are creating, press star 1. To approve the list you are creating and move on to the the next step press pound.
f329	You have not yet entered enough characters to identify a specific subscriber. To enter the letter Q, press 7; for Z press 9.
f330	Or enter just the pound sign if it's your phone.
f331	Personal greeting used.
f332	System greeting used.
f333	To add entries to the list or to change status of list, press 1.
f334	When finished addressing, press pound
f335	When finished, press pound.
f336	To review addressees, press star 1.
f338	To play the admin version, press 2.
f339	To replay the last few seconds, press 5. To advance a few seconds, press 6.
f340	Enter the hour, one through twelve, then two digits for the minutes, then A for AM or P for PM, and the pound sign.
f341	Enter the number of the month, one through twelve, then two digits for the day of the month, then the pound sign.
f342	Electronic document communication
f343	Leave word calling
f344	Message Center Service
f345	Voice mail
f346	You are recording a machine name.
f347	You are adding a list.
f348	You are specifying a mailing list to review.
f349	To approve list as is, press pound.

B-16 Standard Fragments

Fragment	Text
f350	Sunday
f351	Monday
f352	Tuesday
f353	Wednesday
f354	Thursday
f355	Friday
f356	Saturday
f357	You are choosing between subscribers whose names match your entry. To indicate no subscribers match, delete entry by pressing star D. To change to extension addressing and delete your entry, press star A.
f358	You are identifying a list as private or public.
f359	You are changing the status of your list. To modify status, press Y for yes or N for no.
f360	You are scanning mailing lists. To review list members, press 0. To rewind to previous list, press 2. To continue scanning lists, press 3.
f361	To skip to next list, press pound. To delete list, press star D.
f362	If you own the list, press pound. If someone else owns the list
f363	To approve the list you are creating, press pound.
f364	enter owner's extension
f365	enter owner's name
f366	To specify a different owner by extension, press star D.
f367	To specify a different owner by name, press star D.
f368	You are entering the number for a new list. Please enter a number up to six digits long
f369	To replace an existing list, enter that list's number,
f370	These are entries in your list.
f371	To rewind to current entry, press 2. To rewind to previous entries, press 2 as many times as necessary. To continue playback of list, press 3.

Fragment	Text
f372	To skip to next entry, press pound. To delete current entry, press star D.
f373	You are choosing whether to attach a copy of original message to your reply. To include the original, press Y for yes. To send only your reply, press N for no.
f374	You are choosing whether to file this message. To file a copy, press Y for yes. To send without filing a copy, press N for no.
f375	You are getting your incoming messages. To listen to the message, press 0. To respond to the message, press 1.
f376	To skip to the next header, press the pound sign. To listen to the header, rewind by pressing two, then play by pressing three. To skip to the next category, press star pound.
f377	To delete message, press star D.
f378	You are checking the status of your outgoing messages.
f379	To delete status information, press star D.
f380	Please wait..
f381	To listen to the message, press 0. To re-record message before delivery, press 1.
f382	You are scheduling your message for delivery.
f383	Please enter hour, then two digits for minutes, then A for am or P for pm, and pound sign.
f384	Please enter number of month, then two digits for day, and pound sign.
f385	To approve delivery time, press pound. To modify delivery time, press star D and listen for further instructions.
f386	Cannot change a delivered message.
f387	Message not delivered because recipient not found.
f388	To skip, press pound
f389	To delete, press star D.
f390	oh
f391	one

B-18 Standard Fragments

Fragment	Text
f392	two
f393	three
f394	four
f395	five
f396	six
f397	seven
f398	eight
f399	nine
f400	ten
f401	eleven
f402	twelve
f403	thirteen
f404	fourteen
f405	fifteen
f406	sixteen
f407	seventeen
f408	eighteen
f409	nineteen
f410	twenty
f411	twenty-one
f412	twenty-two
f413	twenty-three
f414	twenty-four
f415	twenty-five
f416	twenty-six

Fragment	Text
f417	twenty-seven
f418	twenty-eight
f419	twenty-nine
f420	thirty
f421	thirty-one
f422	thirty-two
f423	thirty-three
f424	thirty-four
f425	thirty-five
f426	thirty-six
f427	thirty-seven
f428	thirty-eight
f429	thirty-nine
f430	forty
f431	forty-one
f432	forty-two
f433	forty-three
f434	forty-four
f435	forty-five
f436	forty-six
f437	forty-seven
f438	forty-eight
f439	forty-nine
f440	fifty
f441	fifty-one
f442	fifty-two

B-20 Standard Fragments

Fragment	Text
f443	fifty-three
f444	fifty-four
f445	fifty-five
f446	fifty-six
f447	fifty-seven
f448	fifty-eight
f449	fifty-nine
f450	sixty
f451	seventy
f452	eighty
f453	ninety
f454	hundred
f455	thousand
f456	million
f457	ninetieth.
f458	hundredth.
f459	thousandth.
f460	millionth.
f461	billionth.
f462	pound
f463	star
f464	Enter extensions
f465	Enter last name
f466	created
f468	To continue playing, press 3.
f469	Enter owner's extension

Fragment	Text
f470	Enter owner's last name
f471	If it's your list, press pound.
f472	To approve, press pound. To record from here, press 1.
f473	filed
f474	To listen, press 0. To change or send again, press 1.
f475	To file a copy, press Y for yes or N for no.
f477	Press 1 to select
f478	2 to select
f479	3 to select
f480	4 to select
f481	5 to select
f482	Press pound to select
f483	or enter more characters
f484	Enter more characters followed by the pound sign; if you just completed entering the last name, enter the first name.
f485	has
f486	To reply to sender by voice@ press 1.
f487	To delete time, press star D. To default rest of the delivery time, press pound.
f488	To specify immediate delivery, press pound. Otherwise
f491	You are getting your incoming messages. To listen to the message, press 0. To respond to the message, press 1.
f492	Owner erased
f493	You are requesting a transfer.
f494	private.
f495	public.

B-22 Standard Fragments

Fragment	Text
f496	Filed.
f497	To review your message, press star L
f498	Please enter a new list id
f499	When finished recording, press # to approve, or 1 to edit your message.
f500	This is AUDIX.
f501	To record messages, press one. To get messages, press two. To administer attendant menu, press 3.
f502	To record attendant menu, press 1. To listen to attendant menu, press 0.
f503	You are administering your attendant menu.
f504	Transferring to an operator,
f505	You have selected an invalid option.
f506	Menu approved and activated.
f507	The person you called is not available. To leave a message, use touch tones to re-enter the number you called.
f508	Attendant Service not available, try again later.
f509	System not administered for outcalling.
f510	Number
f511	If you do not have a touch tone phone,
f512	Your call is being transferred to an operator.
f513	Begin your message by saying the name and telephone number of the person you are calling. Someone will listen to the start of your message, and then forward the complete message to the person you called.
f514	otherwise
f515	To be transferred to an operator,
f516	To leave a message that will be delivered as soon as possible,
f517	You are entering the number of the person for whom you are leaving a message. This may be the complete number you dialed or simply the extension. For a faster response, terminate your entry with a pound sign.

Fragment	Text
f518	You are creating a voice message which will be delivered to the person specified in your message as soon as possible. Please be aware that in order to forward this message to the recipient, someone will listen to the name and number portion.
f519	You are not authorized for outcalling.
f520	Your outcalling number,
f521	turned on
f522	Turned off. To restart at the activity menu, press star R.
f523	for
f524	to
f525	any time
f526	subject to administrator restrictions
f527	To change number, press 1. To change times, press 2. For instructions on entering your outcalling number, press 3.
f528	To turn on, press y. To turn off, press n.
f529	You are changing your outcalling options.
f530	Outcalling
f531	Enter outcalling number
f532	To change your outcalling phone number, press 1 and enter the number to be called followed by the pound sign. Anything you enter will be interpreted as a part of the called number. No global commands such as star H will be accepted at this time .
f533	Too many digits.
f534	Your outcalling number is
f535	For outcalling any time press 1. For outcalling during prime time, press 2. To specify your times, press 3. For system outcalling schedule, press 4.
f536	You are specifying your outcalling time period. The time you specify will be restricted by the times allowed by the system administrator.
f537	Enter the starting hour, minutes A or P, and pound sign.

B-24 Standard Fragments

Fragment	Text
f538	Enter the ending hour, minutes, A or P, and pound sign.
f539	The system allows outcalls from
f540	and from
f541	Up to
f542	digits may be used.
f543	To avoid further notification of these messages, press star pound.
f544	Outcalling specified for
f545	To delete own time, press star D.
f546	pause
f547	Good-bye
f548	You have no attendant menu.
f549	You are administering your attendant menu. To create attendant menu, press 1.
f550	To rewind your attendant menu, press two. To delete it, press star D. To stop playback of your attendant menu, press three.
f551	To access your messages,
f552	is not authorized to receive messages.
f553	You may enter another number
f555	To access your mailbox, press star R.
f556	To exit, press star pound now.
f557	In most cases, entering a star or pound as the first digit will result in the star or pound being outpulsed. A star entered as part of the digit string will be interpreted as a pause of one and a half seconds. If a longer pause is required, use multiple stars in a row.
f559	A name cannot be recorded until the size of the names tile system is increased.
f560	If you are programming a number to call a pager that requires a pound sign termination, press y to hear further help. Otherwise, press n to return to outcalling administration.
f561	You are addressing your message.
f562	Enter the

Fragment	Text
f563	digit extension
f564	There is no room in the mailbox to leave a message.
f565	Outcall canceled for new messages currently in mailbox.
f566	You are responding to an outcall notifying you of new messages.
f567	Either logging in or pressing star pound will result in the outcall being canceled for the new messages currently in your mailbox. If additional new messages arrive, another outcall will be scheduled.
f569	To modify, press one. If finished, press star pound.
f570	Recorded name too long
f571	Non-existent subscriber
f572	To access the options menu, press star M.
f573	DELETED DUE TO REDESIGN
f574	Private
f575	Cannot forward a private message
f576	Recipients can forward this message
f577	To hold the message in its current category, press star star H
f578	To skip to the next category, press star pound.
f579	Password must be
f580	Cannot attach a private message
f581	Press N now
f582	AUDIX passwords must now be at least
f584	Message not delivered because special feature denied on recipients machine.
f585	Zero
f586	To skip, press pound.
f587	You are reviewing a list.

B-26 Standard Fragments

Fragment	Text
f588	or more digits.
f589	For pagers requiring a pound sign termination, start your number with a double pound sign. This will result in a single pound being outpulsed at the end of the digit string. Then, a star or pound in the next position will be interpreted as part of the outcalling number.
f590	A star entered as part of the digit string will be interpreted as a pause of one and a half seconds. If a longer pause is required, use multiple stars in a row.
f591	To change your outcalling phone number, press one. To hear further instructions on programming a pager, press y. To return to outcalling administration, press n.
f592	AUDIX passwords must now be
f593	Please choose a new password of
f600	new Broadcast messages.
f601	Priority
f602	other
f603	You also have
f604	As you use AUDIX your name will be included in system announcements that you and other people will hear. Press 1, and at the tone, please speak your name. After speaking your name, press 1 again.
f605	To re-record your name, press 1. To approve, press pound.
f607	Name cannot be saved at this time, please continue
f608	At the tone, please speak your name. After speaking your name, press 1.
f609	No room to save Broadcastt message so it will be retained in the new message category.
f610	You are recording your name. After you record your name, you can access other AUDIX features. As you use AUDIX your name will be included in system announcements that you and other people will hear. Press 1 and at the tone, please speak your first and last name as you would like others to hear it. After speaking your name, press 1 again.
f611	You are recording your name. To record your name, press 1. After recording, press 1 again. To playback name, press 2-3. To approve, press pound.
f612	To make private, press 1.

Fragment	Text
f613	To make priority, press 2.
f614	To make broadcast, press 8.
f615	To make a login announcement, press 9.
f616	To exit options menu, press pound.
f617	To remove private status, press 1.
f618	To remove priority status, press 2.
f619	To remove broadcast status, press 8.
f620	To remove login announcement status, press 9,
f621	Private.
f622	not Priority.
f623	Broadcast
f624	Login announcement.
f625	To activate message waiting notification, press 1.
f626	To specify expiration date, press 2.
f627	To approve broadcast options, press pound.
f628	To deactivate message waiting notification, press 1.
f629	Please enter month, day, and pound sign.
f630	To change expiration date from
f631	Message waiting notification activated.
f632	Expiration date will be
f633	To make non-interruptible press 1.
f634	To approve login announcement options, press pound.
f635	To remove non-interruptible status, press 1.
f636	Login announcement will be non-interruptible.
f637	Invalid date.

B-28 Standard Fragments

Fragment	Text
f638	is prior to delivery date, please re-schedule.
f639	Message cannot be both broadcast and priority.
f640	Message cannot be both a login announcement and priority.
f641	Message cannot be both a login announcement and private.
f642	Message cannot be both broadcast and a login announcement
f643	You are choosing options for this message. There are no options currently set.
f644	You are choosing options for this message. With the current settings,
f645	Private messages cannot be forwarded by the recipients.
f646	A priority message will be delivered before other messages and will be flagged for special attention in the recipient's mailbox.
f647	the message will be private.
f648	the message will be priority.
f649	the message will be broadcast.
f650	the message will be a login announcement.
f651	the message will be private and priority.
f652	A broadcast message is delivered to every subscriber on this machine. You may also address a broadcast message to subscribers on other machines.
f653	For broadcast options, press star M.
f654	the message will be broadcast and private.
f655	A login announcement will be played each time any subscriber logs onto this machine. You may also address a login message to subscribers on other machines.
f656	For login announcement options, press star M.
f657	You are choosing options for this broadcast message.
f658	Message waiting notification is currently not active.
f659	Message waiting notification will alert all local subscribers of this message. This option should be used sparingly, for it can impact system performance.

Fragment	Text
f660	Expiration date specifies the last day this broadcast message will be available to subscribers. The expiration date does not apply to a broadcast message already received by a subscriber and saved in their mailbox. The default expiration date is the second day after the scheduled delivery date.
f661	To approve these options, press pound.
f662	Message waiting notification is active.
f663	Message waiting notification is not active and this message has an expiration date of.
f664	Message waiting notification is active and this message has an expiration date of.
f665	You are choosing options for this login announcement.
f666	With the current settings, this login announcement will be non-interruptible.
f667	With the current settings, this login announcement will be interruptible.
f668	With the current settings, this login announcement will be non-interruptible and the login announcement has an expiration date of.
f669	With the current settings, this login announcement will be interruptible and the login announcement has an expiration date of.
f670	Non-interruptible status forces each subscriber to listen to the entire login announcement every time they log onto this machine.
f671	Expiration date specifies the last day this login announcement will be available to subscribers. The default expiration date is the second day after the scheduled delivery date.
f674	Due to sending restrictions, you cannot send messages to
f678	is past the expiration date, please reschedule.
f679	is not available. Sorry, you cannot leave a message now because this user's mailbox is full.
f680	is busy. Sorry, you cannot leave a message now because this user's mailbox is full.
f681	Sorry, cannot leave a message now because this user's mailbox is full.
f682	Broadcast message from

B-30 Standard Fragments

Fragment	Text
f683	Broadcaster has deleted this broadcast message.
f684	Private, broadcast message from
f685	Private, priority message from
f686	Private message from
f687	Undeliverable message notification received
f688	An undeliverable message was returned to your outgoing mailbox. To access your outgoing mailbox, press star R 4.
f689	Expiration time is
f690	Priority message from
f691	Login announcement from
f692	Broadcast message deleted.
f693	Broadcast message to all local subscribers
f694	Private, broadcast message to all local subscribers
f695	Private, priority message to
f696	Private message to
f697	Login announcement to all local subscribers
f698	Priority message to
f699	Message not delivered because another login announcement is active.
f700	To administer mailing lists, press 1. To administer personal directory, press 2.
f701	To change your password, press 4.
f702	To record your name, press 5.
f703	You are at subscriber administration.
f704	To create lists, press 1. To scan lists, press 2. To review and modify lists, press 3.

Fragment	Text
f705	Directory contains
f706	To add entries, press 1. To review all entries, press 2. To review a specific entry, press 3.
f707	If finished, press star pound.
f708	If finished adding entries, press pound.
f709	Enter alias for
f710	Enter next name and pound sign.
f711	Alias
f712	defined for
f713	Enter next extension and pound sign.
f714	Directory has no entries.
f715	Cannot add new entries because your directory is full.
f716	Alias must be ten or fewer numerals.
f717	Alias already defined.
f718	Name entered not followed by pound and not added to the directory.
f719	Extension entered not followed by pound and not added to the directory.
f720	Alias entered not followed by pound and not added to the directory.
f721	Directory is full.
f722	was not added to your personal directory.
f723	You are administering your personal directory.
f724	Personal directory review completed
f725	You are adding entries to your personal directory.
f726	You are reviewing all entries in your personal directory.
f727	Enter alias and pound sign.
f728	deleted.

B-32 Standard Fragments

Fragment	Text
f729	You are reviewing a specific entry in your personal directory. To delete the current entry, press star D. To review another entry, enter the alias followed by the pound sign.
f730	Message not delivered because the broadcast mailbox was not defined.
f731	To record messages, press 1. To get messages, press 2.
f734	Private and priority.
f735	Broadcast and private.
f736	You are recording your name. As you use AUDIX your name will be included in system announcements that you and other people will hear.
f737	Login announcement will be interruptible.
f738	Message not delivered due to sending restrictions.
f739	Message sent to all local subscribers.
f740	Private message sent to all local subscribers.
f741	Private, priority message sent to
f742	Private message sent to
f743	Priority message sent to
f744	For all calls,...
f745	active.
f747	For internal calls,...
f748	For external calls,...
f749	For busy calls,...
f750	For no answer calls,...
f751	For out-of-hours calls,...
f752	To listen to a greeting, press 0. To create, change or delete a greeting, press 1. To scan all your greetings, press 2. To activate a greeting, press 3. To administer call types, press 4. If finished, press pound.
f753	Enter greeting number.

Fragment	Text
f754	Greeting
f755	not recorded.
f756	To listen to greeting
f757	To re-record, press 1.
f758	To delete, press star D.
f759	To review status, press 2.
f760	press 0.
f762	press 2.
f764	To use this greeting for all calls, press 0. For internal calls, press 1. For external calls, press 2.
f765	recorded, but not active
f766	To use this greeting for all calls, press 1.
f767	To use this greeting for all calls, press 0. For busy calls, press 1. For no answer calls, press 2
f768	approved
f769	Nothing to approve.
f770	recorded and active
f771	approved and active
f772	again
f773	To activate for out-of-hours calls, press 3.
f774	If you have addressed this message and wish to deliver it immediately, press star star pound.
f775	To record messages, press one. To get messages, press two. To administer personal greetings, press 3.
f776	the system greeting
f777	Cannot listen to system greeting.

B-34 Standard Fragments

Fragment	Text
f778	Cannot modify system greeting.
f779	No greetings recorded.
f780	Personal greetings review completed.
f781	To skip to the next greeting, press the pound sign.
f782	To activate a greeting, enter greeting number. To deactivate greeting, activate a different greeting in its place.
f783	To activate another greeting, enter greeting number. To deactivate a greeting, activate a different greeting in its place.
f784	To activate system greeting, enter zero.
f785	Same greeting used for all calls.
f786	To identify calls as internal and external, press 1.
f787	To identify calls as busy and no answer, press 2.
f788	To identify calls as out-of-hours, press 3.
f789	otherwise, press 4.
f790	Calls identified as internal and external.
f791	Calls identified as busy and no answer.
f792	Calls identified as out-of-hours.
f793	Calls not identified as out-of-hours.
f794	To change identification to busy and no answer, press 2.
f795	To change to identification internal and external, press 1.
f796	To remove out-of-hours identification, press 4.
f797	To use same greeting for all calls, press 5.
f798	Prime time is
f799	Enter last name
f800	You are specifying the expiration date.

Fragment	Text
f801	To respond to this notification, press one. To delete, press star D. To skip, press pound.
f802	Cannot send a message to the broadcast mailbox.
f804	not defined.
f805	For internal...
f806	For external...
f807	For busy...
f808	For no answer...
f809	internal
f810	external
f811	busy
f812	no answer
f813	and out-of-hours
f814	calls.
f815	You are administering your personal greetings.
f816	You are listening to a personal greeting.
f817	You are recording a personal greeting.
f818	You have just recorded
f819	You are scanning your personal greetings.
f820	You are selecting which greeting to activate.
	You are administering call types.
f822	As you use AUDIX your name will be included in system announcements that you and other people will hear. At the tone, please speak your name. After speaking your name, press one.
f823	for all calls
f825	for internal

B-36 Standard Fragments

Fragment	Text
f826	for external
f827	for busy
f828	for no answer
f829	for out-of-hours
f830	You must approve your recording.
f831	To exit the expiration date options, press star pound.
f832	Please enter extension and pound sign.
f833	To delete current entry, press star D.
f835	for all new messages
f836	only for new priority messages
f837	To turn on Outcalling for all new messages, press 1. To turn on outcalling only for new priority messages, press 2.
f838	You are selecting which messages will receive outcalls.
f839	To rewind to the previous greeting, press 2.
f840	Option
f841	not defined
f842	Announcement not recorded. Try again later.
f843	To scan headers and messages, press 1. To scan headers only, press 2. To scan messages only, press 3.
f844	End of message.
f845	Next message.
f846	You are selecting an option for Automatic Message Scan.
f847	You are automatically scanning your incoming messages. To listen to the message, press zero. To respond to or forward the message, press one.
f848	You are automatically scanning your incoming messages. To listen to the message, press zero. To respond to the message, press one.

Fragment	Text
f849	To skip to the next message, press the pound sign. To listen to the header, rewind by pressing two, then play by pressing three. To skip to the next category, press star pound.
f850	Broadcast and Login Message services are not available.
f851	To skip, press pound
f852	To rewind to the current entry, press two. To rewind to previous entries, press two as many times as necessary.
f853	Messages skipped, retained as new.
f854	seconds to finish recoding.
f855	remote AMIS mailbox id
f856	This is a recorded message from
f857	from
f858	To replay, press 0.
f859	Mailbox id not followed by pound.
f860	Mailbox id not valid.
f861	AMIS
f862	It could not be delivered because the recipient appears to be a wrong number.
f863	It could not be delivered after multiple attempts to deliver the message.
f864	Automated call, please press 1 to disconnect.
f865	Your number was dialed by mistake. We are sorry for this inconvenience. To prevent this from recurring, this call has been reported as a misdialed call.
f866	AMIS casual subscribers cannot be added to your list.
f867	You are entering the
f868	Mailbox id must be less than or equal to 16 digits.
f869	If the extension entered belongs to a casual AMIS subscriber, you will be prompted for a mailbox id.

B-38 Standard Fragments

Fragment	Text
f870	
f871	
f872	
f873	
f874	
f875	
f876	
f877	
f878	
f879	
f880	
f881	
f882	
f883	
f884	
f885	
f886	
f887	
f888	
f889	
f890	
f891	
f892	
f893	
f894	

Fragment	Text
f895	
f896	
f897	
f898	
f899	
f900	standard
f901	Announcement set does not exist
f902	Announcement set
f903	(.1 second pause)
f904	(.2 second pause)
f905	(.5 second pause)
f906	(1.0 second pause)
f907	(2.0 second pause)
f908	(5.0 second pause)
f909	Announcement
f910	You are playing an announcement which need additional input before it can be played.
f911	Enter buttons followed by pound.
f912	Enter number followed by pound.
f913	If finished, press pound.
f914	not filed.
f915	No options menu available.
f916	To send message, press pound. Or enter a delivery option. To hear a list of options, press zero.
f917	To schedule delivery, press 3.
f918	To re-schedule delivery, press 3.
f919	To file a copy, press 4.

B 4 0 **Standard Fragments**

Fragment	Text
f920	To not file a copy, press 4.
f921	To make private, press 1. To send, press #.
f922	To access the Delivery Options Menu, press # after recording your message.
f923	Press # to approve your message and access the Delivery Options Menu
f924	seconds
f925	minutes
f926	(error sound)
f927	You have new
f928	New Messages
f929	Old Messages
f930	Accessed Messages
f931	Delivered Messages
f932	Filed Messages
f933	Undeliverable Messages
f934	Undelivered Messages
f935	Unopened Messages
f936	Partial entry deleted.
f937	Sorry you are having difficulty. Please get help and try again later.
f938	first
f939	second
f940	third
f941	fourth
f942	fifth
f943	sixth
f944	seventh

Fragment	Text
f945	eighth
f946	ninth
f947	tenth
f948	eleventh
f949	twelvth
f950	thirteenth
f951	fourteenth
f952	fifteenth
f953	sixteenth
f954	seventeenth
f955	eighteenth
f956	nineteenth
f957	twentieth
f958	twenty-first
f959	twenty-second
f960	twenty-third
f961	twenty-fourth
f962	twenty-fifth
f963	twenty-sixth
f964	twenty-seventh
f965	twenty-eighth
f966	twenty-ninth
f967	thirtieth
f968	thirty-first

B42 Standard Fragments

Fragment	Text
f969	You are choosing between announcement sets whose names match your entry. To indicate no announcement sets match, delete entry by pressing star D.
f970	To continue reviewing, press 3. To delete an entry, press star D. If finished reviewing, press pound.
f971	To send, press #.
f972	To reach the covering extension, press zero.
f973	If you are finished, please hang up.
f974	Not broadcast
f975	Not login announcement.
f976	Name
f977	Name not found.
f978	unknown
f979	After recording, press 1 again
f980	To record from here, press 1
f981	Message not delivered because it was longer than the 8 minute AMIS message limit.
f982	To record and send voice mail messages, press 1. To get messages, press 2. To check your outgoing messages, press 4.
f983	To record and send voice mail messages, press 1. To get messages, press 2. To record or change the greeting heard by callers, press 3.
f984	To record and send voice mail messages, press 1. To get messages, press 2. To administer attendant menu, press 3.
f985	To record and send voice mail messages, press 1. To get messages, press 2.
f986	To record and send voice mail messages, press 1. To get messages, press 2. To record or change the greetings heard by the callers, press 3.
f987	Enter last name of the person

C. Fragment/Announcement Cross-Reference

This appendix provides a cross-referenced listing of the system announcements that access each system fragment.

C-2 Fragment/Announcement Cross-Reference

Fragment	System Announcements That Use The Fragment
1	649
2	210, 235, 236, 273, 342, 343, 344, 350, 352, 366, 372, 381, 387, 398, 404, 412, 418, 493, 540, 541, 542, 543, 544, 545, 546, 553, 554, 673, 675, 767, 794, 800, 838, 839, 840, 841, 887
3	608
4	874
5	26, 283
6	98, 100, 509
7	
8	62, 85, 123, 125, 126, 128, 168, 169, 170, 202, 203, 204, 205, 693, 759, 760, 761, 768
9	914
10	442
11	98
12	310
13	49, 68, 101, 267, 332, 581, 589, 879, 881, 943, 961
14	39, 502
15	455, 456
16	238
17	184, 190
18	202, 693, 759, 768
19	695, 698
20	822
21	276, 527, 530, 747, 892, 893
22	318, 609, 715, 765
23	113, 722
24	508, 747

Fragment	System Announcements That Use The Fragment
25	889
26	757
27	249
28	
29	255
30	508
31	261
32	262
33	315
34	538, 540, 547, 548
35	264, 265
36	50
37	654, 890
38	655, 891
39	26
40	266
41	62, 85, 123, 170, 203
42	284
43	282, 288, 289, 290, 291, 292, 293
44	289, 292
45	290, 291
46	4, 8, 27, 68, 69, 70, 71, 285, 920, 921
47	286, 287, 658, 659
48	76, 77, 113, 114, 115, 119, 120, 121, 125, 127, 129, 159
49	603
50	295, 296, 660, 661

C-4 Fragment/Announcement Cross-Reference

Fragment	System Announcements That Use The Fragment
51	280
52	
53	561
54	
55	
56	285, 920, 921, 954, 955, 956
57	680
58	6, 19, 131, 328, 859, 912
59	681
60	308
61	457, 458
62	566, 567, 568, 569
63	183, 184, 185, 190, 235, 236, 683
64	684
65	451, 452, 469
66	535, 626
67	559
68	685
69	686
70	687
71	198
72	
73	882
74	187, 379, 380, 381, 382, 383, 384, 385, 386, 387, 388, 389, 390, 391, 392, 393, 453
75	179, 913
76	281, 312, 576, 908
77	316, 317, 318
78	
79	323

Fragment	System Announcements That Use The Fragment
80	14, 15, 16, 17, 18, 61, 68, 69, 70, 71, 102, 103, 104, 147, 152, 763, 893, 934, 935, 939, 944, 945, 946, 947, 948, 949, 951, 953, 961
81	199, 443, 514
82	504
83	320, 451
84	320, 451
85	332
86	287, 295, 334, 335, 336, 337, 338, 506, 659, 660, 709, 821, 888, 915
87	812, 834
88	431
89	348
90	354
91	528
92	573
93	362
94	363
95	191, 253, 258, 336, 565, 615, 766, 834, 908, 950, 954, 959
96	496, 694, 763, 968
97	815
98	639, 640, 741
99	437, 969, 973
100	263,496
101	441
102	445
103	
104	447
105	13, 96, 97,99, 105, 106, 116, 117, 147, 152, 171, 172, 200, 246, 559
106	
107	
108	34, 49

C - 6 Fragment/Announcement Cross-Reference

Fragment	System Announcements That Use The Fragment
109	191, 712, 834,877
110	449, 450, 451, 452, 453, 454, 455, 456, 457, 458, 459, 460, 461, 462, 463, 464, 465, 466, 467, 468, 469, 470, 471, 472, 473, 474, 475, 477, 662, 674, 836
111	29, 31, 63, 64, 478, 511, 559
112	291, 292
113	484
114	484
115	116, 117, 193, 194, 195, 196, 932, 933
116	481, 482
117	4, 9, 15, 68, 69, 70, 71, 79, 80, 108, 114, 116, 121, 127, 129, 171, 193, 194, 770, 771, 932, 936, 942, 947, 951, 952, 953, 958, 961
118	349, 770, 771, 773, 774
119	116, 117, 171, 172, 932, 933, 936, 937
120	460, 461, 462, 463, 470, 471, 472
121	219, 223
122	487
123	487
124	463, 472, 476, 480, 483
125	511
126	62, 85, 123, 170, 203
127	694
128	446, 769
129	446
130	459
131	220
132	460, 461, 470
133	480, 481
134	462, 471
135	217, 218, 219, 221, 222, 223, 654, 655
136	435

Fragment/Announcement Cross-Reference C-7

Fragment	System Announcements That Use The Fragment
137	
138	100, 107
139	460, 461, 470
140	322
141	479
142	348, 450, 454, 607, 680, 681, 682, 683, 684, 685, 686, 687, 706, 733, 836, 924, 925, 926, 927, 928, 929, 930
143	175, 607, 733, 836, 924, 925, 926, 927, 928, 929, 930
144	459, 464, 473
145	324
146	175, 176
147	696, 697, 698
148	7, 20, 67, 132, 327, 860
149	436
150	452, 455, 456, 469
151	
152	505, 506
153	510
154	485
155	486
156	294, 513
157	513
158	191, 877
159	452, 455, 456
160	183, 184, 185, 190, 235, 236, 885
161	904
162	
163	85, 168, 169, 170, 759, 760, 761, 768
164	680, 681, 682, 683, 684, 685, 686, 687
165	527, 530

C-8 Fragment/Announcernent Cross-Reference

Fragment	System Announcements That Use The Fragment
166	531
167	34, 533, 560
168	183, 184, 185, 190, 235, 236, 538, 539, 540, 541, 542, 543, 544, 545, 546, 547, 548, 549, 550, 551, 552, 553, 554, 555, 627
169	577
170	534, 535
171	
172	539, 542, 544, 546, 548, 550, 552, 554, 627
173	199, 317, 431, 443, 444, 514, 586, 612
174	
175	349, 770, 771
176	
177	574
178	575, 576
179	816
180	578
181	562, 580, 581, 611
182	585, 586
183	588
184	589
185	229, 467, 468, 475
186	584
187	654, 655
188	592
189	593
190	594
191	595
192	597
193	598, 599, 692
194	600

Fragment/Announcement Cross-Reference C-9

Fragment	System Announcements That Use The Fragment
195	602
196	604
197	178, 226, 348, 454
198	537
199	605, 606, 607
200	609
201	904
202	338, 466, 614, 615, 753, 754
203	566, 567, 568
204	
205	
206	
207	571
208	465, 474, 477
209	572
210	14, 51
211	444
212	10, 16
213	201
214	648
215	569
216	637, 638, 639, 640, 641, 642, 643, 644
217	210, 273, 342, 343, 345, 493, 673, 675, 767, 838, 839, 840, 841, 887
218	181
219	469, 470, 471, 472, 473, 474, 477
220	56, 646
221	57
222	58
223	59

C-10 Fragment/Announcement Cross-Reference

Fragment	System Announcements That Use The Fragment
224	6, 7, 11, 12, 14, 20, 29, 31, 32, 38, 51, 53, 54, 55, 56, 60, 63, 64, 65, 66, 87, 98, 116, 117, 132, 171, 172, 193, 194, 195, 196, 199, 201, 213, 214, 216, 234, 238, 317, 349, 354, 359, 431, 443, 444, 466, 478, 484, 497, 498, 499, 500, 509, 511, 514, 559, 586, 592, 612, 613, 621, 627, 646, 770, 771, 773, 774, 782, 819, 835, 889, 890, 891, 894, 912, 932, 933, 936, 937
225	45, 67, 521, 724, 725, 726, 861, 940, 941
226	455, 658, 659, 660, 661, 662
227	456, 674
228	688
229	689
230	689
231	
232	611, 691, 692, 883
233	11, 12
234	192
235	5, 9, 10, 19, 20, 24, 25, 26, 28, 30, 32, 38, 39, 40, 41, 42, 43, 44, 45, 48, 50, 51, 57, 58, 59, 61, 62, 63, 64, 65, 66, 67, 78, 79, 80, 82, 83, 85, 93, 94, 95, 98, 100, 107, 108, 123, 126, 128, 168, 169, 170, 724, 726
236	191, 265, 712, 834, 877
237	613, 835
238	200
239	282
240	501
241	463, 472, 482, 483
242	680, 681, 682, 683, 684, 685, 686, 687
243	364, 526, 733
244	706
245	708, 709
246	210
247	211
248	713
249	713

Fragment	System Announcements That Use The Fragment
250	714
251	770, 771, 773, 774
252	206
253	819
254	93, 94
255	530
256	606, 699
257	727
258	838, 839
259	736, 737
260	637, 638, 639, 640, 641, 642, 643, 644, 738, 739, 740, 741, 742, 743, 744, 896, 897
261	637, 638, 639, 640, 641, 642, 643, 644
262	269, 270, 271, 272, 286, 287, 295, 296, 355, 356, 357, 358, 489, 490, 491, 492, 505, 506, 658, 659, 660, 661, 663, 664, 665, 666, 668, 669, 670, 671, 676, 677, 678, 679, 745, 476, 808, 809, 810, 811, 884, 885
263	878, 880
264	637, 744
265	637, 638
266	
267	359, 613, 835
268	
269	
270	753, 754
271	
272	258, 593
273	
274	70, 103, 298, 712, 762, 763, 945, 953
275	766
276	765
277	147, 152, 826, 934, 935

C-12 Fragment/Announcement Cross-Reference

Fragment	System Announcements That Use The Fragment
278	53, 60, 87, 627, 782
279	95, 107, 807, 853, 854
280	95, 107
281	808, 809, 810, 811, 884
282	5, 9, 10, 13, 19, 20, 24, 25, 26, 28, 30, 32, 38, 39, 40, 41, 42, 43, 44, 45, 48, 50, 51, 57, 58, 59, 62, 63, 64, 65, 66, 67, 76, 77, 78, 79, 80, 82, 83, 85, 93, 94, 95, 96, 97, 98, 99, 100, 101, 105, 106, 107, 108, 113, 114, 115, 116, 117, 119, 120, 121, 123, 125, 126, 127, 128, 129, 159, 168, 169, 170, 171, 172, 724, 726, 932, 933, 935, 937, 938, 940, 941, 942, 943, 960
283	814
284	814
285	6, 19, 912
286	7, 20
287	815
288	147, 934
289	
290	171, 172, 936, 937
291	4, 8, 15, 18, 68, 69, 70, 71, 77, 113, 114, 115, 121, 125, 127, 129, 920, 921, 938, 939, 940, 941, 942, 947, 949, 951, 952, 953, 955, 956, 957, 958, 961
292	24, 26, 34, 40, 41, 42, 44, 47, 49, 68, 72, 73, 74, 81, 86, 96, 101, 118, 122, 124, 880, 881, 925, 926, 927, 928, 929, 930, 943
293	817
294	179, 40
295	468, 477
296	34, 501
297	55, 66
298	54, 65
299	26, 50
300	904
301	904

Fragment	System Announcements That Use The Fragment
302	30
303	32
304	68, 101, 880, 881, 943, 961
305	76, 77, 113, 114, 115, 119, 120, 121, 125, 127, 129, 159
306	10,14,16,51
307	57,93,854
308	58,94,853
309	59,95
310	3
311	
312	
313	
314	
315	
316	
317	
318	
319	
320	
321	
322	152, 935
323	62, 85, 123, 126, 128, 168, 169, 170
324	78
325	137
326	83
327	19, 20, 45
328	6, 7, 19, 20, 912
329	45, 67, 861
330	12, 87
331	790

C-14 Fragment/Announcement Cross-Reference

Fragment	System Announcements That Use The Fragment
332	380, 381, 383, 383, 384, 385, 386, 387, 388, 389, 390, 391, 392, 393, 792, 793, 794, 795, 796, 797, 798, 799, 800, 801, 802, 803, 804, 805, 806
333	44, 913
334	212
335	194, 196, 218, 222, 771, 774
336	211
337	
338	93, 94
339	24, 26, 34, 47, 72, 73, 74, 86, 96, 118, 122, 124, 880, 881, 924, 925, 926, 927, 928, 929
340	84
341	33
342	541, 542, 545, 546, 549, 550, 553, 554
343	539, 540, 541, 542, 543, 544, 545, 546, 555
344	543, 544, 545, 546, 551, 552, 553, 554
345	184, 185, 190, 236
346	879, 881
347	29, 31, 54, 55
348	63, 64, 65, 66, 67
349	463, 472, 482, 483, 654, 655
350	3
351	
352	
353	
354	
355	
356	
357	61, 939
358	39
359	43
360	41

Fragment	System Announcements That Use The Fragment
361	41
362	54, 55, 65, 66
363	29, 31, 63, 64
364	54, 65
365	55, 66
366	29, 63
367	31, 64
368	38
369	38
370	40, 44
371	40, 42, 44
372	40, 44, 157, 228
373	25
374	82
375	72, 926
376	72, 73, 91, 84, 124
377	72, 73, 86, 118, 122, 124, 924, 925, 926, 927, 928, 929
378	73, 81, 86, 928, 929, 930
379	81, 930
380	69, 71, 102, 104, 299, 775, 813, 944, 946, 951, 952
381	86, 928
382	33, 84
383	266, 862, 863
384	90, 92, 161, 162, 261
385	75
386	520
387	641, 642, 742
388	192, 206, 276, 315, 346, 507, 508, 530, 730, 747, 924, 926, 928, 929, 930
389	192, 206, 276, 326, 507, 527, 892, 893, 907
390	820, 843, 903

C-16 **Fragment/Announcement Cross-Reference**

Fragment	System Announcements That Use The Fragment
391	844
392	845
393	846
394	847
395	848
396	849
397	850
398	851
399	852
400	972
401	
402	
403	
404	
405	
406	
407	
408	
409	
410	
411	
412	
413	
414	
415	
416	
417	
418	
419	

Fragment	System Announcements That Use The Fragment
420	
421	
422	
423	
424	
425	
426	
427	
428	
429	
430	
431	
432	
433	
434	
435	
436	
437	
438	
439	
440	
441	
442	
443	
444	
445	
446	
447	
448	

C-18 Fragment/Announcement Cross-Reference

Fragment	System Announcements That Use The Fragment
449	
450	820
451	
452	
453	
454	901
455	906
456	906
457	
458	
459	
460	
461	
462	
463	823
464	213, 217, 218, 219, 654
465	214, 221, 222, 223, 655
466	735
467	
468	488, 749
469	497, 499, 890
470	498, 500, 891
471	497, 498, 499, 500, 890, 891
472	326, 749
473	682
474	73, 346, 507, 929
475	
476	
477	717, 963

Fragment	System Announcements That Use The Fragment
478	718, 964
479	719, 965
480	720, 966
481	721, 967
482	724, 725, 726, 827, 940, 941
483	724, 725, 726, 827, 940, 941
484	45,67,521,861
485	455, 456
486	62, 85, 126, 168, 204, 693, 760, 768
487	33
488	84
489	
490	
491	124, 924
492	448
493	116, 117, 171, 172, 932, 933, 936, 937
494	457
495	458
496	532
497	34, 68, 101, 812, 880, 881, 943, 961
498	466, 889
499	750
500	627
501	723
502	24, 96, 246
503	24, 96
504	252
505	248
506	247
507	282, 297, 298

C-20 Fragment/Announcement Cross-Reference

Fragment	System Announcements That Use The Fragment
508	253
509	601
510	614,615,886
511	299, 712
512	772
513	279
514	712
515	104, 71, 775, 946, 951
516	102, 69, 944, 952
517	69, 70, 71, 102, 103, 104, 944, 945, 946, 951, 952, 953
518	68, 101, 943, 961
519	628
520	629, 630, 631, 632, 633
521	618, 619, 630, 631, 632, 633
522	617, 629
523	630, 631, 632, 633
524	22, 237, 625, 626, 631, 633, 656, 657, 758
525	624, 630, 632
526	624, 625, 626, 630, 631, 632, 633
527	28, 97,108, 307, 629, 630, 631, 632, 633
528	28, 97, 108, 307, 629, 630, 631, 632, 633
529	28, 97, 108
530	617, 618, 619
531	621
532	620
533	764
534	623
535	80, 106, 616
536	79, 80, 105, 106
537	734

Fragment	System Announcements That Use The Fragment
538	325
539	758
540	237
541	781
542	781
543	53, 627
544	624, 625, 626
545	79, 105
546	825
547	197, 872
548	582
549	48, 99
550	24, 96
551	53, 627
552	334, 335, 336
553	335
554	
555	15, 17, 18, 101, 102, 103, 104
556	621
557	620, 927
558	
559	570
560	620
561	6, 7, 912
562	116, 117, 193, 194, 195, 196, 894, 932, 933
563	116, 117, 193, 194, 195, 196, 932, 933
564	
565	309
566	53
567	53
568	

C-22 Fragment/Announcement Cross-Reference

Fragment	System Announcements That Use The Fragment
569	697
570	512, 883
571	610
572	
573	
574	
575	590
576	
577	72, 118, 122, 124, 924, 925, 926
578	924, 925, 926, 927, 928, 929, 930
579	443, 444
580	250, 251
581	251
582	514
583	
584	643, 644, 743
585	873
586	42, 180
587	42
588	514
589	622
590	622
591	52
592	199
593	199,514
594	
595	
596	
597	
598	
599	

Fragment	System Announcements That Use The Fragment
600	557
601	183, 184, 190, 235, 875
602	210, 236, 273, 342, 343, 344, 345, 493, 673, 675, 767, 838, 839, 840, 841
603	538, 540, 541, 543, 545, 547, 549, 551, 553, 555
604	690
605	
606	241
607	650
608	167 ,599, 692, 883
609	583
610	150
611	151
612	149, 519
613	518
614	515
615	516
616	
617	705, 919
618	704
619	700
620	701
621	866
622	876
623	275
624	495
625	208, 209, 831, 833
626	143, 146, 209, 731, 732, 831, 832, 833
627	239, 832, 833
628	146, 311, 832
629	716
630	303

C-24 Fragment/Announcement Cross-Reference

Fragment	System Announcements That Use The Fragment
631	227, 536
632	227, 333
633	517
634	240, 732
635	702
636	564
637	438, 439, 440
638	440
639	260
640	256
641	257
642	259
643	149
644	155
645	145, 149
646	144
647	842
648	156
649	135
650	139
651	164
652	140
653	274
654	134
655	141
656	494
657	133
658	831
659	130, 146, 209, 831
660	160, 161

Fragment	System Announcements That Use The Fragment
661	143, 160, 163
662	146
663	110
664	112
665	138
666	148
667	
668	111
669	109
670	142, 143
671	143, 162, 163
672	
673	
674	729, 931
675	
676	
677	
678	439
679	182, 293
680	177, 288
681	647
682	269, 270, 271, 272
683	268
684	355, 356, 357, 358
685	676, 677, 678, 679
686	663, 664, 665, 666
687	779
688	778

C-26 Fragment/Announcement Cross-Reference

Fragment	System Announcements That Use The Fragment
689	270, 272, 356, 358, 490, 492, 638, 640, 642, 644, 664, 666, 669, 671, 677, 679, 737, 746, 809, 811
690	668, 669, 670, 671
691	489, 490, 491, 492
692	
693	273
694	675
695	767
696	841, 887
697	493
698	673
699	739
700	165, 166, 755, 756
701	165, 166, 755, 756
702	166, 756
703	165, 166
704	503
705	320
706	136, 319
707	74, 525
708	215, 216, 330, 331
709	234
710	331, 860
711	224, 225, 226, 228, 229, 917
712	224, 225, 226, 228, 917
713	330
714	587
715	360, 361
716	231, 232

Fragment	System Announcements That Use The Fragment
717	233
718	653
719	652
720	651
721	
722	188, 361
723	136
724	321
725	131, 132
726	157
727	232, 327, 328, 329
728	189, 225
729	158
730	738
731	
732	
733	
734	
735	
736	167
737	434
738	740
739	342
740	343
741	344
742	840
743	345
744	230

C-28 Fragment/Announcement Cross-Reference

Fragment	System Announcements That Use The Fragment
745	1, 230, 278, 339, 350, 351, 352, 353, 411, 412, 413, 414, 415, 416, 417, 418, 419, 420, 421, 422, 423, 424, 433, 579, 645
746	
747	433
748	339
749	278
750	579
751	645
752	425
753	35,36, 428
754	88, 89, 91, 230, 278, 339, 350, 351, 352, 353, 365, 366, 367, 368, 369, 370, 371, 372, 373, 374, 375, 376, 377, 378, 379, 380, 381, 382, 383, 384, 385, 386, 387, 388, 389, 390, 391, 392, 393, 394, 395, 396, 397, 398, 399, 400, 401, 402, 403, 404, 405, 406, 407, 408, 409, 410, 411, 412, 413, 414, 415, 416, 417, 418, 419, 420, 421, 422, 423, 424, 433, 579, 645, 830
755	395
756	74, 426, 427, 525
757	429, 430
758	74, 430, 525
759	430
760	74, 426, 427, 525
761	
762	303
763	
764	91, 787, 788, 828
765	396
766	88, 783
767	89, 785, 786, 829
768	394
769	591

Fragment	System Announcements That Use The Fragment
770	397, 398, 399, 400, 401, 402, 403, 404, 405, 406, 407, 408, 409, 410
771	365, 366, 367, 368, 369, 370, 371, 372, 373, 374, 375, 376, 377, 378
772	426
773	828, 829
774	143, 160, 161, 162, 163, 341
775	121, 728
776	1, 230, 278, 339, 350, 351, 352, 353, 433, 579, 645
777	522
778	523
779	596
780	524
781	74, 525
782	789
783	784
784	784, 789
785	23, 710, 711
786	23, 711
787	23, 711
788	432, 657
789	22, 657
790	244, 245
791	242, 243
792	242, 244
793	243,245
794	300
795	304
796	703
797	791
798	22, 656, 657
799	132, 216

C-30 Fragment/Announcement Cross-Reference

Fragment	System Announcements That Use The Fragment
800	161, 162
801	314
802	707
803	
804	
805	352, 353
806	
807	350,351
808	
809	
810	352, 353, 372, 375, 387, 390, 404, 407, 418, 421, 800, 803
811	
812	350, 351, 366, 369, 381, 384, 398, 401, 412, 415, 794, 797
813	351, 353, 367, 369, 370, 373, 375, 376, 382, 384, 385, 388, 390, 391, 399, 401, 402, 405, 407, 408, 413, 415, 416, 419, 421, 422, 795, 797, 798, 801, 803, 804
814	350, 351, 352, 353, 366, 367, 368, 369, 370, 371, 372, 373, 374, 375, 376, 377, 378, 381, 382, 383, 384, 385, 386, 387, 388, 389, 390, 391, 392, 393, 398, 399, 400, 401, 402, 403, 404, 405, 406, 407, 408, 409, 410, 412, 413, 414, 415, 416, 417, 418, 419, 420, 421, 422, 423, 424, 794, 795, 796, 797, 798, 799, 800, 801, 802, 803, 804, 805, 806
815	46
816	35
817	36
818	88, 89, 91, 830
819	74
820	37
821	21, 22, 23
822	174
823	1, 365, 380, 397, 411, 793
824	

Fragment	System Announcements That Use The Fragment
825	372, 373, 374, 375, 387, 388, 389, 390, 404, 405, 406, 407, 418, 419, 420, 421, 800, 801, 802, 803
826	370, 371, 385, 386, 402, 403, 416, 417, 798, 799
827	366, 367, 368, 369, 381, 382, 383, 384, 398, 399, 400, 401, 412, 413, 414, 415, 794, 795, 796, 797
828	376, 377, 391, 392, 408, 409, 422, 423, 804, 805
829	378, 393, 410, 424, 806
830	560
831	161, 162
832	131, 215, 859
833	131, 132, 327, 328, 895
834	
835	618, 630, 631
836	619, 632, 633
837	634
838	153
839	74
840	636
841	337, 636
842	565
843	254, 837
844	529
845	558
846	837
847	118, 927
848	122 ,925
849	118, 122
850	563
851	527, 925, 927
852	157

C-32 Fragment/Announcement Cross-Reference

Fragment	System Announcements That Use The Fragment
853	962
854	882
855	894, 895
856	892, 893
857	
858	907
859	909
860	910
861	884, 885, 886, 887, 915, 931
862	896
863	897
864	898
865	899
866	911
867	895
868	895,912
869	912
870	
871	
872	
873	
874	
875	
876	
877	
878	
879	
880	
881	
882	
883	

Fragment/Announcement Cross-Reference C-33

Fragment	System Announcements That Use The Fragment
884	
885	
886	
887	
888	
889	
890	
891	
892	
893	
894	
895	
896	
897	
898	
899	
900	855
901	856
902	857
903	
904	
905	
906	
907	
908	
909	858
910	92, 305, 306, 859, 860, 861, 863
911	301, 305
912	302, 306
913	35, 36, 88, 131, 132, 136, 319, 327, 328, 329, 429, 430, 783, 784, 786, 788, 789, 791, 828, 829

C-34 Fragment/Announcement Cross-Reference

Fragment	System Announcements That Use The Fragment
914	864
915	865
916	154
917	277
918	667
919	672
920	748
921	868
922	869
923	870
924	873, 972
925	873
926	871
927	
928	556
929	635
930	207
931	313
932	347
933	776
934	777
935	780
936	2
937	872
938	905
939	
940	
941	
942	
943	
944	

Fragment/Announcement Cross-Reference C-35

Fragment	System Announcements That Use The Fragment
945	
946	
947	
948	
949	
950	
951	
952	
953	
954	
955	
956	
957	
958	
959	
960	
961	
962	
963	
964	
965	
966	
967	
968	
969	867
970	476
971	340, 341, 919
972	921, 956
973	285, 920, 921, 955, 956
974	922
975	923

C-36 **Fragment/Announcement Cross-Reference**

Fragment	System Announcements That Use The Fragment
976	
977	752
978	886
979	878, 880
980	878, 880
981	974
982	
983	76, 127
984	77, 114, 120
985	119, 125, 129
986	115, 121, 159
987	171, 172, 936, 937