



AT&T 585-305-531
Issue 1
November 1993
Comcode 107095663

AUDIX®
Announcement Customization
R1V2 through R1V7

**Copyright © 1995 AT&T
All Rights Reserved
Printed in U.S.A.**

Notice

While reasonable efforts were made to ensure that the information in this document was complete and accurate at the time of printing, AT&T can assume no responsibility for any errors. Changes and corrections to the information contained in this document may be incorporated into future reissues.

Your Responsibility for Your System's Security

You are responsible for the security of your system. AT&T does not warrant that this product is immune from or will prevent unauthorized use of common-carrier telecommunication services or facilities accessed through or connected to it. AT&T will not be responsible for any charges that result from such unauthorized use. Product administration to prevent unauthorized use is your responsibility and your system administrator should read all documents provided with this product to fully understand the features available that may reduce your risk of incurring charges.

Federal Communications Commission Statement

Part 15: Class A Statement. This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio-frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference, in which case the user will be required to correct the interference at his or her own expense.

Part 68: Network Registration Number. This equipment is registered with the FCC in accordance with Part 68 of the FCC Rules. It is identified by FCC registration number AS593M-14695-MA-E.

Trademarks

AUDIX is a registered trademark of AT&T.

Ordering Information

The ordering number for this document is 585-305-531. To order this document, call the GBCS Publications Fulfillment Center at 1-800-457-1235 (International callers use 1-317-361-5353). For more information about AT&T documents, refer to the *Global Business Communications Systems Publications Catalog* (555-000-010).

Comments

To comment on this document, return the comment card at the front of the document.

Acknowledgment

This document was prepared by the AT&T Product Documentation Development Department, Denver, CO 80234-2703.

Contents

About This Document	v
INTENDED AUDIENCE	v
HOW THIS DOCUMENT IS ORGANIZED	v
HOW TO USE THIS DOCUMENT	vi
CONVENTIONS USED IN THIS DOCUMENT	vi
RELATED RESOURCES	vii
HOW TO MAKE COMMENTS ABOUT THIS DOCUMENT	vii
1. Overview	1-1
ANNOUNCEMENT SETS	1-1
Announcements and Fragments	1-1
Active and Administrative Announcement Sets	1-2
ANNOUNCEMENT CUSTOMIZATION PROCESS	1-3
2. Announcement Customization Procedures	2-1
ANNOUNCEMENT CUSTOMIZATION PROCEDURES	2-1
To Re-record a Fragment	2-1
To Delete a Fragment from an Announcement	2-4
To Add a Fragment to an Announcement	2-5
RESTORING CUSTOMIZED ANNOUNCEMENTS AFTER AN UPGRADE	2-7
A. System Announcements	A-1


B. Abbreviated (Terse) Fragments	B-1
C. Verbose System Fragments	C-1
D. Fragment/Announcement Cross-Reference	D-1
Index	IN-1

About This Document

This document describes how to customize system announcements (prompts and messages) on an AT&T AUDIX Voice Messaging System. Because the system announcements changed in the R1V8 release of AUDIX software, this document should *only* be used for AUDIX systems that are running Release 1 Version 2 (R1V2), R1V3, R1V4, R1V5, R1V6, or R1V7 software.

INTENDED AUDIENCE

This document is intended for system administrators who need to customize (modify or re-record) AUDIX announcements on an AUDIX system that is running R1V7 or earlier software.



Because one AUDIX fragment (spoken word or phrase) may affect many system announcements, it is strongly recommended that system administrators obtain training or consult their AT&T representative prior to changing any system announcements (customers may be charged for this service).

HOW THIS DOCUMENT IS ORGANIZED

This document is organized as follows:

- Chapter 1, *Overview*, describes the role of announcements and fragments in creating AUDIX system prompts and messages.
- Chapter 2, *Announcement Customization Procedures*, details the steps for re-recording, changing, or deleting AUDIX system announcements and fragments. Procedures for restoring your customized announcements following an upgrade to R1V7 (or earlier) software are also included.
- Appendix A, *System Announcements*, lists the AUDIX system announcements and the fragments that compose them.
- Appendix B, *Abbreviated Fragments*, lists the abbreviated (terse) version of AUDIX announcement fragments.
- Appendix C, *Verbose Fragments*, lists the verbose (long) version of AUDIX announcement fragments.
- Appendix D, *Fragment/Announcement Cross-Reference*, lists the fragments for both the abbreviated and verbose announcement sets and lists the system announcements that use them.

An index appears at the end of this document.

HOW TO USE THIS DOCUMENT

Read the overview, then follow the steps in Chapter 2 to customize the system announcements and/or fragments you wish. This document is intended to be used in conjunction with the appropriate administration and forms reference manual for your system (see the *Related Resources* section).

CONVENTIONS USED IN THIS DOCUMENT

The following typographic conventions are used in this document:

- Information that appears on your terminal screen (including displays, field names, prompts, and error messages) is shown in constant-width type. Information that you are to type just as it appears in the document is shown in constant-width bold type. For example:

At the `when?` prompt, type **`now`**

- Terminal keys that you are to press are shown in boxes. For example, an instruction to press the return, carriage return, or equivalent key might appear in this document as:

Press `RETURN`.

- Two or three keys that you are to press at the same time (that is, you are to hold down the first key while pressing the second key and, if appropriate, the third key as well) are enclosed together, separated by hyphens, in a curved-edge box. For example, an instruction to press and hold the `ALT` key while typing the letter *d* appears in this document as:

Press `ALT-d`.

- Variables for which you or the system substitute a word specific to your own application are shown in italic type. For example, an error message that appears on the screen with the name of your own specific filename might appear generically in this document as:

Your file *filename* is formatted incorrectly.

RELATED RESOURCES

This document should be used in conjunction with the appropriate administration and forms reference manuals for your system. Because this document is intended to support customers whose AUDIX system may be running R1V2, R1V3, R1V4, R1V5, R1V6, or R1V7 software, please use the document intended to support the version of software your AUDIX system is running:

- *AUDIX Administration (585-305-501)* — supports AUDIX R1V5, R1V6, and R1V7 systems
- *AUDIX Administration (585-304-501)* — supports AUDIX R1V4 systems
- *AUDIX Administration (585-302-501)* — supports AUDIX R1V2 and R1V3 systems
- *AUDIX Release 1 Version 7 Forms Reference (585-305-208)*
- *AUDIX Release 1 Version 6 Forms Reference (585-305-204)*
- *AUDIX Release 1 Version 5 Forms Reference (585-305-202)*
- *AUDIX Release 1 Version 4 Forms Reference (585-304-202)*

HOW TO MAKE COMMENTS ABOUT THIS DOCUMENT

While we have tried to make this document fit your needs, we are interested in your suggestions for improving it. If the reader comment card has been removed from this document, please send your comments to:

AT&T
Product Documentation Development Department
11900 North Pecos Street
Room 22-2C11
Denver, Colorado 80234

1. Overview

AUDIX system *announcements* are the voiced (spoken) prompts and messages that the AUDIX system plays for subscribers, callers, and administrators who access the AUDIX system. Announcements are made of up one or more *fragments*. A fragment is a piece of voice text consisting of an individually recorded word, phrase, or sentence.

This chapter describes how the AUDIX system combines fragments to make system announcements, and gathers the announcements into different *announcement sets* (filesystems) that may be altered by the system administrator.

ANNOUNCEMENT SETS

An *announcement set* is a filesystem that contains all the announcements (prompts and other system messages) that may be encountered by the user. Two versions of the AUDIX system announcement sets were available prior to R1V8:

- *Abbreviated* — The “terse” version of system announcements. This was the default announcement set shipped with R1V2 through R1V7 systems. It was typically named `disk00.ana` on a new system or `ana.adat` on a generic cartridge.
- *Verbose* — The “long” version of system announcements. This announcement set was optionally available for R1V2 through R1V7 systems. It was typically named `disk00.anp` on a new system or `anp.adat` on a generic cartridge.

The abbreviated announcement set contains the same announcements as the verbose version, but individual announcements use fewer words to convey the same message. For example, announcement a258 accesses fragment 30. The verbose version of this fragment is, “*To change this message before it’s delivered, press one.*” The abbreviated version is simply, “*To change, press one.*”

Announcements and Fragments

Each system announcement is identified by a number and contains up to nine system fragments consisting of a word, phrase, or sentence. Fragments are also identified by number. A single fragment or several fragments can be used to compose an announcement. Announcements determine the number and order of fragments as they will be encountered by the user.

For example, refer to Appendix A, *System Announcements*. It indicates that system announcement number 10 is composed of fragments 16 and 224. If you look these fragment numbers up in Appendix C, *Verbose System Fragments*, you find that fragment number 16 is the phrase, “*Please enter announcement ID*”, and fragment number 224 is, “*followed by the pound sign*”. If you look up the same fragment numbers in Appendix B, *Abbreviated (Terse) Fragments*, you find that fragment number 16 has been shortened to,

“*Enter announcement ID*”, and fragment number 224 is, “*and pound sign*”.

Appendix D, *Fragment/Announcement Cross-Reference*, shows all the announcements in which a given fragment is used. Changing a fragment in one announcement could cause an unintentional change in another announcement if you aren't careful. Announcements, fragments, and their identifying numbers are listed and cross-referenced in Appendixes A through D.



If you decide to change your system announcements, you must be extremely careful and precise. If you make a mistake, the resulting announcements could be erroneous, and straightening out mistakes can be frustrating and time-consuming. It is strongly recommended that you do not attempt to modify any announcements without the help of your AT&T representative (you may be charged for this service).

Active and Administrative Announcement Sets

Only one announcement set can be active (accessible to users) at a time. The `system : announcement : filesystems` form shows the name of the *active* announcement set. The *active* designation means that this is the announcement set that will be heard by anyone who accesses the AUDIX system.

The `system : announcement : filesystems` form also shows whether an *administrative* announcement set has been defined. The *administrative* announcement set is the “working” version used to make changes. When the changes are complete, the administrator switches (*swaps*) the administrative announcement set with the currently active announcement set in order to hear the changes. When the administrator is satisfied with the changes, he or she copies the changes from the updated, active version to the previously active (now the new administrative) version. This last step ensures the system has two identical copies of the customized system announcements.

ANNOUNCEMENT CUSTOMIZATION PROCESS

How you customize announcements depends on the announcement and the global implication of changing its fragments:

- If the fragment or fragments you want to change are not used by any other announcement or only by announcements that you also want changed, you can simply re-record the fragments to be whatever you want using your touch-tone telephone.
- If the fragment or fragments you want to change are used by other announcements that you do *not* want to change, you can create and record new fragments to associate with just those announcements you want changed.

Either of these methods requires care, because fragments may be used by more than one system announcement. Study the tables in the appendixes before attempting to change system fragments, and use the `system : announcement : detail` form to verify which fragments make up a specific announcement before making changes.

You *cannot* make changes to the active announcement set in AUDIX R1 software; use the administrative copy to make changes. When you are satisfied with your changes (the customized announcements play correctly), you then make the administrative version the new active version so that users will hear the customized set of announcements. You should limit the number of administrative copies you create because keeping track of them may become confusing.

If you have more than one hard disk in your system, you may create the administrative filesystem on a different disk than the one containing the active announcements filesystem. Refer to the filesystem distribution guidelines in the *AUDIX System Description* manual (585-302-201) to determine the best drive on which to make your working copy (refer to Chapter 3, *AUDIX Software*). You may also back up either the active or administrative filesystem onto a removable cartridge disk if desired.

NOTE

If you plan to make extensive changes to the announcement sets, you may wish to create a backup copy, either on a hard disk or on a removable cartridge, *before* you begin modifying announcements.

2. Announcement Customization Procedures

The chapter describes the procedures for customizing system announcements. If you have already customized announcements and are upgrading to a version prior to R1V8 (for example, if you have already purchased an upgrade to an R1V7 software load), you can copy your customized announcements to the new announcement sets as described at the end of this chapter.

ANNOUNCEMENT CUSTOMIZATION PROCEDURES

You can customize system announcements in the following ways:

- Re-record a fragment
- Delete a fragment
- Add a fragment

These procedures are described in this section.



If you decide to change a fragment recording or an announcement's composition, you must be extremely careful and precise. Failure to do so could jeopardize the integrity of your system. It is recommended that you do not attempt to modify any system announcements or fragments without the help of your AT&T representative (you may be charged for this service).

To Re-record a Fragment

The two announcements you will most likely want to change when you customize your AUDIX system are the default Call Answer greeting (the greeting someone hears when they are redirected to a subscriber's AUDIX mailbox) and the default Voice Mail greeting (the greeting subscribers hears when they call the AUDIX system directly). These announcement and fragment numbers are listed below.

- *Default Call Answer Greeting:* When someone calls a subscriber who is unavailable and the call is redirected to the AUDIX system, the caller hears the subscriber's personal greeting if one has been recorded. However, if a personal greeting was not recorded or is not active, the caller hears the default system greeting. This greeting begins with announcement 36, which contains only fragment number 43, "Your call is being answered by AUDIX". To customize this announcement (for example, with your company name), you would just re-record fragment number 43.
- *Default Voice Mail Greeting:* When a subscriber calls the AUDIX system directly, the subscriber is greeted by fragment number 287, *Welcome to AUDIX*, and fragment number 97, *For help at any time, press *H*. To customize this announcement (for example, with your company name), you would just

re-record fragment number 287.

The procedure for re-recording a fragment is the same for any announcement, as described below:

1. Using Appendix B or Appendix C (depending on whether you have activated the abbreviated or verbose version of system announcements), note the fragment number(s) you want to change.
2. Using Appendix A and Appendix D, verify that the fragments are used only by announcements you expect to be affected by your changes. If too many announcements would be affected by changing a fragment, for example, you may wish to record a *new* custom fragment instead of re-recording one (see the following *To Add a Fragment to an Announcement* section).
3. Log on to the AUDIX administration terminal.

NOTE

For details on any of the following procedures, refer to the appropriate forms reference manual for your system (see the *Related Resources* section in the preface).

4. Use the `system : announcement : filesystems` form to determine if an administrative announcement version is mounted (available for use). If so, the name of the filesystem (such as `disk02.ans`) will be displayed in the `admin announcements` field. You can only make changes to an administrative (working) version of an announcement set.

If an active administrative announcement version is mounted *and* it is the version you want to change, go to the next step. If not, do the following:

- a. If the administrative version shown on the form is not the version you want to make changes to, but you know the name of the existing filesystem that you do want to modify, type the name of the correct administrative filesystem in the `admin announcements` field and press **F1** (CHANGE or RUN).
- b. If no administrative announcement set appears on the form, use the `filesystem : list` form to determine if an administrative version exists. If you find one (it may be on a different disk if your system has more than one hard disk drive), go back to the `system : announcement : filesystems` form and type the name of the administrative filesystem in the `admin announcements` field. Press **F1** (CHANGE or RUN).
- c. If an administrative version does not exist, use the `filesystem : detail` form to create a new filesystem that will contain the administrative version of your customized announcements. Go back to the `system : announcement : filesystems` form and type the name of the filesystem you just created in the `admin announcements` field. Press **F1** (CHANGE or RUN).

For any of these steps, to ensure that the administrative version is identical to the active version before you make announcement changes, copy the active version to the administrative version using the `copy announcements (active to admin)` field; type an **x** in the field and press **F1** (CHANGE or RUN).

When you are sure that the correct administrative version is mounted, go to the next step.

5. Use the `system : announcement : detail` form to verify that the announcement you plan to change is actually composed of the fragments you expect.
 - a. Move the cursor to the `filesystem` name field and type the name of the announcement filesystem to be accessed (in this case, the administrative version).
 - b. Move the cursor to the `announcement` field and type the number of the announcement containing the fragment(s) you wish to change. Press `(F8)` (ENTER).
 - c. Compare the list of fragments shown in the `composition` field with the notes you made from Steps 1 and 2. If there is a discrepancy, trust the information on the screen. (For example, a fragment may have been added to an announcement after the publication of this document.)

You should now have all the information you need to determine the impact of changing the fragment(s) in your target announcement.

6. Use the `subscriber : local` form to confirm that you have permission to access the system announcements (a `y` should appear in the `announcement control` field of your subscriber profile).
7. Using your touch-tone phone, log in to the AUDIX system.
8. At the activity menu, press `(9)`. (For security purposes, this option is not included in the voiced options you hear.) If you hear *“Entry not understood. Try again,”* you do not have announcement control permission.
9. When you hear *“To record names, press 4. To play names, press 5,”* press `(1)` to change fragments. (For security purposes, this option is not included in the voiced options you hear.)
10. Enter the fragment ID as prompted. For example, to change the default Call Answer greeting, you would press `(4)(3)(#)`.
11. Record the new fragment when prompted.

For example, your new fragment might be *“This is XYZ Company.”* You can use all the normal voice mail editing capabilities on your touch-tone phone to make sure the new fragment is exactly how you want it to sound.

12. When you are satisfied with the new fragment recording, press `(*)(#)` to approve it.

For example, if you re-recorded the default Call Answer greeting, instead of saying, *“Your call is being answered by AUDIX,”* the system now says (in the administrator’s voice), *“This is XYZ Company.”*
13. At this point, only the administrative announcement version has this version of the re-recorded fragment. To update the currently active announcement set, go to the `system : announcement : filesystems` form and swap the active and administrative announcement versions.
14. The announcement filesystem you modified is now the active announcement version. When you have tested it to your satisfaction, use the `system : announcement : filesystems` form again to copy the contents of the active version (your modified copy) to the administrative version (the version that was previously active) so that both versions are once again identical.

To Delete a Fragment from an Announcement

Some announcements can be modified by simply eliminating (deleting) an existing fragment from that specific announcement. For example, you could modify the default voice mail greeting (“*Welcome to AUDIX. For help at any time, press *H*”) to just say “*For help at any time, press *H*” by removing fragment number 287 (“*Welcome to AUDIX*”) from the list of fragments that compose the announcement (in this case, announcement number 240).

To delete a fragment from an announcement:

1. Using Appendix A, note the number of the announcement you want to change.
2. Use Step 4 in the previous section to make sure the correct administrative announcement filesystem is mounted on the `system : announcement : filesystems` form.
3. Use the `system : announcement : detail` form to eliminate (delete) the fragment from the target announcement as follows:
 - a. Move the cursor to the `filesystem name` field and type the name of the administrative filesystem.
 - b. Move the cursor to the `announcement` field type the announcement number, in this case **240**.
 - c. Press **F8** (ENTER) to display and verify the fragment composition of the announcement. In this example, the fragment composition is `287,97`.
 - d. Change the composition line by spacing over or deleting the characters for the unwanted fragment(s). For example, delete the characters `287,.` Press **F1** (CHANGE or RUN).

Announcement number 240 is now composed of fragment number 97 only. Future callers will hear only the phrase, “*For help at any time, press *H*”.

4. At this point, only the administrative announcement version has this change to the announcement. To update the currently active announcement set, go to the `system : announcement : filesystems` form and swap the active and administrative announcement versions.
5. The announcement filesystem you modified is now the active announcement version. When you have tested it to your satisfaction, use the `system : announcement : filesystems` form again to copy the contents of the active version (your modified copy) to the administrative version (the version that was previously active) so that both versions are once again identical.

To Add a Fragment to an Announcement

The previous examples dealt with modifications where the fragments being changed were not used by other announcements or where the fragment itself was left intact but was eliminated from just specific announcements. If you need to change the content of a fragment for some announcements but not others, you need to either substitute an existing fragment or create a new fragment for use by the announcements you want to change and leave the old fragment intact for use by existing announcements that you do not want changed. Be very careful if you do this.

For example, announcement number 61 and announcement number 78 are the only announcements that use fragment number 87, *“This call is experiencing difficulties.”* If you want to change this fragment for announcement number 61 but *not* for announcement number 78, you could create a new fragment to associate with announcement number 61 instead of fragment number 87; this would leave fragment number 87 and its association with announcement number 78 intact.

To add a fragment to an announcement:

1. Using Appendix A and Appendix D, verify that the announcement(s) you intend to change use only the fragments you expect.
2. Using Appendix B or Appendix C (depending on whether you have activated the abbreviated or verbose version of system announcements), locate an unused fragment number (unused fragments are followed by a blank line instead of text). Fragment numbers up to 999 may be used (even though the tables stop at number 872).

Generally, using the highest numbered fragment available minimizes the chance that future software will reference that same fragment number. For example, start with fragment number 999 and work your way backwards. Write down your customized fragments in one of the appendixes in order to keep a written record of your changes.

3. Follow Steps 3 through 9 in the *To Re-record a Fragment* section.
4. When the AUDIX system prompts you to enter the fragment ID, enter an unused number. For example, you might press .
5. Record the new fragment when prompted.

For example, your new fragment might be *“This call is experiencing difficulties and cannot continue at this time.”* You can use all the normal voice mail editing capabilities on your touch-tone phone to make sure the new fragment is exactly how you want it to sound.

6. When you are satisfied with the new fragment recording, press to approve it.
7. Use the `system : announcement : detail` form to add the new fragment to the appropriate announcement.
 - a. Move the cursor to the `filesystem` name field and type the name of the administrative filesystem.
 - b. Move the cursor to the `announcement` field type the announcement number, in this case **61**.
 - c. Press (ENTER) to display the fragment composition of the announcement. In this example, the fragment composition is:

— 87: This call is experiencing difficulties.

- 236: Try again
- 109: later.
- 95: Please disconnect.

- d. Rewrite the line to reflect the new composition (in this case **999, 236, 109, 95**) and press **F1** (CHANGE or RUN).

Announcement number 61 is now composed of the following fragments:

- 999: This call is experiencing difficulties and cannot continue at this time.
- 236: Try again
- 109: later.
- 95: Please disconnect.

Meanwhile, announcement number 78 still uses fragment number 87 as before.

8. At this point, only the administrative announcement version has this new version of the announcement and the new fragment. To update the currently active announcement set, go to the `system : announcement : filesystems` form and swap the active and administrative announcement versions.
9. The announcement filesystem you modified is now the active announcement version. When you have tested it to your satisfaction, use the `system : announcement : filesystems` form again to copy the contents of the active version (your modified copy) to the administrative version (the version that was previously active) so that both versions are once again identical.

NOTE

Alternatively in this example, you could have created a new fragment number 999 with just the phrase “*and cannot continue at this time*” to use *in addition to* fragment number 87 instead of replacing it in announcement number 61. Either way, be careful if you make changes to announcements and fragments and be sure you have thoroughly researched the global ramifications of changes that you plan to make before you actually make them. Be sure to test your changes before copying them to the old (previously active) announcement set, because this will destroy the original version.

RESTORING CUSTOMIZED ANNOUNCEMENTS AFTER AN UPGRADE

If you have already purchased an upgrade to R1V7 (or earlier) software, you can use the following procedure to restore your customized announcements.

NOTE

The announcement set changed in AUDIX R1V8 software. Customers should refer to the appropriate announcement customization guide for R1V8 before copying over any customized announcements or fragments to make sure the customized items will not have an adverse impact on the new announcement set.

During the software upgrade, the upgrade utility saved your customized announcements to a temporary file. After the upgrade is complete, you can restore your customized announcements using the following procedure:

1. Look up your customized announcements and/or fragments in the cross-referenced appendixes in this document. Verify that the customized items affect only those fragments and/or announcements that you expect, and that the wording and context of the customized announcements are similar between the new announcement set and the previous version.

NOTE

Because the default Call Answer and Voice Mail greetings are so often customized, fragment 43 (the default Call Answer greeting) and fragment 287 (the default Voice Mail greeting) are always the same from release to release. If these are the only fragments you customized, you can copy your customized version into the new announcement set without any adverse effect.

2. Go to the `system : announcement : filesystems` form by typing `sy an f` on the path line. Press `RETURN`.
 - a. Type the name of the temporary filesystem in the `admin` field. (For example, `disk00.temp`.) Press `F1` (CHANGE or RUN).
 - b. Tab to `swap active` and `admin announcements` field and type `x`. Press `F1` (CHANGE or RUN).
 - c. Press `CTRL-z` to exit the form.
3. Go to the `system : announcement : detail` form by typing `sy an de` on the path line. Press `RETURN`.
 - a. Type the name of the administrative announcement filesystem in the `filesystem name` field. The filesystem is typically named `disk00.ana` for abbreviated announcements and `disk00.anp` for verbose announcements.
 - b. Tab to the `fragment` field and type the first customized fragment number.
 - c. Tab to the `copy from filesystem` field and type the name of the active announcements filesystem. (Use the same name you used in Step 1a, for example, `disk00.temp`.)
 - d. Tab to the `copy from fragment` field and type the same fragment number.
 - e. Press `F1` (CHANGE or RUN).

- f. Repeat this procedure for each customized fragment number.
 - g. When you are finished, press **CTRL-z** to exit the form.
4. Go to the `system : announcement : filesystems` form by typing **sy an f** on the path line. Press **RETURN**.
 - a. Tab to `swap active` and `admin announcements` field and type **x**.
 - b. Blank out the `admin` field, then press **F1** (CHANGE or RUN).
 - c. Press **CTRL-z** to exit the form.
5. Go to `filesystem : detail` form by typing **f d** on the path line. Press **RETURN**.
 - a. In the `filesystem` field, type the name of the temporary announcement filesystem. (Use the same name as in Step 1a, for example, **disk00.temp**.)
 - b. Type **adat** in the `type` field.
 - c. Press **F3** (DELETE) to delete the filesystem.
 - d. Press **CTRL-z** to exit the form.

A. System Announcements

This appendix lists the fragments that compose each AUDIX system announcement. Generally, the abbreviated (terse) and verbose announcements are composed of the same fragments. Any exceptions are noted in the text.

Announcement	System Fragments That Compose The Announcement
1	57
2	73
3	246
4	336, 247
5	334
6	160
7	18, 8
8	2
9	15
10	16, 224
11	131
12	
13	88
14	272, 95
15	29
16	31, 384
17	32
18	498, 224
19	35
20	41, 126, 8
21	486, 8
22	40, 383
23	20
24	21, 389, 388
25	8
26	91
27	
28	323, 41, 126, 8, 235, 282
29	323, 486, 8, 235, 282
30	51
31	Verbose: 52, 76 Abbreviated: 76

Announcement	System Fragments That Compose The Announcement
32	164
33	44
34	42
35	56, 46
36	43
37	60
38	61
39	
40	65
41	66
42	
43	12
44	Verbose: 156, 56 Abbreviated: 156
45	72
46	76
47	59
48	74
49	77
50	98
51	140
52	323, 8, 235, 282
53	79
54	252, 389, 388
55	342
56	145
57	83
58	85, 13
59	472, 389
60	86
61	87, 236, 109, 95
62	197

Announcement	System Fragments That Compose The Announcement
63	197, 142
64	89, 197, 142
65	90, 224
66	485
67	92
68	491, 376, 577, 339, 292, 377, 235, 282
69	232, 181
70	94
71	99
72	Verbose: 243, 568 Abbreviated: 243
73	101
74	103, 224
75	579
76	44, 112
77	104
78	87, 497
79	106
80	563, 224, 115
81	82
82	110
83	111, 224
84	49
85	113
86	154
87	155
88	563, 224, 117, 115
89	118, 224, 175
90	128, 129
91	335
92	122

Announcement	System Fragments That Compose The Announcement
93	123
94	121
95	144, 130
96	3
97	120
98	132
99	277
100	139
101	288, 277, 105, 80
102	322, 277, 105, 80
103	141
104	
105	231
106	124, 133
107	116, 133
108	114, 224
109	116, 349, 241
110	134
111	124, 349, 241
112	121
113	
114	144
115	107
116	100, 151
117	14
118	343
119	158, 236, 109, 95
120	563, 119, 224, 115, 105, 282
121	153
122	156, 157

Announcement	System Fragments That Compose The Announcement
123	344
124	136
125	
126	159
127	150
128	Verbose: 243, 160 Abbreviated: 243
129	161
130	168
131	149
132	165, 21, 255, 388
133	166
134	167
135	
136	170
137	171
138	63
139	172
140	201
141	105, 67, 111, 224
142	105, 238
143	181, 95
144	53
145	181
146	Verbose: 203, 204, 62 Abbreviated: 203, 62
147	Verbose: 203, 205, 62 Abbreviated: 203, 62
148	Verbose: 203, 206, 62 Abbreviated: 203, 62
149	215, 62
150	207
151	177
152	180

Announcement	System Fragments That Compose The Announcement
153	178
154	181
155	186
156	182
157	183
158	184, 13
159	169
160	185
161	127, 96
162	
163	188, 224
164	189, 272
165	190
166	191
167	192
168	194
169	195
170	196
171	199
172	200, 22
173	389, 388
174	202
175	208
176	209
177	6, 224
178	173, 224
179	213, 224
180	468
181	10
182	64

Announcement	System Fragments That Compose The Announcement
183	217
184	11, 6, 224, 235, 282
185	218
186	219
187	220, 224
188	
189	226
190	227
191	242
192	228
193	230
194	236
195	19
196	142, 143
197	142
198	146, 143
199	1
200	146
201	486, 18, 8
202	234, 389, 388
203	256
204	570
205	
206	244, 142
207	
208	98
209	387
210	
211	245
212	248
213	249

Announcement	System Fragments That Compose The Announcement
214	250
215	22
216	253, 224
217	138, 6, 224, 235, 282
218	
219	
220	294
221	23
222	Verbose
223	21, 24, 388
224	270
226	26
227	Verbose: 273, 96, 80, 274 Abbreviated: 96, 80, 274
228	275, 95
229	7
230	68
231	69
232	70
233	278, 224
234	279, 280
235	345
236	283
237	284
238	276
239	
240	287, 97
241	179
242	
243	
244	

Announcement	System Fragments That Compose The Announcement
245	
246	
247	
248	293
249	34
250	
251	499
252	389, 388
253	388
254	33, 388
255	37, 187, 464, 135, 349
256	38, 187, 465, 135, 349
257	474, 389, 388
258	30, 24, 388
259	386
260	300
261	301
262	387
263	
264	
265	
266	
267	
268	
269	
270	310
271	311
272	312
273	313
274	314
275	315

Announcement	System Fragments That Compose The Announcement
276	316
277	317
278	318
279	319
280	320
281	321
282	258
283	259
284	260
285	261
286	
287	262
288	
289	264
290	265
291	Verbose: 266
292	466
293	
294	
295	
296	
297	
298	
299	
300	
301	5
302	50
303	78
304	281
305	54

Announcement	System Fragments That Compose The Announcement
306	55
307	216
308	216, 260
309	214
310	93
311	331
312	332
313	257
314	45
315	102
316	267, 224
317	Verbose: 268, 267, 224, 237 Abbreviated: 267, 224, 237
318	193
319	Verbose: 269, 267, 224, 237 Abbreviated: 267, 224, 237
320	152
321	
322	176, 224
323	477
324	478
325	479
326	480
327	481
328	482
329	483, 225
330	484, 225
331	
332	
333	
334	
335	
336	

Announcement	System Fragments That Compose The Announcement
337	
338	
339	
340	25, 498, 224
341	125, 111, 224
342	464, 135
343	465, 135
344	37, 469, 224, 471
345	38, 470, 224, 471
346	469, 224, 471
347	470, 224, 471
348	229
349	240, 296
350	75
351	494
352	495
353	147
354	492
355	295
356	198
357	Verbose: 469, 239, 224, 471 Abbreviated: 468, 224, 471
358	Verbose: 470, 239, 224, 471 Abbreviated: 470, 224, 471
359	496
360	350
361	351
362	352
363	353
364	354
365	355
366	356
367	18

Announcement	System Fragments That Compose The Announcement
368	Verbose: 476 Abbreviated: 258
369	89
370	
371	
372	
373	
374	
375	
376	
377	
378	
379	
380	
381	
382	
383	
384	
385	
386	
387	
388	
389	
390	390
391	391
392	392
393	393
394	394
395	395
396	396
397	397
398	398

Announcement	System Fragments That Compose The Announcement
399	399
400	400
401	401
402	402
403	403
404	404
405	405
406	406
407	407
408	408
409	409
410	410
411	411
412	412
413	413
414	414
415	415
416	416
417	417
418	418
419	419
420	420
421	421
422	
423	
424	
425	
426	
427	
428	
429	

Announcement	System Fragments That Compose The Announcement
430	430
431	431
432	432
433	433
434	434
435	435
436	436
437	437
438	438
439	439
440	440
441	441
442	442
443	443
444	444
445	445
446	446
447	447
448	448
449	449
450	450
451	451
452	452
453	453
454	454
455	455
456	456
457	457
458	458
459	459
460	460

Announcement	System Fragments That Compose The Announcement
461	461
462	462
463	463
464	234
465	
466	27
467	475
468	473
469	474, 388
470	
471	472, 468
472	47
473	
474	
475	
476	
477	
478	
479	
480	
481	
482	
483	
484	
485	
486	
487	
488	
489	
490	
491	

Announcement	System Fragments That Compose The Announcement
492	
493	
494	
495	
496	
497	
498	
499	
500	299, 5, 39, 339, 292, 235, 282
501	263, 13
502	299, 36, 235, 282
503	346, 13
504	Verbose: 302, 225, 235, 282 Abbreviated: 302, 235, 282
505	71
506	303, 224, 235, 282
507	263, 13, 304, 339, 292, 497
508	108, 13, 304, 339, 292, 497
509	346, 13, 304, 339, 292, 497
510	108, 13, 339, 292
511	380
512	305, 23, 48, 282
513	13
514	
515	486, 18, 8, 163
516	278, 224, 330
517	323, 486, 41, 126, 8, 163, 235, 282
518	278, 224
519	18, 8, 163
520	233, 224, 330
521	323, 41, 126, 8, 163, 235, 282
522	486, 8, 163

Announcement	System Fragments That Compose The Announcement
523	233, 224
524	323, 486, 8, 163, 235, 282
525	220, 224
526	8, 163
527	370, 333, 371, 292, 372, 235, 282
528	323, 8, 163, 235, 282
529	118, 224, 175, 117, 251
530	306, 210, 224, 235, 282
531	118, 224, 251
532	306, 212, 235, 282
533	235, 282
534	Verbose: 308, 279, 280, 235, 282 Abbreviated: 308, 254, 338, 235, 282
535	
536	Verbose: 308, 222, 225, 235, 282 Abbreviated: 308, 222, 235, 282
537	46, 117, 291
538	Verbose: 307, 279, 280, 235, 282 Abbreviated: 307, 254, 338, 235, 282
539	45, 112
540	Verbose: 307, 221, 225, 235, 282 Abbreviated: 307, 221, 235, 282
541	
542	
543	46, 291
544	309, 223, 224, 235, 282
545	563, 119, 224, 115, 105, 117, 282
546	323, 486, 41, 126, 8, 235, 282
547	493, 118, 119, 224, 290, 105, 282
548	375, 376, 577, 339, 292, 377, 235, 282
549	493, 118, 119, 224, 290, 105, 117, 282
550	378, 376, 292, 379, 235, 282
551	128
552	378, 381, 376, 339, 292, 377, 235, 282
553	

Announcement	System Fragments That Compose The Announcement
554	
555	
556	
557	
558	
559	
560	Verbose: 382, 488, 383 Abbreviated: 382, 488, 340
561	
562	Verbose: 382, 384, 487 Abbreviated: 382, 341, 487
563	
564	
565	
566	385
567	
568	324, 235, 282
569	
570	
571	
572	326, 235, 282
573	
574	327, 285, 224, 328, 58, 235, 282
575	561, 285, 224, 328, 58
576	347, 111, 224, 366, 363
577	
578	359, 235, 282
579	
580	360, 292, 361, 235, 282
581	
582	368, 224, 369, 224, 235, 282
583	
584	370, 294, 371, 292, 372, 235, 282

Announcement	System Fragments That Compose The Announcement
585	
586	46
587	
588	358, 14, 235, 282
589	
590	374, 235, 282
591	
592	373, 235, 282
593	
594	378, 474, 376, 339, 292, 377, 235, 282
595	
596	327, 286, 224, 328, 148, 235, 282
597	561, 286, 224, 328, 148
598	347, 362, 364, 224, 298
599	
600	347, 362, 365, 224, 297
601	
602	357, 235, 80
603	
604	Verbose: 483, 225, 328, 148, 235, 282 Abbreviated: 483, 225, 235, 282
605	
606	Verbose: 327, 329, 484, 225, 328, 148, 235, 282 Abbreviated: 327 329, 484, 225, 235, 282
607	
608	347, 111, 224, 367, 363
609	
610	348, 362, 364, 224, 298, 235, 282
611	
612	348, 362, 365, 224, 297, 235, 282
613	
614	348, 111, 224, 366, 363, 235, 282

Announcement	System Fragments That Compose The Announcement
615	
616	348, 111, 224, 367, 363, 235, 282
617	
618	348, 329, 484, 225, 148, 235, 282
619	
620	
621	
622	
623	
624	
625	
626	
627	
628	
629	
630	
631	
632	
633	
634	
635	
636	
637	
638	
639	
640	
641	
642	
643	
644	

Announcement	System Fragments That Compose The Announcement
645	
646	
647	
648	
649	
650	
651	
652	
653	
654	
655	
656	
657	
658	
659	
660	
661	
662	
663	
664	
665	
666	
667	
668	
669	
670	
671	
672	
673	
674	
675	

Announcement	System Fragments That Compose The Announcement
676	
677	
678	
679	
680	
681	
682	
683	
684	
685	
686	
687	
688	
689	
690	
691	
692	
693	
694	
695	
696	
697	
698	
699	
700	501
701	305, 501, 48, 291, 282
702	502
703	503, 502, 550, 339, 292, 235, 282
704	503, 502, 550, 339, 292, 105, 282
705	504
706	505

Announcement	System Fragments That Compose The Announcement
707	506
708	547
709	Verbose: 43, 507, 224 Abbreviated: 43, 507, 239
710	559
711	510
712	511, 236, 109, 514, 274
713	274
714	507
715	515
716	512
717	513
718	516
719	500
720	519
721	520
722	521
723	522
724	523
725	524
726	525
727	526
728	527
729	528
730	530
731	533
732	534
733	531, 224
734	532, 557, 560
735	535
736	536, 535, 235, 117, 282

Announcement	System Fragments That Compose The Announcement
737	536, 545, 235, 117, 282
738	508, 95
739	537
740	538
741	509
742	539
743	540
744	541
745	542
746	517, 46, 117, 291, 80
747	518, 13, 304, 292, 497, 46, 117, 291, 80
748	529, 527, 528, 235, 282
749	517, 555, 80
750	518, 13, 304, 292, 497, 572, 555, 282
751	529, 527, 528, 105, 282
752	546
753	536, 535, 105, 282
754	536, 545, 105, 282
755	100
756	172, 168, 551, 278, 224, 543
757	95
758	549, 235, 282
759	549, 105, 282
760	548
761	556
762	552
763	553
764	589, 590
765	511, 380
766	544

Announcement	System Fragments That Compose The Announcement
767	Verbose: 558
768	562
769	493, 562
770	564, 236, 109
771	565
772	566, 551, 278, 224, 543, 567
773	569
774	571
775	235, 117, 282
776	572
777	
778	574
779	575
780	576
781	580
782	211
783	306, 210, 224, 80
784	306, 212, 80
785	581
786	582
787	81
788	591, 235, 282
789	584
790	585
791	586
792	587, 586, 371, 292, 235, 282
793	588
794	592
795	593
796	
797	

Announcement	System Fragments That Compose The Announcement
798	
799	
800	600
801	601
802	602
803	603
804	604
805	
806	606
807	607
808	608
809	609
810	610
811	611
812	612
813	613
814	614
815	615
816	616
817	617
818	618
819	619
820	620
821	621
822	622
823	623
824	624
825	625
826	626
827	627

Announcement	System Fragments That Compose The Announcement
828	628
829	629
830	630
831	631
832	632
833	633
834	634
835	635
836	636
837	637
838	638
839	639
840	640
841	641
842	642
843	643
844	644
845	645
846	646
847	647
848	648
849	649
850	650
851	651
852	652
853	653
854	654
855	855
856	656
857	657

Announcement	System Fragments That Compose The Announcement
858	658
859	659
860	660
861	661
862	662
863	663
864	664
865	665
866	666
867	667
868	668
869	669
870	670
871	671
872	464, 224, 572
873	465, 224, 572
874	674
875	
876	
877	
878	678
879	679
880	680
881	681
882	682
883	683
884	684
885	685
886	686
887	687

Announcement	System Fragments That Compose The Announcement
888	688
889	689
890	690
891	691
892	692
893	693
894	694
895	695
896	696
897	697
898	698
899	699
900	700
901	701
902	702
903	703
904	704
905	705
906	706
907	707
908	708
909	709
910	710
911	711
912	712
913	713
914	714
915	715
916	716
917	717

Announcement	System Fragments That Compose The Announcement
918	718
919	719
920	720
921	721
922	722
923	723
924	724
925	725
926	726, 372, 852
927	727
928	728
929	729
930	730
931	232
932	305, 23, 48, 291, 282
933	305, 731, 48, 282
934	305, 731, 48, 291, 282
935	105, 282
936	305, 23, 48, 291, 117, 282
937	736
938	555, 117, 291, 80
939	555, 80
940	555, 291, 80
941	
942	
943	734
944	735
945	
946	737
947	738

Announcement	System Fragments That Compose The Announcement
948	739
949	740
950	741
951	742
952	743
953	744
954	745
955	
956	747
957	748
958	749
959	750
960	751
961	752
962	753
963	754
964	755
965	756
966	757
967	758
968	759
969	760
970	
971	762
972	
973	764
974	765
975	766
976	767
977	768

Announcement	System Fragments That Compose The Announcement
978	769
979	770
980	771
981	772
982	773
983	774
984	775
985	776
986	777
987	778
988	779
989	780
990	781
991	782
992	783
993	784
994	785
995	786
996	787
997	788
998	789
999	790
1000	791
1001	792
1002	793
1003	794
1004	795
1005	796
1006	797
1007	798
1008	799, 224

Announcement	System Fragments That Compose The Announcement
1009	800
1010	384
1011	215
1012	801
1013	802
1014	
1015	804
1016	805
1017	806
1018	807
1019	808
1020	809
1021	810
1022	811
1023	812
1024	813
1025	814
1026	815
1027	816
1028	817
1029	818
1030	819
1031	820
1032	821
1033	
1034	325
1035	822
1036	339, 292
1037	823
1038	305, 501, 48, 282
1039	825

Announcement	System Fragments That Compose The Announcement
1040	826
1041	827
1042	828
1043	829
1044	830
1045	831
1046	372
1047	832
1048	224
1049	305, 731, 48, 291, 117, 282
1050	305, 501, 48, 291, 117, 282
1051	305, 775, 48, 282
1052	305, 775, 48, 291, 282
1053	305, 775, 48, 291, 117, 282
1054	833, 58
1055	833, 148
1056	835
1057	836
1058	529, 527, 528, 235, 117, 282
1059	837
1060	838
1061	839
1062	840
1063	841
1064	842, 95
1065	843
1066	844
1067	845
1068	846, 843
1069	847, 849, 577, 339, 292, 377, 235, 282

Announcement	System Fragments That Compose The Announcement
1070	848, 849, 577, 339, 292, 377, 235, 282
1071	850
1072	165, 21, 389, 851
1073	333
1074	853
1075	854
1076	856
1077	861
1078	562, 855, 224
1079	867, 855, 868, 833
1080	862
1081	863
1082	864
1083	865
1084	857
1085	21, 594
1086	858, 389
1087	76, 95
1088	21, 389, 80
1089	859
1090	860
1091	866
1092	561, 285, 224, 869, 868, 328, 58
1100	870
1101	871
1102	872

B. Abbreviated (Terse) Fragments

This appendix lists the fragments (pieces of voice text) that compose the *abbreviated* (or “terse”) set of AUDIX system announcements.

B-2 Abbreviated (Terse) Fragments

Fragment	Abbreviated Fragment Text
1	Someone is changing your greeting, please try again later.
2	and
3	No new remote subscribers can be addressed.
4	at end.
5	To record personal greeting, press one. To listen to personal greeting, press zero. To select which greeting to use, press star pound.
6	Enter machine voice ID.
7	Cannot listen to an undeliverable message.
8	To record a new message, press four.
9	You may now record new messages.
10	That is not a valid machine voice ID.
11	You are recording machine names.
12	To re-record, press one. After recording, press one again. To delete, press star D. To playback, press two three. To approve as is, press star pound.
13	To record, press one. After recording, press one again.
14	To make private, press one. To make public, press two.
15	and is
16	Enter announcement ID
17	at beginning.
18	To forward with comment, press two.
19	To review from beginning, press star one. If finished, press star pound.
20	Remote extension
21	To listen, press zero.
22	To deliver now, press star pound. To schedule delivery time enter hour, minutes, A or P, and pound sign.
23	To record messages, press one. To get messages, press two. To administer your greeting, press three.
24	To delete, press star D.
25	List-id not followed by pound.
26	To record names, press four. To play names, press five. To record machine names, press six. To play machine names, press seven.
27	To attach original, press Y for yes or N for no.
28	Returned to incoming messages.

Fragment	Abbreviated Fragment Text
29	Returned to checking status of outgoing messages.
30	To change, press one.
31	Date not understood.
32	You must enter your extension to log on.
33	To delete, press star D.
34	Electronic Text
35	Login incorrect.
36	To record a personal greeting, press one.
37	Extension entered not followed by pound
38	Name entered not followed by pound
39	To delete, press star D. To stop playback, press three.
40	Time not understood.
41	To forward message with comment at beginning, press two.
42	Can only reply to messages from other subscribers.
43	Your call is being answered by AUDIX.
44	is not available. To leave a message, wait for the tone.
45	is busy. To leave a message, wait for the tone.
46	To access your mailbox, press star R.
47	Call Answering message from
48	To check your outgoing messages, press four. To administer other personal options, press five. To change outcalling information, press six. To automatically scan incoming messages, press seven. To re-logon, press star star R.
49	No operator defined.
50	Call answering message
51	Entries deleted, please re-enter delivery time.
52	
53	Message deleted, no delivery will occur.
54	was only partially recorded due to a system problem.
55	The message was delivered at
56	Thank you for leaving your message.
57	accessed
58	For name addressing, press star A.

B-4 Abbreviated (Terse) Fragments

Fragment	Abbreviated Fragment Text
59	delivered
60	Changed.
61	To modify status, press Y for yes or N for no.
62	Please delete unneeded messages.
63	new
64	old
65	contains
66	If correct, press star pound. If not, press star D and re-enter time.
67	To create another list,
68	undeliverable
69	undelivered
70	unopened
71	To leave a message, wait for the tone.
72	defaulted to
73	You have
74	deleted.
75	To skip, press pound. To delete, press star D.
76	Deleted.
77	Deleted.
78	delivered at
79	Deleted.
80	To have system wait, press star W. If finished, please hang up, or to disconnect AUDIX press star star X.
81	digits.
82	Please leave a message for
83	entries.
84	entry.
85	Erased.
86	extension
87	This call is experiencing difficulties.
88	Cannot use the guest password

Fragment	Abbreviated Fragment Text
89	First message.
90	Enter fragment ID
91	At end.
92	Nothing to advance.
93	You have no personal greeting, system greeting used.
94	Good-bye.
95	Please disconnect.
96	For help, press star H.
97	For help at any time, press star H.
98	Message not delivered due to transmission problems.
99	Invalid announcement.
100	Entry not understood.
101	Invalid fragment.
102	That is not a valid extension.
103	Invalid version, re-enter number
104	Message delivered, cannot listen to a delivered message.
105	To restart at the activity menu, press star R.
106	Last list.
107	Last member of list.
108	You are recording a message.
109	later.
110	list
111	Please enter list ID
112	Otherwise, for assistance, press zero now.
113	You already have a list
114	To replace list, re-enter ID and pound sign. To create a new list, enter new list ID
115	To transfer using names instead, press star A.
116	List is full.
117	To reach the covering extension, press star zero.
118	Enter name

B-6 Abbreviated (Terse) Fragments

Fragment	Abbreviated Fragment Text
119	you wish to call
120	too large to include.
121	When finished, approve list by pressing star pound.
122	List space nearly full. You may enter
123	new members.
124	No more list space.
125	Must be six or less numerals.
126	To forward message with comment at end, press three.
127	Returned to previous activity.
128	To request another transfer, press star T.
129	or leave a message for
130	because there were no entries.
131	To send to others not on your list,
132	You can store your list as is by pressing star pound, or add up to
133	To continue reviewing, press three. To delete an entry, press star D. If finished reviewing, press star pound.
134	You can store your list or delete members, but you cannot add members.
135	and pound sign.
136	Line busy.
137	or approve entire list by pressing star pound.
138	You are listening to machine names.
139	additional members,
140	Entry already deleted. To delete more entries, press star one.
141	No more lists.
142	To play, press three.
143	To step back again, press two.
144	deleted,
145	List has no entries.
146	To continue, press pound.
147	Review complete.
148	For extension addressing, press star A.

Fragment	Abbreviated Fragment Text
149	All circuits busy.
150	members.
151	Try again after the tone.
152	Leave Word Calling from
153	Maximum length recorded. To re-record, press two one. To approve as is, press star pound.
154	Cannot create new list, you have maximum lists allowed. To select lists to be deleted, press five one two and follow instructions.
155	Cannot create new list, total number of members in all of your lists equals maximum allowed.
156	Maximum length recorded.
157	To approve as is, press star pound.
158	Transfer cannot be completed.
159	member.
160	message
161	midnight.
162	To record personal greeting, press one. To listen to personal greeting, press zero. To select which greeting to us press star pound.
163	To call sender, press zero.
164	category.
165	Returned to getting messages.
166	At end. To playback, press two three.
167	To approve, press star pound. To record from here, press one. To playback, press two three.
168	messages.
169	Admin version not specified, please do so using administrator's terminal.
170	Delivery scheduled
171	message summary.
172	You have new
173	Please enter new password
174	
175	Please note, only AUDIX subscribers can be specified by name.
176	Enter fragment ID

B-8 Abbreviated (Terse) Fragments

Fragment	Abbreviated Fragment Text
177	Cannot listen to a delivered message.
178	No addressees identified.
179	Warning, if you do not supply an addressee list, message will be deleted immediately.
180	Nothing to approve.
181	Nothing to approve.
182	Nothing to delete.
183	Nothing to delete.
184	Nothing to erase.
185	not found.
186	To record messages, press one. To get messages, press two. To check your outgoing messages, press four.
187	and not added to the list.
188	Passwords do not match. Please re-enter new password.
189	You have no mailbox.
190	Message delivered, you cannot change it now.
191	No more messages.
192	No messages.
193	No name recorded.
194	No new messages.
195	No messages.
196	You have no personal greeting.
197	Cannot step back.
198	Partial name deleted.
199	Nothing to rewind.
200	No time entered, nothing to delete.
201	noon.
202	not valid.
203	No room in your mailbox for a recording.
204	another message.
205	your response.
206	comment.

Fragment	Abbreviated Fragment Text
207	Message too long to add comment. To record a new message, press star R one.
208	is not a public list.
209	Cannot modify another subscriber's list.
210	Please enter a new password.
211	to fifteen digits
212	Please enter password again for confirmation. To delete previously entered password, press star D.
213	Re-enter password
214	Approved.
215	No room to retain a copy.
216	originally
217	others
218	deleted.
219	owned by
220	Enter password
221	Enter announcement ID and pound sign. Refer to the admin manual for correct ID.
222	Enter fragment ID and pound sign. Refer to admin manual for correct ID.
223	Please enter extension
224	and pound sign.
225	
226	private
227	public
228	Record at the tone.
229	You will have up to
230	seconds to record.
231	cannot be found.
232	Recording stopped.
233	Previous login incorrect. Please re-enter extension.
234	To respond or forward, press one.
235	To restart at the activity menu, press star R. To transfer to another extension, press star T.
236	Try again

B-10 Abbreviated (Terse) Fragments

Fragment	Abbreviated Fragment Text
237	Or press star R.
238	To review another list,
239	Followed by the pound sign.
240	To skip, press pound. To listen, press zero.
241	To review list, press star one.
242	Returned to the
243	Rewound.
244	Rewound to previous message.
245	Please return call.
246	Message addressed to
247	To add to list,
248	scheduled
249	To change delivery time, press star D. To approve, press star pound.
250	To change delivery time, press star D.
251	To transfer using extension instead, press star A.
252	To respond to this message, press one.
253	Please enter month, day
254	To play the active version, press one.
255	To delete this message, press star D.
256	at beginning. To re-record, press one. To playback, press two three.
257	To use personal greeting, press Y. To use system greeting, press N.
258	Message to
259	scheduled for
260	scheduled for
261	rescheduled for
262	delivered
263	You are recording a subscriber name.
264	Message not delivered because mailbox was full.
265	Messages not delivered because their mailboxes were full.
266	was undeliverable
267	Please enter extension

Fragment	Abbreviated Fragment Text
268	
269	
270	subscriber ID
271	
272	Contact administrator for help.
273	
274	Please make entry soon, or be disconnected.
275	Cannot get your messages now due to multiple logins to your mailbox.
276	Time requested has passed, please re-schedule delivery.
277	To exit directory, press star pound.
278	Please enter extension
279	For active version, press one.
280	For admin version, press two.
281	Message from
282	To have system wait, press star W. To access the names or numbers directory, press star star N. If finished, please hang up, or to disconnect AUDIX, press star star X.
283	Your mailbox is more than
284	percent full. Please delete unneeded messages or greetings.
285	To add a member, enter extension
286	To add a member, enter name
287	Welcome to AUDIX.
288	You are in the names directory. To find a subscriber's extension, enter the name followed by the pound sign. To look up by extension instead, press star A.
289	
290	If you wish to specify a non-AUDIX subscriber, first change to extension addressing by pressing star A.
291	To transfer to another extension, press star T.
292	Volume up, press four. Volume down, press seven. Speed up, press nine. Speed down, press eight.
293	Nothing to playback.
294	To add entries, press one.

B-12 Abbreviated (Terse) Fragments

Fragment	Abbreviated Fragment Text
295	To re-enter list, press star L.
296	To delete, press star D.
297	To specify owner by extension, press star A.
298	To specify owner by name, press star A.
299	You are administering your greeting.
300	A. M.
301	P. M.
302	You are recording announcement fragments. Enter fragment ID followed by pound sign. Refer to admin manual for correct ID.
303	You are recording names. Enter extension
304	To play back message, press two three. To delete your message, press star D. To approve your message, press star pound.
305	You are at the activity menu.
306	You are changing your password.
307	You are playing announcements.
308	You are playing announcement fragments.
309	You are playing names.
310	January
311	February
312	March
313	April
314	May
315	June
316	July
317	August
318	September
319	October
320	November
321	December
322	You are in the numbers directory. To find a subscriber's name, enter the extension followed by the pound sign. To look up by name instead, press star A.

Fragment	Abbreviated Fragment Text
323	You are responding to a piece of incoming mail.
324	You are selecting which greeting will be played to callers. If you want your personal greeting to be played, press Y for yes. To use the system greeting, press N for no.
325	You are administering your lists. To create a mailing list, press one. To play a summary of all your lists, press two. To review a particular list, press three.
326	You are doing system administration. To record names, press four. To play names, press five. To record a machine name, press six. To play a machine name, press seven. To record fragments, press one. To play fragments, press two. To play announcements, press three.
327	You are creating a mailing list.
328	To add an existing list, press star L. You may add lists you own, or public lists owned by others. To review your list from the beginning, press star one. To approve the list you are creating, press star pound. To delete the previous entry, press star D.
329	The entry made does not uniquely specify a subscriber.
330	Or enter just the pound sign if it's your phone.
331	Personal greeting used.
332	System greeting used.
333	To add entries to list or to change status of list, press one.
334	When finished addressing, press star pound.
335	When finished, press star pound.
336	To review addressees, press star one.
337	
338	To play the admin version, press two.
339	To replay the last few seconds, press five. To advance a few seconds, press six.
340	Please enter the time in the following format: First enter the hour, then two digits for the minutes, then A for A.M. or P for P.M., and then the pound sign.
341	Please enter the month and day in the following format. First enter the number of the month, then two digits for the day and then the pound sign.
342	Electronic Document Communication
343	Leave Word Calling
344	Message Center Service
345	Voice mail
346	You are recording a machine name.
347	You are adding a list.

Fragment	Abbreviated Fragment Text
348	You are specifying a mailing list to review.
349	To approve list as is, press star pound.
350	Sunday
351	Monday
352	Tuesday
353	Wednesday
354	Thursday
355	Friday
356	Saturday
357	You are choosing between subscribers whose names match your entry. To indicate no subscribers match, delete entry by pressing star D. To change to extension addressing and delete your entry, press star A.
358	You are identifying a list as private or public.
359	You are changing the status of your list. To modify status, press Y for yes or N for no.
360	You are scanning mailing lists. To review list members, press zero. To rewind to previous list, press two. To continue scanning lists, press three.
361	To skip to next list, press pound. To delete list, press star D.
362	If you own the list, press pound. If someone else owns the list
363	To approve the list you are creating, press star pound.
364	enter owner's extension
365	enter owner's name
366	To specify a different owner by extension, press star D.
367	To specify a different owner by name, press star D.
368	You are entering the number for a new list. Please enter a number up to six digits long.
369	To replace an existing list, enter that list's number,
370	These are entries in your list.
371	To rewind to current entry, press two. To rewind to previous entries, press two as many times as necessary. To continue playback of list, press three.
372	To skip to next entry, press pound. To delete current entry, press star D.
373	You are choosing whether to attach a copy of original message to your reply. To include the original, press Y for yes. To send only your reply, press N for no.

Fragment	Abbreviated Fragment Text
374	You are choosing whether to save this message in your file cabinet. To save a copy in file cabinet, press Y for yes. To send without saving a copy, press N for no.
375	You are getting your incoming messages. To listen to the message, press zero. To respond to the message, press one.
376	To skip to the next header, press the pound sign. To listen to the header, rewind by pressing two, then play by pressing three. To skip to the next category, press star pound.
377	To delete message, press star D.
378	You are checking the status of your outgoing messages.
379	To delete status information, press star D.
380	Please wait.
381	To listen to the message, press zero. To re-record message before delivery, press one.
382	You are scheduling your message for delivery.
383	Please enter hour, then two digits for minutes, then A for A.M or P for P.M., and pound sign.
384	Please enter number of month, then two digits for day, and pound sign.
385	To approve delivery time, press star pound. To modify delivery time, press star D and listen for further instructions.
386	Cannot change a delivered message.
387	Message not delivered because recipient not found.
388	To skip, press pound.
389	To delete, press star D.
390	oh
391	one
392	two
393	three
394	four
395	five
396	six
397	seven
398	eight
399	nine
400	ten

B-16 Abbreviated (Terse) Fragments

Fragment	Abbreviated Fragment Text
401	eleven
402	twelve
403	thirteen
404	fourteen
405	fifteen
406	sixteen
407	seventeen
408	eighteen
409	nineteen
410	twenty
411	thirty
412	forty
413	fifty
414	sixty
415	seventy
416	eighty
417	ninety
418	hundred
419	thousand
420	oh.
421	one.
422	two.
423	three.
424	four.
425	five.
426	six.
427	seven.
428	eight.
429	nine.
430	zeroth.

Fragment	Abbreviated Fragment Text
431	first.
432	second.
433	third.
434	fourth.
435	fifth.
436	sixth.
437	seventh.
438	eighth.
439	ninth.
440	tenth.
441	eleventh.
442	twelfth.
443	thirteenth.
444	fourteenth.
445	fifteenth.
446	sixteenth.
447	seventeenth.
448	eighteenth.
449	nineteenth.
450	twentieth.
451	thirtieth.
452	fortieth.
453	fiftieth.
454	sixtieth.
455	seventieth.
456	eightieth.
457	ninetieth.
458	hundredth.
459	thousandth.
460	millionth.
461	billionth.

B-18 Abbreviated (Terse) Fragments

Fragment	Abbreviated Fragment Text
462	pound
463	star
464	Enter extensions
465	Enter name
466	created
467	To begin recording, press one. After you finish recording, press one again.
468	To continue playing, press three.
469	Enter owner's extension
470	Enter owner's name
471	If it's your list, press pound.
472	To approve, press star pound. To record from here, press one.
473	file cabinet
474	To listen, press zero. To change or send again, press one.
475	To file a copy, press Y for yes or N for no.
476	Message sent to
477	Press one to select
478	two to select
479	three to select
480	four to select
481	five to select
482	Press pound to select
483	or enter more characters
484	Enter more characters
485	has
486	To reply to sender by voice mail, press one.
487	To delete time, press star D. To default rest of the delivery time, press star pound.
488	To specify immediate delivery, press star pound. Otherwise
489	Otherwise, enter more characters of the name starting from where you left off.
490	Please enter additional characters of the name, starting from where you left off,

Fragment	Abbreviated Fragment Text
491	You are getting your incoming messages. To listen to the message, press zero. To respond to the message, press one.
492	Owner erased.
493	You are requesting a transfer.
494	private.
495	public.
496	Filed.
497	To review your message, press star one.
498	Please enter a new list ID
499	After recording, press one.
500	This is AUDIX.
501	To record messages, press one. To get messages, press two. To administer attendant menu, press three.
502	To record attendant menu, press one. To listen to attendant menu, press zero.
503	You are administering your attendant menu.
504	Transferring to an operator,
505	You have selected an invalid option.
506	Menu approved and activated.
507	Using touch-tones, please enter the number of the person whom you are calling.
508	Attendant Service not available, try again later.
509	System not administered for outcalling.
510	Number
511	If you do not have a touch-tone phone,
512	Your call is being transferred to an operator.
513	Please speak first the name and number of the person whom you are calling followed by your message. It will be delivered to that person as soon as possible. Please be aware that in order to forward this message to the recipient, someone will listen to the name and number portion.
514	otherwise
515	To be transferred to an operator,
516	To leave a message that will be delivered as soon as possible,

Fragment	Abbreviated Fragment Text
517	You are entering the number of the person for whom you are leaving a message. This may be the complete number you dialed or simply the extension. For a faster response, terminate your entry with a pound sign.
518	You are creating a voice message which will be delivered to the person specified in your message as soon as possible. Please be aware that in order to forward this message to the recipient, someone will listen to the name and number portion.
519	You are not authorized for outcalling.
520	Your outcalling number,
521	turned on
522	turned off
523	for
524	to
525	any time
526	subject to administrator restrictions
527	To change number, press one. To change times, press two. For instructions on
528	To turn on, press Y. To turn off, press N.
529	You are changing your outcalling options.
530	Outcalling
531	Enter number
532	To change your outcalling phone number, press one and enter the number to be called followed by the pound sign. Anything you enter will be interpreted as a part of the called number. No global commands such as star H will be accepted at this time.
533	Too many digits.
534	Your outcalling number is
535	For outcalling any time, press one. For outcalling during prime time, press two. To specify your times, press three. For system outcalling schedule, press four.
536	You are specifying your outcalling time period. The time you specify will be restricted by the times allowed by the system administrator.
537	Enter the starting hour, minutes, A or P, and pound sign.
538	Enter the ending hour, minutes, A or P, and pound sign.
539	The system allows outcalls from
540	and from
541	Up to

Fragment	Abbreviated Fragment Text
542	digits may be used.
543	To avoid further notification of these messages, press star pound.
544	Outcalling specified for
545	To delete own time, press star D.
546	pause
547	Good-bye
548	You have no attendant menu.
549	You are administering your attendant menu. To create attendant menu, press one.
550	To rewind your attendant menu, press two. To delete it, press star D. To stop playback of your attendant menu, press three.
551	To access your messages,
552	is not authorized to receive messages.
553	You may enter another number
554	To access your mailbox, press star R. To transfer to another extension, press star T.
555	To access your mailbox, press star R.
556	To exit, press star pound now.
557	In most cases, entering a star or pound as the first digit will result in the star or pound being outpulsed. A star entered as part of the digit string will be interpreted as a pause of one and a half seconds. If a longer pause is required, use multiple stars in a row.
558	
559	No space to record a name. Increase size of the names filesystem.
560	If you are programming a number to call a pager that requires a pound sign termination, press Y to hear further help. Otherwise, press N to return to outcalling administration.
561	You are addressing your message.
562	Enter the
563	digit extension
564	There is no room in the mailbox to leave a message.
565	Outcall canceled for new messages currently in mailbox.
566	You are responding to an outcall notifying you of new messages.

Fragment	Abbreviated Fragment Text
567	Either logging in or pressing star pound will result in the outcall being canceled for the new messages currently in your mailbox. If additional new messages arrive, another outcall will be scheduled.
568	
569	To modify, press one. If finished, press star pound.
570	Recorded name too long
571	Non-existent subscriber
572	To access the options menu, press star M.
573	
574	Private
575	Cannot forward a private message
576	Recipients can forward this message
577	To hold the message in its current category, press star star H.
578	
579	Password must be
580	Cannot attach a private message
581	Press N now.
582	AUDIX passwords must now be at least
583	
584	Message not delivered because special feature denied on recipient's machine.
585	zero
586	To skip, press pound.
587	You are reviewing a list.
588	or more digits.
589	For pagers requiring a pound sign termination, start your number with a double pound sign. This will result in a single pound sign being outpulsed at the end of the digit string. Then, a star or pound in the next position will be interpreted as part of the outcalling number.
590	A star entered as part of the digit string will be interpreted as a pause of one and a half seconds. If a longer pause is desired, use multiple stars in a row.
591	To change your outcalling phone number, press one. To hear further instructions on programming a page, press Y. To return to outcalling administration, press N.
592	AUDIX passwords must now be

Fragment	Abbreviated Fragment Text
593	Please choose a new password of
594	To delete, press star D.
595	
596	
597	You are recording a subscriber name.
598	
599	
600	You have new broadcast messages.
601	Priority
602	other
603	You also have
604	As you use AUDIX, your name will be included in system announcements that you and other people will hear. Press one, and at the tone, please speak your name. After speaking your name, press one again.
605	
606	To re-record your name, press one. To approve, press star pound.
607	Name cannot be saved at this time, please continue
608	At the tone, please speak your name. After speaking your name, please press one.
609	No room to save broadcast message so it will be retained in the new message category.
610	You are recording your name. After you record your name, you can access other AUDIX features. As you use AUDIX, your name will be included in system announcements that you and other people will hear. Press one and at the tone, please speak your first and last name as your would like others to hear it. After speaking your name, press one again.
611	You are recording your name. To record your name, press one. After recording
612	To make private, press one.
613	To make priority, press two.
614	To make broadcast, press eight.
615	To make a login announcement, press nine.
616	To exit options menu, press star pound.
617	To remove private status, press one.
618	To remove priority status, press two.
619	To remove broadcast status, press eight.

B-24 Abbreviated (Terse) Fragments

Fragment	Abbreviated Fragment Text
620	To remove login announcement status, press nine.
621	Private
622	Priority
623	Broadcast.
624	Login announcement
625	To activate message waiting notification, press one.
626	To specify expiration date, press two.
627	To approve broadcast options, press star pound.
628	To deactivate message waiting notification, press 1.
629	Please enter month, day, and pound sign.
630	To change expiration date from
631	Message waiting notification activated.
632	Expiration date will be
633	To make non-interruptible, press one.
634	To approve login announcement options, press star pound.
635	To remove non-interruptible status, press one.
636	Login announcement will be non-interruptible.
637	Invalid date.
638	is prior to delivery date, please reschedule.
639	Message cannot be both broadcast and priority.
640	Message cannot be both a login announcement and priority.
641	Message cannot be both a login announcement and private.
642	Message cannot be both a broadcast and a login announcement.
643	You are choosing options for this message. There are no options currently set.
644	You are choosing options for this message. With the current settings,
645	Private messages cannot be forwarded by the recipients.
646	A priority message will be delivered before other messages and will be flagged for special attention in the recipient's mailbox.
647	the message will be private.
648	the message will be priority.

Fragment	Abbreviated Fragment Text
649	the message will be broadcast.
650	the message will be a login announcement.
651	the message will be private and priority.
652	A broadcast message is delivered to every subscriber on this machine. You may also address a broadcast message to subscribers on other machines.
653	For broadcast options, press star M.
654	the message will be broadcast and private.
655	A login announcement will be played each time any subscriber logs onto this machine. You may also address a login message to subscribers on other machines.
656	For login announcement options, press star M.
657	You are choosing options for this broadcast message.
658	Message waiting notification is currently not active.
659	Message waiting notification will alert all local subscribers of this message. This option should be used sparingly, for it can impact system performance.
660	Expiration date specifies the last day this broadcast message will be available to subscribers. The expiration date does not apply to a broadcast message already is the second day after the scheduled delivery date.
661	To approve these options, press star pound.
662	Message waiting notification is active.
663	Message waiting notification is not active and this message has an expiration date of
664	Message waiting notification is active and this message has an expiration date of
665	You are choosing options for this login announcement.
666	With the current settings, this login announcement will be non-interruptible
667	With the current settings, this login announcement will be interruptible.
668	With the current settings, this login announcement will be non-interruptible and the login announcement has an expiration date of
669	With the current settings, this login announcement will be interruptible and the login announcement has an expiration date of
670	Non-interruptible status forces each subscriber to listen to the entire login announcement every time they log onto this machine.
671	Expiration date specifies the last day this login announcement will be available to subscribers. The default expiration date is the second day after the scheduled
672	To address, please enter extensions and pound sign, or for options menu, press star M.
673	To address, please enter names and pound sign, or for options menu, press star M.

Fragment	Abbreviated Fragment Text
674	Due to sending restrictions, you cannot send messages to
675	
676	
677	
678	is past the expiration date, please reschedule.
679	is not available and has a full mailbox.
680	is busy and has a full mailbox.
681	Sorry, cannot leave a message now because this user's mailbox is full.
682	Broadcast message from
683	Broadcaster has deleted this broadcast message.
684	Private, broadcast message from
685	Private, priority message from
686	Private message from
687	Undeliverable message notification delivered
688	An undeliverable message was returned to your outgoing mailbox. To access your outgoing mailbox, press star R four.
689	Expiration time is
690	Priority message from
691	Login announcement from
692	Broadcast message deleted.
693	Broadcast message to all local subscribers
694	Private, broadcast message to all local subscribers
695	Private, priority message to
696	Private message to
697	Login announcement to all local subscribers
698	Priority message to
699	Message not delivered because another login announcement is active.
700	To administer mailing lists, press one. To administer personal directory, press two.
701	To change your password, press four.
702	To record your name, press five.
703	You are at subscriber administration.

Fragment	Abbreviated Fragment Text
704	To create lists, press one. To scan lists, press two. To review and modify lists, press three.
705	Directory contains
706	To add entries, press one. To review all entries, press two. To review a specific entry, press three.
707	If finished, press star pound.
708	If finished adding entries, press star pound.
709	Enter alias for
710	Enter next name and pound sign.
711	Alias
712	defined for
713	Enter next extension and pound sign.
714	Directory has no entries.
715	Cannot add new entries because your directory is full.
716	Alias must be ten or fewer numerals.
717	Alias already defined.
718	Name entered not followed by pound and not added to the directory.
719	Extension entered not followed by pound and not added to the directory.
720	Alias entered not followed by pound and not added to the directory.
721	Directory is full.
722	was not added to your personal directory.
723	You are administering your personal directory.
724	Personal directory review completed.
725	You are adding entries to your personal directory.
726	You are reviewing all entries in your personal directory.
727	Enter alias and pound sign.
728	deleted.
729	You are reviewing a specific entry in your personal directory. To delete the current entry, press star D. To review another entry, enter the alias followed by the pound sign.
730	Message not delivered because the broadcast mailbox was not defined.

Fragment	Abbreviated Fragment Text
731	To record messages, press one. To get messages, press two.
732	
733	
734	Private and priority.
735	Broadcast and private.
736	You are recording your name. As you use AUDIX your name will be included in system announcements that you and other people will hear.
737	Login announcement will be interruptible.
738	Message not delivered due to sending restrictions.
739	Message sent to all local subscribers.
740	Private message sent to all local subscribers.
741	Private, priority message sent to
742	Private message sent to
743	Priority message sent to
744	For all calls,
745	active.
746	
747	For internal calls,
748	For external calls,
749	For busy calls,
750	For no answer calls,
751	For out-of-hours calls,
752	To listen to a greeting, press zero. To create or change a greeting, press one. To scan all your greetings, press two. To activate a greeting, press three. To administer call types, press four. If finished, press star pound.
753	Enter greeting number.
754	Greeting
755	not recorded.
756	To listen to greeting
757	To re-record, press one.
758	To delete, press star D.
759	To review status, press two.

Fragment	Abbreviated Fragment Text
760	press zero.
761	
762	press two.
763	
764	To activate for each call type, press zero. For internal calls, press one. For external calls, press two.
765	recorded, but not active
766	To activate for all calls, press one.
767	To activate for each call type, press zero. For busy calls, press one. For no answer calls, press two.
768	approved.
769	Nothing to approve.
770	recorded and active
771	approved and active
772	again
773	To activate for out-of-hours calls, press three.
774	If you have addressed this message and wish to deliver it immediately, press star star pound.
775	To record messages, press one. To get messages, press two. To administer personal greetings, press three.
776	the system greeting
777	Cannot listen to system greeting.
778	Cannot modify system greeting.
779	No greetings recorded.
780	Personal greetings review completed.
781	To skip to the next greeting, press the pound sign.
782	To activate a greeting, enter greeting number.
783	To activate another greeting, enter greeting number.
784	To activate system greeting, enter zero.
785	Same greeting used for all calls.
786	To identify calls as internal and external, press one.
787	To identify calls as busy and no answer, press two.

B-30 Abbreviated (Terse) Fragments

Fragment	Abbreviated Fragment Text
788	To identify calls as out-of-hours, press three.
789	Otherwise, press four.
790	Calls identified as internal and external.
791	Calls identified as busy and no answer.
792	Calls identified as out-of-hours.
793	Calls not identified as out-of-hours.
794	To change identification to busy and no answer, press two.
795	To change to identification internal and external, press one.
796	To remove out-of-hours identification, press four.
797	To use same greeting for all calls, press five.
798	Prime time is
799	Enter name
800	You are specifying the expiration date.
801	To respond to this notification, press one. To delete, press star D. To skip, press pound.
802	Cannot send a message to the broadcast mailbox.
803	
804	not defined.
805	For internal
806	For external
807	For busy
808	For no answer
809	internal
810	external
811	busy
812	no answer
813	and out-of-hours
814	calls.
815	You are administering your personal greetings.
816	You are listening to a personal greeting.
817	You are recording a personal greeting.

Fragment	Abbreviated Fragment Text
818	You have just recorded
819	You are scanning your personal greetings.
820	You are selecting which greeting to activate.
821	You are administering call types.
822	As you use AUDIX your name will be included in system announcements that you and other people will hear. At the tone, please speak your name. After speaking your name, press one.
823	for all calls
824	for each call type
825	for internal
826	for external
827	for busy
828	for no answer
829	for out-of-hours
830	You must approve your recording.
831	To exit the expiration date options, press star pound.
832	Please enter extension and pound sign.
833	To delete current entry, press star D.
834	To delete this notification, press star D. To skip, press pound.
835	for all new messages
836	only for new priority messages
837	To turn on outcalling for all new messages, press one. To turn on outcalling only for new priority messages, press two.
838	You are selecting which messages will receive outcalls.
839	To rewind to the previous greeting, press two.
840	Option
841	not defined
842	Announcement not recorded. Try again later.
843	To scan headers and messages, press one. To scan headers only, press two. To scan messages only, press three.
844	End of message.
845	Next message.

Fragment	Abbreviated Fragment Text
846	You are selecting an option for Automatic Message Scan.
847	You are automatically scanning your incoming messages. To listen to the message, press zero. To respond to or forward the message, press one.
848	You are automatically scanning your incoming messages. To listen to the message, press zero. To respond to the message, press one.
849	To skip to the next message, press the pound sign. To listen to the header, rewind by pressing two, then play by pressing three. To skip to the next category, press star pound.
850	Broadcast and login Message services are not available.
851	To skip, press pound.
852	To rewind to the current entry, press two. To rewind to previous entries, press two as many times as necessary.
853	Messages skipped, retained as new.
854	seconds to finish recording.
855	remote AMIS mailbox id
856	This is a recorded message from
857	from
858	To replay, press 0.
859	Mailbox id not followed by pound.
860	Mailbox id not valid.
861	AMIS
862	It could not be delivered because the recipient appears to be a wrong number.
863	It could not be delivered after multiple attempts to deliver the message.
864	Automated call, please press 1 to disconnect.
865	Your number was dialed by mistake. We are sorry for the inconvenience. To prevent this from recurring, this call has been reported as a misdialed call.
866	AMIS casual subscribers cannot be added to your list.
867	You are entering the
868	Mailbox id must be less than or equal to 16 digits.
869	If the extension you entered belongs to a casual AMIS subscriber, you will be prompted for a mailbox id.

Fragment	Abbreviated Fragment Text
870	The following message was restored.
871	No message to restore.
872	To undelete last deleted message, press star star U.

C. Verbose System Fragments

This appendix lists the fragments (pieces of voice text) that compose the *verbose* set of AUDIX system announcements.

Fragment	Verbose Fragment Text
1	Another person is currently changing your personal greeting, try again later.
2	and
3	No new remote subscribers can be addressed.
4	to add to the end of the incoming message.
5	To create or change your personal greeting, press one. To listen to your personal greeting, press zero. To select which greeting to use, press star pound.
6	Please enter the machine voice ID.
7	You cannot listen to an undeliverable message.
8	To create a new message, press four.
9	You may now record your new message.
10	That is not a valid machine voice ID.
11	You are recording machine names.
12	To re-record your message, press one. After you finish recording, press one again. You may delete the message by pressing star D, or you may listen to it by pressing three. To approve it as is, press star pound.
13	To begin recording, press one. After you finish recording, press one again.
14	To make this list private, press one. To make the list public, press two.
15	and is
16	Please enter announcement ID
17	to add to the beginning of the incoming message.
18	To forward the message with a comment, press two.
19	To review the list from the beginning, press star one. If you are finished reviewing this list, press star pound.
20	Remote extension
21	To listen to the message, press zero.
22	For immediate delivery, press star pound. Otherwise, enter the hour, minutes, A or P, and then the pound sign.
23	To create a message, press one. To get your messages, press two. To change your personal greeting, press three.
24	To delete this message and cancel delivery, press star D.
25	This list-ID was not followed by a pound sign.
26	To record a subscriber's name, press four. To listen to a subscriber's name press five. To record a machine name, press six. To play a machine name, press seven.

Fragment	Verbose Fragment Text
27	If you would like a copy of the original attached to your reply, press Y for yes. If you would like only your reply to be sent, press N for no.
28	You are returned to getting your messages.
29	You are returned to scanning your outgoing messages.
30	To change this message before it's delivered, press one.
31	Date not understood.
32	You must enter your extension to log on.
33	To delete the status information, press star D.
34	Electronic Text
35	Subscriber information incorrect.
36	To create a personal greeting, press one.
37	This extension was not followed by a pound sign,
38	This name was not followed by a pound sign,
39	To rewind your personal greeting, press two. To delete it, press star D. To stop playback of your personal greeting, press three.
40	Time not understood.
41	To forward the message and add a comment at the beginning, press two.
42	Can only reply to call answering messages from subscribers.
43	Your call is being answered by the Audio Information Exchange.
44	is not available at this time. To leave a message, wait for the tone.
45	is currently busy. To leave a message, wait for the tone.
46	If you wish to access your mailbox, press star R.
47	Call Answering message from
48	To check your outgoing messages, press four. To administer other personal options, press five. To change outcalling information, press six. To automatically scan incoming messages, press seven. To re-logon, press star star R.
49	No operator has been defined.
50	Call answering message
51	Your entries for the delivery schedule are deleted, please re-enter entire delivery time and date, starting with the time.
52	Delivery is canceled, and
53	You have deleted the original message, hence no delivery will take place.

C-4 Verbose System Fragments

Fragment	Verbose Fragment Text
54	was only partially recorded due to a system problem.
55	The message was delivered at
56	Thank you for leaving your message.
57	delivered and accessed
58	To change to name addressing, press star A.
59	delivered
60	Your password has been changed as requested.
61	If you would like to modify the status of this list, press Y for yes. Otherwise, press or N for no.
62	To make room in your mailbox, delete any unneeded messages.
63	new
64	old
65	contains
66	If correct, press star pound. If not, press star D and re-enter the time.
67	To create another list,
68	undeliverable
69	undelivered
70	unopened
71	To leave a message, wait for the tone.
72	defaulted to
73	You have
74	deleted.
75	To skip, press pound. To delete, press star D.
76	Message deleted.
77	Entry deleted.
78	delivered at
79	Status information deleted.
80	To have the system wait for you, press star W. If you are finished, simply hang up or to disconnect AUDIX, press star star X.
81	digits.
82	Please leave a message for

Fragment	Verbose Fragment Text
83	entries.
84	entry.
85	Message erased.
86	extension
87	This call is experiencing difficulties.
88	You cannot use the guest password as your own password.
89	This is the first message in the mailbox.
90	Please enter fragment ID
91	At end of message.
92	No message to advance.
93	You have no personal greeting, therefore the standard system greeting will be used.
94	Good-bye.
95	Please disconnect.
96	For help, press star H.
97	For help at any time, press star H.
98	It could not be delivered due to transmission problems.
99	That is not a valid announcement number.
100	Entry not understood.
101	That is not a valid fragment number.
102	That is not a valid extension.
103	That is not a valid version number, please re-enter it,
104	This message was just delivered, you cannot listen to it any more.
105	To restart at the activity menu, press star R.
106	This was your last list.
107	This was the last member of the list.
108	You are creating a voice message.
109	later.
110	list
111	Enter the list ID,
112	Otherwise, for assistance, press zero now.

Fragment	Verbose Fragment Text
113	You already have a list
114	To replace that list, re-enter the same ID. To create a new list, enter a new list ID.
115	To transfer by specifying names instead, press star A.
116	This list is full.
117	To reach the person covering this extension, press star zero.
118	Please enter the name
119	you wish to call
120	is too large to include.
121	When you are done entering the entire list, approve the list by pressing star pound.
122	Your list space is nearly full. You may only enter
123	new subscribers.
124	You have no more list space.
125	A list name must be six or less numerals.
126	To forward the message and add a comment to the end, press three.
127	You have been returned to your previous activity.
128	You may request another transfer by pressing star T.
129	or you may leave a message for
130	because there were no entries.
131	If you wish to send this message to others not on your list,
132	You can store the list you are creating as it is now by pressing star pound, or you can add up to
133	To resume reviewing, press three. To delete an entry, press star D. If you are finished reviewing this list, press star pound.
134	You can store the list as it is now or you can delete members from it, but you cannot add any additional members.
135	following each entry with the pound sign.
136	That line is busy.
137	or approve the entire list by pressing star pound.
138	You are listening to machine names.
139	additional recipients,
140	You have already removed the entry. To remove more entries, review the list by pressing star one.

Fragment	Verbose Fragment Text
141	You have no more lists.
142	To listen to the header, press three.
143	To step back again, press two.
144	removed,
145	This list has no entries.
146	To resume reviewing the list, press the pound sign.
147	List review completed.
148	To change to extension addressing, press star A.
149	All circuits are busy.
150	members.
151	Try again after the tone.
152	Leave Word Calling message from
153	The message is at its maximum length, you cannot add to it. To re-record your message, first rewind it by pressing two, and then record over the original message by pressing one. To approve your recording, press star pound.
154	You cannot create a new list because you already have the maximum number of lists that you are allowed to have. To select lists that can be deleted, press five one two and follow instructions.
155	You cannot create a new list because the total number of subscribers in all of your lists equals the maximum that you are allowed to have.
156	You have recorded the maximum message length.
157	To approve your recording, press star pound.
158	Your transfer cannot be completed.
159	member.
160	message
161	midnight.
162	5TERSE (used in abbreviated version but not in verbose version)
163	To call the sender, press zero.
164	message category.
165	You have been returned to getting your messages.
166	At end of message. Rewind by pressing two. Then play by pressing three.
167	To approve your recording, press star pound. To record from this point, press one. To listen to your message, rewind by pressing two. Then play by pressing three.

C-8 Verbose System Fragments

Fragment	Verbose Fragment Text
168	messages.
169	You have not specified an administrative version. Please do so using the administrator's terminal.
170	Message scheduled for delivery.
171	message summary.
172	You have new
173	Enter your new password
174	Please make your next entry.
175	Please note, only AUDIX subscribers can be specified by name.
176	Please enter the next fragment ID
177	You cannot listen to a delivered message.
178	You've identified no addressees,
179	Warning, if you don't supply an addressee list, this message will be deleted immediately. Press star pound if you really don't want to address this message. Otherwise,
180	No announcement has yet been created for approval.
181	No message has yet been created for approval.
182	No entry to delete.
183	No message to delete.
184	No message to erase.
185	does not exist.
186	To create a message, press one. To get your messages, press two. To check your outgoing messages, press four.
187	and was not added to the list.
188	The two password entries do not match. Please try again by entering your new password.
189	You have no mailbox.
190	This message has been delivered, you cannot modify it now.
191	No more messages.
192	There are no messages in your mailbox.
193	No name has yet been recorded.
194	You have no new messages.
195	Your outgoing mailbox is empty.

Fragment	Verbose Fragment Text
196	You have no personal greeting.
197	You cannot step back any further.
198	Partial name deleted.
199	No message to rewind.
200	No delivery time has been entered, there is nothing to delete.
201	noon.
202	is not valid.
203	There is no room in your mailbox to create
204	another message.
205	an answer.
206	a comment.
207	You cannot create a comment for this message because it is already too long. You could instead create a new message by pressing star R one.
208	is not a public list.
209	You are not allowed to modify a list that belongs to another subscriber.
210	Please enter a new password.
211	to fifteen digits
212	Enter the same password a second time for confirmation. To delete the previously entered password, press star D.
213	Enter your new password again for confirmation.
214	Your new personal greeting is approved.
215	There is no room in your mailbox to retain a copy of this message.
216	originally
217	others
218	has been removed from the list.
219	owned by
220	Please enter your password,
221	Enter the announcement's ID number. Refer to the administration manual for the correct ID.
222	Enter the fragment's ID number. Refer to the administration manual for the correct ID.
223	Enter the subscriber's extension

Fragment	Verbose Fragment Text
224	followed by the pound sign.
225	Follow your entry with the pound sign.
226	private
227	public
228	Record at the tone.
229	You will have up to
230	seconds for your message.
231	cannot be found.
232	Recording has stopped.
233	Your previous login was incorrect. Begin again by entering your extension.
234	To respond to or forward this message, press one.
235	To restart at the activity menu, press star R. To transfer to another extension, press star T.
236	Try again
237	Otherwise, press star R.
238	To review another list,
239	you wish to review
240	To skip to the next list, press the pound sign. To listen to the contents of this list, press zero.
241	To review this list, press star one.
242	You just returned to the
243	You are at the beginning of your
244	Rewound to previous message.
245	Please return the call.
246	This message is addressed to
247	To add to this list,
248	You have already scheduled this message to be delivered at
249	If you want to change this scheduled delivery time, press star D, otherwise press star pound.
250	If you want to change the delivery time, delete the previously scheduled delivery time by pressing star D.
251	To transfer by specifying extension instead, press star A.

Fragment	Verbose Fragment Text
252	To respond to this message, press one.
253	Enter the month and day you'd like it to be delivered.
254	279TERSE (used in abbreviated version but not in verbose version)
255	To delete the message to which you just responded, press star D.
256	You are already at the beginning of the message. To re-record your message, press one. To play your message, press three.
257	To use your personal greeting, press Y for yes. To use the system standard greeting instead, press N for no.
258	Message to
259	will be delivered at
260	scheduled for delivery at
261	has been rescheduled for delivery at
262	delivered
263	You are recording a subscriber name.
264	It could not be delivered because the mailbox was full.
265	It could not be delivered because their mailboxes were full.
266	was undeliverable
267	Please enter the extension
268	To record another subscriber's name,
269	To play another subscriber's name,
270	subscriber ID
271	header.
272	Please contact your system administrator for help.
273	Please make your next entry.
274	If you do not press a button soon, you'll be disconnected from the system.
275	You cannot scan this mailbox now because someone else is currently in it.
276	The time you requested has already passed, please re-schedule delivery.
277	To exit the directory, press star pound.
278	Please enter your extension
279	To hear the active version, press one.
280	To hear the administrative version, press two.

Fragment	Verbose Fragment Text
281	Message from
282	To have the system wait for you, press star W. To access the names or numbers directory, press star star N. If you are finished, simply hang up, or to disconnect AUDIX, press star star X.
283	Your mailbox is more than
284	percent full. Please delete any unneeded messages or personal greetings.
285	To add a subscriber to the list, enter that subscriber's extension
286	To add a subscriber to the list, enter that subscriber's name
287	Welcome to your Audio Information Exchange.
288	You are in the names directory. To find a subscriber's extension, enter the name followed by the pound sign. To look up by extension instead, press star A.
289	
290	If you wish to specify a non-AUDIX subscriber, first change to extension addressing by pressing star A.
291	To transfer to another extension, press star T.
292	To increase volume, press four. To decrease volume, press seven. To increase speed, press nine. To decrease speed, press eight.
293	There is no message to playback.
294	To add entries to this list, press one.
295	If you wish to re-enter the list, press star L.
296	To delete this list, press star D.
297	If you would prefer to specify the owner by extension, press star A.
298	If you would prefer to specify the owner by name, press star A.
299	You are administering your personal greeting.
300	A. M.
301	P. M.
302	You are creating announcement fragments. Enter the fragment's ID number. Refer to the administrator's manual for the correct ID.
303	You are recording names. Enter the subscriber's extension
304	To rewind, press two. To delete your message, press star D. To approve your message, press star pound.
305	You are at the activity menu.
306	You are changing your password.

Fragment	Verbose Fragment Text
307	You are listening to announcements.
308	You are listening to announcement fragments.
309	You are listening to subscriber names.
310	January
311	February
312	March
313	April
314	May
315	June
316	July
317	August
318	September
319	October
320	November
321	December
322	You are in the numbers directory. To find a subscriber's name, enter the extension followed by the pound sign. To look up by name instead, press star A.
323	You are responding to a piece of incoming mail.
324	You are selecting which greeting will be played to callers redirected to this service. If you want your personal greeting to be played, press Y for yes. To use the system standard greeting, press N for no.
325	You are administering your lists. To create a mailing list, press one. To play a summary of all your lists, press two. To review a particular list, press three.
326	You are doing system administration. To record subscriber names, press four. To play subscriber names, press five. To record a machine name, press six. To play a machine name, press seven. To record fragments, press one. To play fragments, press two. To play announcements, press three.
327	You are creating a mailing list.
328	To add a list, press star L. You may add lists you own, or public lists owned by others. To review the list from the beginning, press star one. To approve the list, press star pound. To delete the previous entry, press star D.
329	The entry just made does not uniquely specify a subscriber.
330	Or enter just the pound sign if you are at your own phone.
331	Your personal greeting will be used.

Fragment	Verbose Fragment Text
332	The system greeting will be used.
333	To add entries to this list or to change the status of this list, press one.
334	When you are finished addressing, press star pound.
335	When you complete the list, press star pound.
336	To review the addressees, press star one.
337	
338	280TERSE (used in abbreviated version but not in verbose version)
339	To replay the last few seconds, press five. To advance a few seconds, press six.
340	383TERSE (used in abbreviated version but not in verbose version)
341	384TERSE (used in abbreviated version but not in verbose version)
342	Electronic Document Communication
343	Leave Word Calling
344	Message Center Service
345	Voice mail
346	You are recording a machine name.
347	The entry you are adding is a list.
348	You are specifying a mailing list to review.
349	To approve this list, press star pound.
350	Sunday
351	Monday
352	Tuesday
353	Wednesday
354	Thursday
355	Friday
356	Saturday
357	You are choosing between subscribers whose names match your entry. To indicate that none of the subscribers is the one desired, delete your entry by pressing star D. To change to extension addressing and delete your entry, press star A.
358	You are identifying this list as private or public.
359	You are changing the status of your list. If you would like to modify the status, press Y for yes. Otherwise, press N for no.

Fragment	Verbose Fragment Text
360	You are scanning mailing lists. To review the members of the list, press zero. To rewind to the previous list, press two. To resume scanning your lists, press three.
361	To skip to the next list, press the pound sign. To delete this list, press star D.
362	If you own the list, press the pound sign. If someone else owns the list
363	To approve the list you are creating, press star pound.
364	enter the owner's extension
365	enter the owner's name
366	To specify a different owner by extension, press star D.
367	To specify a different owner by name, press star D.
368	You are entering the number for a new list. Enter a number up to six digits long
369	To replace an existing list, enter that list's number,
370	These are the entries in your list.
371	To rewind to the current entry, press two. To rewind to previous entries, press two as many times as necessary. To resume playback of the list, press three.
372	To skip to the next entry, press the pound sign. To delete the current entry, press star D.
373	You are choosing whether to attach a copy of the original message to your reply or not. To include the original, press Y for yes. To send only your reply, press N for no.
374	You are choosing whether to store this message in your file cabinet. To put a copy in the file cabinet, press Y for yes. To send out the message without retaining a copy, press N for no.
375	You are getting your incoming messages. To listen to the message, press zero. To respond to or forward this message, press one.
376	To skip to the next header, press the pound sign. To listen to the header, rewind by pressing two, then play by pressing three. To skip to the next category, press star pound.
377	To delete this message, press star D.
378	You are scanning your outgoing messages.
379	To delete the status information, press star D.
380	Please wait.
381	To listen to the message, press zero. To modify this message before delivery, press one.
382	You are scheduling your message for delivery.

Fragment	Verbose Fragment Text
383	Enter the time in the following format: first enter the hour, then two digits for the minutes, then A for A.M or P for P.M., and then the pound sign.
384	Enter the month and day on the following format: first enter the number of the month, then then two digits for the day, and then the pound sign.
385	To approve this delivery time, press star pound. To modify it in any way, first delete it be pressing star D and listen for further instructions.
386	You cannot modify a delivered message.
387	It could not be delivered because the recipient could not be found.
388	To skip to the next header, press the pound sign.
389	To delete this message, press star D.
390	oh
391	one
392	two
393	three
394	four
395	five
396	six
397	seven
398	eight
399	nine
400	ten
401	eleven
402	twelve
403	thirteen
404	fourteen
405	fifteen
406	sixteen
407	seventeen
408	eighteen
409	nineteen
410	twenty
411	thirty

Fragment	Verbose Fragment Text
412	forty
413	fifty
414	sixty
415	seventy
416	eighty
417	ninety
418	hundred
419	thousand
420	oh.
421	one.
422	two.
423	three.
424	four.
425	five.
426	six.
427	seven.
428	eight.
429	nine.
430	zeroth.
431	first.
432	second.
433	third.
434	fourth.
435	fifth.
436	sixth.
437	seventh.
438	eighth.
439	ninth.
440	tenth.
441	eleventh.

Fragment	Verbose Fragment Text
442	twelfth.
443	thirteenth.
444	fourteenth.
445	fifteenth.
446	sixteenth.
447	seventeenth.
448	eighteenth.
449	nineteenth.
450	twentieth.
451	thirtieth.
452	fortieth.
453	fiftieth.
454	sixtieth.
455	seventieth.
456	eightieth.
457	ninetieth.
458	hundredth.
459	thousandth.
460	millionth.
461	billionth.
462	pound
463	star
464	Enter extensions
465	Enter names
466	created
467	13TERSE (used in abbreviated version but not in verbose version)
468	To continue listening, press three.
469	Enter the extension of the owner of the list
470	Enter the name of the owner of the list
471	If you own the list, you may enter the pound sign by itself.

Fragment	Verbose Fragment Text
472	To approve your recording, press star pound. To record from this point, press one.
473	file cabinet
474	To listen to the message, press zero. To modify or send this message to others, press one.
475	If you would like a copy of this message put in your file cabinet, press Y for yes. Otherwise, press N for no.
476	Message sent to
477	Press one to select
478	two to select
479	three to select
480	four to select
481	five to select
482	Press the pound sign to select
483	Otherwise, enter more characters of the name starting from where you left off.
484	Please enter additional characters of the name, starting from where you left off.
485	has
486	To reply to the sender by voice mail, press one.
487	To delete the time, press star D. To default the rest of the delivery time, press star pound.
488	To specify immediate delivery, press star pound. Otherwise
489	483TERSE (used in abbreviated version but not in verbose version)
490	484TERSE (used in abbreviated version but not in verbose version)
491	You are getting your incoming messages. To listen to the message, press zero. To respond to the message, press one.
492	List owner erased.
493	You are requesting a transfer.
494	is private.
495	is public.
496	Message filed.
497	To review your message, press star one.
498	Please enter a new list ID
499	When you finish recording, press one.

Fragment	Verbose Fragment Text
500	This is your Audio Information Exchange.
501	To create a message, press one. To get your messages, press two. To administer attendant menu, press three.
502	To record attendant menu, press one. To listen to attendant menu, press zero.
503	You are administering your attendant menu.
504	Transferring to an operator,
505	You have selected an invalid option.
506	Attendant menu is approved and activated.
507	Using touch-tones, please enter the number of the person whom you are calling.
508	Attendant Service not available, try again later.
509	System has not been administered for outcalling.
510	Number
511	If you do not have a touch-tone phone,
512	Your call is being transferred to an operator.
513	Please speak first the name and number of the person whom you are calling followed by your message. It will be delivered to that person as soon as possible. Please be aware that in order to forward this message to the recipient, someone will listen to the name and number portion.
514	otherwise
515	To be transferred to an operator,
516	To leave a message that will be delivered as soon as possible,
517	You are entering the number of the person for whom you are leaving a message. This number may be the complete number you dialed or simply the extension. For a faster response, terminate your entry with a pound sign.
518	You are creating a voice message which will be delivered to the person specified in your message as soon as possible. Please be aware that in order to forward this message to the recipient, someone will listen to the name and number portion.
519	You are not authorized for outcalling.
520	Your outcalling phone number,
521	is turned on
522	is turned off
523	You have specified outcalling for
524	to

Fragment	Verbose Fragment Text
525	any time
526	subject to administrator restrictions
527	To change your outcalling phone number, press one. To specify when to be called, press two. To listen to detailed instructions on how to change your outcalling phone number, press three.
528	To turn on outcalling, press Y for yes. To turn off outcalling, press N for no.
529	You are changing your outcalling options.
530	Outcalling
531	Please enter the number to be called
532	To change your outcalling phone number, press one and enter the number to be called followed by the pound sign. Anything you enter will be interpreted as a part of the called number. No global commands such as star H will be accepted at this time.
533	Too many digits entered.
534	Your outcalling number is
535	To allow outcalling at any time, press one. To allow outcalling during prime time, press two. To specify your own time period, press three. To hear system outcalling schedule, press four.
536	You are specifying when you would like to be called when you have new messages. The time you specify will be restricted by the times allowed by the system administrator.
537	Enter the starting hour, then two digits for the minutes, A for A.M. or P for P.M., and then the pound sign.
538	Enter the ending hour, then two digits for the minutes, A for A.M. or P for P.M., and then the pound sign.
539	The system allows outcalls to be made only from
540	and from
541	Up to
542	digits may be used.
543	To avoid further notification of these messages, press star pound.
544	You have specified outcalling for
545	To delete your own time range, press star D.
546	pause
547	Good-bye

Fragment	Verbose Fragment Text
548	You have no attendant menu.
549	You are administering your attendant menu. To create attendant menu, press one.
550	To rewind your attendant menu, press two. To delete it, press star D. To stop playback of your attendant menu, press three.
551	To access your messages,
552	is not authorized to receive messages.
553	You may enter another number
554	To access your mailbox, press star R. To transfer to another extension, press star T.
555	To access your mailbox, press star R.
556	No global commands such as star H will be accepted at this time. To return to outcalling administration, press star pound now.
557	In most cases, entering a star or pound as the first digit will result in the star or pound being outpulsed. A star entered as part of the digit string will be interpreted as a pause of one and a half seconds. If a longer pause is required, use multiple stars in a row.
558	subject to administrator restrictions.
559	There is no space to record a name. The size of the names filesystem must be increased.
560	If you are programming a number to call a pager that requires a pound sign termination, press Y to hear further help. Otherwise, press N to return to outcalling administration.
561	You are addressing your message.
562	Please enter the
563	digit extension
564	There is no room in the mailbox to leave a message.
565	Outcall canceled for new messages currently in mailbox.
566	You are responding to an outcall notifying you of new messages.
567	Either logging in or pressing star pound will result in the outcall being canceled for the new messages currently in your mailbox. If additional new messages arrive, another outcall will be scheduled.
568	personal greeting
569	To modify this list, press one. If you are finished with this list, press star pound.
570	The recorded name exceeded the maximum limit.

Fragment	Verbose Fragment Text
571	Non-existent subscriber
572	To access the options menu, press star M.
573	
574	Private message
575	You cannot forward a private message
576	Recipients can forward this message
577	To hold the message in its current category, press star star H.
578	
579	Password must be
580	You Cannot attach a private message
581	Please press N now.
582	AUDIX passwords must now be at least
583	
584	It could not be delivered because special feature denied on recipient's machine.
585	zero
586	To skip to the next entry, press the pound sign.
587	You are reviewing a list.
588	or more digits.
589	For pagers requiring a pound sign termination, start your number with a double pound sign. This will result in a single pound sign being outpulsed at the end of the digit string. Then, a star or pound in the next position will be interpreted as part of the outcalling number.
590	A star entered as part of the digit string will be interpreted as a pause of one and a half seconds. If a longer pause is desired, use multiple stars in a row.
591	To change your outcalling phone number, press one. To hear further instructions on programming a page, press Y. To return to outcalling administration, press N.
592	AUDIX passwords must now be
593	Please choose a new password of
594	To delete this message, press star D.
595	
596	
597	

Fragment	Verbose Fragment Text
598	
599	
600	You have new broadcast messages.
601	Priority
602	other
603	You also have
604	As you use AUDIX, your name will be included in system announcements that you and other people will hear. Press one, and at the tone, please speak your first and last name as you would like others to hear it. After speaking your name, press one again.
605	
606	To re-record your name, press one. To approve your name, press star pound.
607	Your recorded name cannot be saved at this time, please continue
608	At the tone, please speak your name as you would like others to hear it. After speaking your name, press one.
609	There is no room in your mailbox to save copy of this broadcast message so it will be retained in the new message category.
610	You are recording your name. After you record your name, you can access other AUDIX features. As you use AUDIX, your name will be included in system announcements that you and other people will hear. Press one and at the tone, please speak your first and last name as you would like others to hear it. After speaking your name, press one again.
611	You are recording your name. To record your name, press one. After recording, press one again. To rewind press two, then play by pressing three. To approve your name, press star pound.
612	To make the message private, press one.
613	To make the message priority, press two.
614	To make the message broadcast, press eight.
615	To make the message a login announcement, press nine.
616	To exit the options menu, press star pound.
617	To remove private status, press one.
618	To remove priority status, press two.
619	To remove broadcast status, press eight.
620	To remove login announcement status, press nine.

Fragment	Verbose Fragment Text
621	Message will be private
622	Message will be priority
623	Message will be broadcast.
624	Message will be a login announcement
625	To activate message waiting notification for this message, press one.
626	To specify expiration date, press two.
627	To approve broadcast message options, press star pound.
628	To deactivate message waiting notification for this message, press 1.
629	Enter the month and day followed by the pound sign.
630	To change expiration date from
631	Message waiting notification will be activated.
632	Expiration date will be
633	To make this login announcement non-interruptible, press one.
634	To approve login announcement options, press star pound.
635	To remove non-interruptible status, press one.
636	Login announcement will be non-interruptible.
637	Invalid date.
638	is prior to the delivery date, please reschedule expiration date.
639	A message cannot be both broadcast and priority.
640	A message cannot be both a login announcement and priority.
641	A message cannot be both a login announcement and private.
642	A message cannot be both broadcast and a login announcement.
643	You are choosing options for this message. There are no options currently set.
644	You are choosing options for this message. With the current settings,
645	Private messages cannot be forwarded by the recipients.
646	A priority message will be delivered before other messages and will be flagged for special attention in the recipient's mailbox.
647	the message will be private.
648	the message will be priority.
649	the message will be broadcast.

Fragment	Verbose Fragment Text
650	the message will be a login announcement.
651	the message will be private and priority.
652	A broadcast message is delivered to every subscriber on this machine. You may also address a broadcast message to subscribers on other machines.
653	For broadcast message options, press star M.
654	the message will be broadcast and private.
655	A login announcement will be played each time any subscriber logs onto this machine. You may also address a login message to subscribers on other machines.
656	For login announcement options, press star M.
657	You are choosing options for this broadcast message.
658	Message waiting notification is currently not active.
659	Message waiting notification will alert all local subscribers of this message. This option should be used sparingly, for it can impact system performance.
660	Expiration date specifies the last day this broadcast message will be available to subscribers. The expiration date does not apply to a broadcast message already received by a subscriber and saved in their mailbox. The default expiration date is the second day after the scheduled delivery date.
661	To approve these options, press star pound.
662	Message waiting notification is currently active.
663	Message waiting notification is currently not active and this message has an expiration date of
664	Message waiting notification is currently active and this message has an expiration date of
665	You are choosing options for this login announcement.
666	With the current settings, this login announcement will be non-interruptible.
667	With the current settings, this login announcement will be interruptible.
668	With the current settings, this login announcement will be non-interruptible and the login announcement has an expiration date of
669	With the current settings, this login announcement will be interruptible and the login announcement has an expiration date of
670	Non-interruptible status forces each subscriber to listen to the entire login announcement every time they log onto this machine.
671	Expiration date specifies the last day this login announcement will be available to subscribers. The default expiration date is the second day after the scheduled delivery date.

Fragment	Verbose Fragment Text
672	To address, enter extensions following each entry with the pound sign, or for the options menu, press star M.
673	To address, enter names following each entry with the pound sign, or for the options menu, press star M.
674	Due to sending restrictions, you cannot send messages to
675	
676	
677	
678	is past the expiration date, please reschedule.
679	is not available at this time and has a full mailbox.
680	is currently busy and has a full mailbox.
681	Sorry, you cannot leave a message now because this user's mailbox is full.
682	Broadcast message from
683	Broadcaster has deleted this broadcast message.
684	Private, broadcast message from
685	Private, priority message from
686	Private message from
687	Undeliverable message notification delivered
688	An undeliverable message was returned to your outgoing mailbox. To access your outgoing mailbox, press star R four.
689	Expiration time is
690	Priority message from
691	Login announcement from
692	Broadcast message deleted.
693	Broadcast message to all local subscribers
694	Private, broadcast message to all local subscribers
695	Private, priority message to
696	Private message to
697	Login announcement to all local subscribers
698	Priority message to
699	It could not be delivered because another login announcement is active.

Fragment	Verbose Fragment Text
700	To administer mailing lists, press one. To administer personal directory, press two.
701	To change your password, press four.
702	To record your name, press five.
703	You are at subscriber administration.
704	To create a mailing list, press one. To scan your mailing lists, press two. To review and modify a list, press three.
705	Your directory contains
706	To add entries, press one. To review all entries, press two. To review a specific entry, press three.
707	If you are finished, press star pound.
708	If you are finished adding entries, press star pound.
709	Enter the alias for
710	Enter the next name followed by the pound sign.
711	Alias
712	defined for
713	Enter the next extension followed by the pound sign.
714	Directory has no entries.
715	You cannot add new entries because your directory is full.
716	Alias must be ten or fewer numerals.
717	Alias already defined.
718	This name was not followed by a pound sign and was not added to the directory.
719	This extension was not followed by a pound sign and was not added to the directory.
720	This alias was not followed by a pound sign and was not added to the directory.
721	Directory is full.
722	was not added to your personal directory.
723	You are administering your personal directory.
724	Your personal directory review completed.
725	You are adding entries to your personal directory.
726	You are reviewing all entries in your personal directory.
727	Enter the alias followed by the pound sign.
728	has been removed from the directory.

Fragment	Verbose Fragment Text
729	You are reviewing a specific entry in your personal directory. To delete the current entry, press star D. To review another entry, enter the alias followed by the pound sign.
730	It could not be delivered because the broadcast mailbox was not defined.
731	To create a message, press one. To get your messages, press two.
732	
733	
734	Message will be private and priority.
735	Message will be broadcast and private.
736	You are recording your name. As you use AUDIX your name will be included in system announcements that you and other people will hear.
737	Login announcement will be interruptible.
738	It could not be delivered due to sending restrictions.
739	Message sent to all local subscribers.
740	Private message sent to all local subscribers.
741	Private, priority message sent to
742	Private message sent to
743	Priority message sent to
744	For all calls,
745	is active.
746	
747	For internal calls,
748	For external calls,
749	For busy calls,
750	For no answer calls,
751	For out-of-hours calls,
752	To listen to a greeting, press zero. To create or change a greeting, press one. To scan all your greetings, press two. To activate a greeting, press three. To administer call types, press four. If you are finished, press star pound.
753	Enter greeting number, one through nine.
754	Greeting
755	is not recorded.
756	To listen to greeting

Fragment	Verbose Fragment Text
757	To re-record this greeting, press one.
758	To delete this greeting, press star D.
759	To review status of this greeting, press two.
760	press zero.
761	
762	press two.
763	
764	To activate this greeting for each call type, press zero. To activate this greeting for internal calls, press one. To activate this greeting for external calls, press two.
765	is recorded, but not active
766	To activate this greeting for all calls, press one.
767	To activate this greeting for each call type, press zero. To activate this greeting for busy calls, press one. To activate this greeting for no answer calls, press two.
768	is approved but not active
769	No greeting has yet been created for approval.
770	is recorded and active
771	approved and active
772	again
773	To activate this greeting for out-of-hours calls, press three.
774	If you have addressed this message and wish to deliver it immediately, press star star pound.
775	To create a message, press one. To get your messages, press two. To administer your personal greetings, press three.
776	the system greeting
777	You cannot listen to the system greeting.
778	You cannot modify the system greeting.
779	You have no greetings recorded.
780	Your personal greetings review completed.
781	To skip to the next greeting, press the pound sign.
782	To activate a personal greeting, enter the greeting number one through nine.

Fragment	Verbose Fragment Text
783	To activate another personal greeting, enter the greeting number one through nine.
784	To activate the system greeting, enter zero.
785	The same greeting is used for all calls.
786	To identify calls as internal and external, press one.
787	To identify calls as busy and no answer, press two.
788	To identify calls as out-of-hours, press three.
789	Otherwise, press four.
790	Calls are being identified as internal and external.
791	Calls are being identified as busy and no answer.
792	Calls are being identified as out-of-hours.
793	Calls are not being identified as out-of-hours.
794	To change call identification to busy and no answer, press two.
795	To change call identification to internal and external, press one.
796	To remove out-of-hours identification, press four.
797	To use the same greeting for all calls, press five.
798	Prime time is
799	Enter name
800	You are specifying the expiration date.
801	To respond to this notification, press one. To delete this notification, press star D. To skip to the next header, press the pound sign.
802	You cannot send a message to the broadcast mailbox.
803	
804	is not defined.
805	For internal
806	For external
807	For busy
808	For no answer
809	internal
810	external
811	busy

Fragment	Verbose Fragment Text
812	no answer
813	and out-of-hours
814	calls.
815	You are administering your personal greetings.
816	You are listening to a personal greeting.
817	You are recording a personal greeting.
818	You have just recorded
819	You are scanning your personal greetings.
820	You are selecting which greeting to activate.
821	You are administering call types.
822	As you use AUDIX your name will be included in system announcements that you and other people will hear. At the tone, please speak your first and last name as you would like others to hear it. After speaking your name, press one.
823	
824	
825	
826	
827	
828	
829	
830	You must approve your recording.
831	To exit the expiration date options, press star pound.
832	Enter extension followed by pound sign.
833	To delete the current entry, press star D.
834	To delete this notification, press star D. To skip to the next header, press the pound sign.
835	for all new messages
836	for all new priority messages
837	To turn on Outcalling for all new messages, press one. To turn on outcalling only for new priority messages, press two.
838	You are selecting which messages will receive outcalls.

Fragment	Verbose Fragment Text
839	To rewind to the previous greeting, press two.
840	Option
841	not defined
842	Announcement not recorded. Try again later.
843	To scan headers and messages, press one. To scan headers only, press two. To scan messages only, press three.
844	End of message.
845	Next message.
846	You are selecting an option for Automatic Message Scan.
847	You are automatically scanning your incoming messages. To listen to the message, press zero. To respond to or forward the message, press one.
848	You are automatically scanning your incoming messages. To listen to the message, press zero. To respond to the message, press one.
849	To skip to the next message, press the pound sign. To listen to the header, rewind by pressing two, then play by pressing three. To skip to the next category, press star pound.
850	Broadcast and Login Message services are not available.
851	To skip to the next message, press the pound sign.
852	To rewind to the current entry, press two. To rewind to previous entries, press two as many times as necessary.
853	Messages skipped, retained as new.
854	seconds to finish recording.
855	remote AMIS mailbox id
856	This is a recorded message from
857	from
858	To replay this message, press 0.
859	This mailbox id was not followed by the pound sign.
860	This mailbox id is not valid.
861	AMIS
862	It could not be delivered because the recipient appears to be a wrong number.
863	It could not be delivered after multiple attempts to deliver the message.
864	Automated call, please press 1 to disconnect.

Fragment	Verbose Fragment Text
865	Your number was dialed by mistake. We are sorry for this inconvenience. To prevent this from recurring, this call has been reported as a misdialed call.
866	AMIS casual subscribers cannot be added to your list.
867	You are entering the
868	This mailbox id must be less than or equal to 16 digits.
869	If the extension belongs to a casual AMIS subscriber, you will be prompted for a mailbox id.
870	The following message was restored.
871	No message to restore.
872	To undelete last deleted message, press star star U.

D. Fragment/Announcement Cross-Reference

This appendix provides a cross-referenced list of the system announcements that access each voiced fragment. Generally, the verbose and abbreviated announcement sets access the same fragments. Any exceptions are noted in the text.

D-2 Fragment/Announcement Cross-Reference

Fragment	System Announcements That Use The Fragment
1	199
2	8
3	96
4	
5	301, 500
6	177, 184, 217
7	229
8	7, 20, 21, 25, 28, 29, 52, 201, 515, 517, 519, 521, 522, 524, 526, 528, 546
9	
10	181
11	184
12	43
13	58, 158, 501, 503, 507, 508, 509, 510, 513, 747, 750
14	117, 588
15	9
16	10
17	
18	7, 201, 367, 515, 519
19	195
20	23
21	24, 132, 223, 1072, 1085, 1088
22	172, 215
23	221, 512, 932, 936
24	223, 258
25	340
26	226
27	466
28	
29	15
30	258

Fragment	System Announcements That Use The Fragment
31	16
32	17
33	254
34	249
35	19
36	502
37	255, 344
38	256, 345
39	500
40	22
41	20, 28, 517, 521, 546
42	34
43	36, 709
44	33, 76
45	314, 539
46	35, 537, 543, 586, 746, 747
47	472
48	512, 701, 932, 933, 934, 936, 1038, 1049, 1050, 1051, 1052, 1053
49	84
50	302
51	30
52	Verbose: 31
53	144
54	305
55	306
56	Verbose: 35, 44 Abbreviated: 35
57	1
58	574, 575, 1054, 1092
59	47
60	37

D-4 Fragment/Announcement Cross-Reference

Fragment	System Announcements That Use The Fragment
61	38
62	146, 147, 148, 149
63	138
64	182
65	40
66	41
67	141
68	230
69	231
70	232
71	505
72	45
73	2
74	48
75	350
76	31, 46, 1087
77	49
78	303
79	53
80	101, 102, 227, 602, 746, 747, 749, 783, 784, 938, 939, 940, 1088
81	787
82	81
83	57
84	369
85	58
86	60
87	61, 78
88	13
89	64
90	65

Fragment	System Announcements That Use The Fragment
91	26
92	67
93	310
94	70
95	14, 61, 119, 143,228, 738, 757, 1064, 1087
96	161, 227
97	240
98	50, 208
99	71
100	116, 755
101	73
102	315
103	74
104	77
105	101, 102, 120, 141, 142, 545, 547, 549, 704, 751, 753, 754, 759, 935
106	79
107	115
108	107, 508, 510
109	61, 119, 712, 770
110	82
111	83, 141, 341, 576, 608, 614, 616
112	76, 539
113	85
114	107
115	80, 88, 120, 545
116	107, 109
117	88, 529, 537, 545, 549, 736, 737, 746, 747, 775, 936, 938, 1049, 1050, 1053, 1058
118	89, 529, 531, 547, 549
119	120, 545, 547, 549
120	97

Fragment	System Announcements That Use The Fragment
121	94, 112
122	92
123	93
124	106, 111
125	341
126	20, 28, 517, 521, 546
127	161
128	90, 551
129	90
130	95
131	11
132	98
133	106, 107
134	110
135	255, 256, 342, 343
136	124
137	
138	217
139	100
140	51
141	103
142	63, 64, 196, 197, 206, 222
143	196, 198, 222
144	95, 114
145	56
146	198, 200
147	353
148	Verbose: 596, 597, 604, 606, 618, 1055 Abbreviated: 596, 597, 618, 1055
149	131
150	127

Fragment	System Announcements That Use The Fragment
151	116
152	320
153	121
154	86
154	86
155	87
156	44, 122
157	122
158	119
159	126
160	Verbose: 6, 128 Abbreviated: 6
161	129
162	
163	515, 517, 519, 521, 522, 524, 526, 528
164	32
165	132, 1072
166	133
167	134
168	130, 756
169	159
170	136
171	137
172	139, 756
173	178
174	
175	89, 529
176	322
177	151
178	153
179	241
180	152

D-8 Fragment/Announcement Cross-Reference

Fragment	System Announcements That Use The Fragment
181	69, 143, 145, 154
182	156
183	157
184	158
185	160
186	155
187	255, 256
188	163
189	164
190	165
191	166
192	167
193	318
194	168
195	169
196	170
197	62, 63, 64
198	356
199	171
200	172
201	140
202	174
203	146, 147, 148
204	Verbose: 146
205	Verbose: 147
206	Verbose: 148
207	150
208	175
209	176
210	530, 783

Fragment	System Announcements That Use The Fragment
211	782
212	532, 784
213	179
214	309
215	149, 1011
216	307, 308
217	183
218	185
219	186
220	187, 525
221	540
222	536
223	544
224	10, 18, 65, 74, 80, 83, 88, 89, 108, 120, 141, 163, 177, 178, 179, 184, 187 216, 217, 233, 316, 317, 319, 322, 340, 341, 344, 345, 346, 347, 357, 358 506, 516, 518, 520, 523, 525, 529, 530, 531, 544, 545, 547, 549, 574, 575 576, 582, 596, 597, 598, 600, 608, 610, 612, 614, 616, 733, 756, 772, 783 872, 873, 1008, 1048, 1078, 1092
225	Verbose: 329, 330, 504, 536, 540, 604, 606, 618 Abbreviated: 329, 330, 604, 606, 618
226	189
227	190
228	192
229	348
230	193
231	105
232	69, 931
233	520, 523
234	202, 464
235	28, 29, 52, 68, 184, 217, 500, 502, 504, 506, 517, 521, 524, 527, 528, 530 532, 533, 534, 536, 538, 540, 544, 546, 548, 550, 552, 568, 572, 574, 578, 580 582, 584, 588, 590, 592, 594, 596, 602, 604, 606, 610, 612, 614, 616, 618, 703 736, 737, 748, 758, 775, 788, 792, 1058, 1069, 1070
236	61, 119, 194, 712, 770

Fragment	System Announcements That Use The Fragment
237	317, 319
238	142
239	Verbose: 357, 358, 709
240	349
241	109, 111
242	191
243	72, 128, 222
244	206
245	211
246	3
247	4
248	212
249	213
250	214
251	529, 531
252	54
253	216
254	Abbreviated: 534, 538
255	132
256	203
257	313
258	Verbose: 282 Abbreviated: 282, 368
259	283
260	284, 308
261	285
262	287
263	501, 507
264	289
265	290
266	Verbose: 266
267	316, 317, 319

Fragment	System Announcements That Use The Fragment
268	Verbose: 317
269	Verbose: 319
270	224
271	Verbose: 222
272	14, 164
273	Verbose: 227
274	227, 712, 713
275	228
276	238
277	99, 101, 102
278	233, 516, 518, 756, 772
279	Verbose: 234, 534, 538 Abbreviated: 234
280	Verbose: 234, 534, 538 Abbreviated: 234
281	304
282	28, 29, 52, 68, 120, 184, 217, 500, 502, 504, 506, 512, 517, 521, 524, 527, 528, 530, 532, 533, 534, 536, 538, 540, 544, 545, 546, 547, 548, 549, 550, 552, 568, 572, 574, 578, 580, 582, 584, 588, 590, 592, 594, 596, 604, 606, 610, 612, 614, 616, 618, 701, 703, 704, 736, 737, 748, 750, 751, 753, 754, 758, 759, 775, 788, 792, 932, 933, 934, 935, 936, 1038, 1049, 1050, 1051, 1052, 1053, 1058, 1069, 1070
283	236
284	237
285	574, 575, 1092
286	596, 597
287	240
288	101
289	
290	547, 549
291	537, 543, 701, 746, 747, 932, 934, 936, 938, 940, 1049, 1050, 1052, 1053
292	68, 500, 507, 508, 509, 510, 527, 548, 550, 552, 580, 584, 594, 703, 704, 747, 750, 792, 1036, 1069, 1070
293	248

D-12 Fragment/Announcement Cross-Reference

Fragment	System Announcements That Use The Fragment
294	220, 584
295	355
296	349
297	600, 612
298	598, 610
299	500, 502
300	260
301	261
302	504
303	506
304	507, 508, 509, 747, 750
305	512, 701, 932, 933, 934, 936, 1038, 1049, 1050, 1051, 1052, 1053
306	530, 532, 783, 784
307	538, 540
308	534, 536
309	544
310	270
311	271
312	272
313	273
314	274
315	275
316	276
317	277
318	278
319	279
320	280
321	281
322	102
323	28, 29, 52, 517, 521, 524, 528, 546
324	568

Fragment	System Announcements That Use The Fragment
325	1034
326	572
327	574, 596, 606
328	Verbose: 574, 575, 596, 597, 604, 606, 1092 Abbreviated: 574, 575, 596, 597, 1092
329	606, 618
330	516, 520
331	
332	312
333	527, 1073
334	5
335	91
336	4
337	
338	Abbreviated: 534, 538
339	68, 500, 507, 508, 509, 510, 548, 552, 594, 703, 704, 1036, 1069, 1070
340	Abbreviated: 560
341	Abbreviated: 562
342	55
343	118
344	123
345	235
346	503, 509
347	576, 598, 600, 608
348	610, 612, 614, 616, 618
349	109, 111, 255, 256
350	360
351	361
352	362
353	363
354	364

D-14 Fragment/Announcement Cross-Reference

Fragment	System Announcements That Use The Fragment
355	365
356	366
357	602
358	588
359	578
360	580
361	580
362	598, 600, 610, 612
363	576, 608, 614, 616
364	598, 610
365	600, 612
366	576, 614
367	608, 616
368	582
369	582
370	527, 584
371	527, 584, 791
372	527, 584, 926, 1046
373	592
374	590
375	548
376	68, 548, 550, 552, 594
377	68, 548, 552, 594, 1069, 1070
378	550, 552, 594
379	550
380	511, 765
381	552
382	560, 562
383	Verbose: 22, 560 Abbreviated: 22
384	Verbose: 16, 562, 1010 Abbreviated: 16, 1010

Fragment	System Announcements That Use The Fragment
385	566
386	259
387	209, 262
388	24, 54, 131, 173, 202, 223, 252, 253, 254, 257, 258, 469
389	24, 54, 59, 173, 202, 252, 257, 1072, 1086, 1088
390	390
391	391
392	392
393	393
394	394
395	395
396	396
397	397
398	398
399	399
400	400
401	401
402	402
403	403
404	404
405	405
406	406
407	407
408	408
409	409
410	410
411	411
412	412
413	413
414	414

Fragment	System Announcements That Use The Fragment
415	415
416	416
417	417
418	418
419	419
420	420
421	421
422	
423	
424	
425	
426	
427	
428	
429	
430	430
431	431
432	432
433	433
434	434
435	435
436	436
437	437
438	438
439	439
440	440
441	441
442	442
443	443
444	444
445	445

Fragment	System Announcements That Use The Fragment
446	446
447	447
448	448
449	449
450	450
451	451
452	452
453	453
454	454
455	455
456	456
457	457
458	458
459	459
460	460
461	461
462	462
463	463
464	255, 342, 872
465	256, 343, 873
466	292
467	
468	180, 471
469	344, 346, 347
470	345, 347, 358
471	344, 345, 346, 347, 357, 358
472	59, 471
473	468
474	257, 469, 594
475	467

Fragment	System Announcements That Use The Fragment
476	Verbose: 368
477	323
478	324
479	325
480	326
481	327
482	328
483	329, 604
484	330, 606, 618
485	66
486	21, 29, 201, 515, 517, 522, 523, 546
487	562
488	560
489	
490	
491	68
492	354
493	547, 549, 769
494	351
495	352
496	359
497	78, 507, 508, 509, 747, 750
498	18, 340
499	251
500	719
501	700, 701, 1038, 1050
502	702, 703, 704
503	703, 704
504	705
505	706

Fragment	System Announcements That Use The Fragment
506	707
507	709, 714
508	738
509	741
510	711
511	712, 765
512	716
513	717
514	712
515	715
516	718
517	746, 749
518	747, 750
519	720
520	721
521	722
522	723
523	724
524	725
525	726
526	727
527	728, 748, 751, 1058
528	729, 748, 751, 1058
529	748, 751, 1058
530	730
531	733
532	734
533	731
534	732
535	735, 736, 753

Fragment	System Announcements That Use The Fragment
536	736, 737, 753, 754
537	739
538	740
539	742
540	743
541	744
542	745
543	756, 772
544	766
545	737, 754
546	752
547	708
548	760
549	758, 759
550	703, 704
551	756, 772
552	762
553	763
554	
555	709, 749, 750, 938, 939, 940
556	761
557	734
558	Verbose: 767
559	710
560	734
561	575, 597, 1092
562	768, 769, 1078
563	80, 88, 120, 545
564	770
565	771
566	772

Fragment	System Announcements That Use The Fragment
567	772
568	Verbose: 72
569	773
570	204
571	774
572	750, 776, 872, 873
573	
574	778
575	779
576	780
577	68, 548, 1069, 1070
578	
579	75
580	781
581	785
582	786
583	
584	789
585	790
586	791, 792
587	792
588	793
589	764
590	764
591	788
592	794
593	795
594	1085
595	

D-22 Fragment/Announcement Cross-Reference

Fragment	System Announcements That Use The Fragment
596	
597	
598	
599	
600	800
601	801
602	802
603	803
604	804
605	
606	806
607	807
608	808
609	809
610	810
611	811
612	812
613	813
614	814
615	815
616	816
617	817
618	818
619	819
620	820
621	821
622	822
623	823
624	824
625	825

Fragment	System Announcements That Use The Fragment
626	826
627	827
628	828
629	829
630	830
631	831
632	832
633	833
634	834
635	835
636	836
637	837
638	838
639	839
640	840
641	841
642	842
643	843
644	844
645	845
646	846
647	847
648	848
649	849
650	850
651	851
652	852
653	853
654	854
655	855

D-24 Fragment/Announcement Cross-Reference

Fragment	System Announcements That Use The Fragment
656	856
657	857
658	858
659	859
660	860
661	861
662	862
663	863
664	864
665	865
666	866
667	867
668	868
669	869
670	870
671	871
672	
673	
674	874
675	
676	
677	
678	878
679	879
680	880
681	881
682	882
683	883
684	884
685	885

Fragment	System Announcements That Use The Fragment
686	886
687	887
688	888
689	889
690	890
691	891
692	892
693	893
694	894
695	895
696	896
697	897
698	898
699	899
700	900
701	901
702	902
703	903
704	904
705	905
706	906
707	907
708	908
709	909
710	910
711	911
712	912
713	913
714	914
715	915

Fragment	System Announcements That Use The Fragment
716	916
717	917
718	918
719	919
720	920
721	921
722	922
723	923
724	924
725	925
726	926
727	927
728	928
729	929
730	930
731	933, 934, 1049
732	
733	
734	943
735	944
736	937
737	946
738	947
739	948
740	949
741	950
742	951
743	952
744	953
745	954

Fragment	System Announcements That Use The Fragment
746	
747	956
748	957
749	958
750	959
751	960
752	961
753	962
754	963
755	964
756	965
757	966
758	967
759	968
760	969
761	
762	971
763	
764	973
765	974
766	975
767	976
768	977
769	978
770	979
771	980
772	981
773	982
774	983
775	984

Fragment	System Announcements That Use The Fragment
776	985
777	986
778	987
779	988
780	989
781	990
782	991
783	992
784	993
785	994
786	995
787	996
788	997
789	998
790	999
791	1000
792	1001
793	1002
794	1003
795	1004
796	1005
797	1006
798	1007
799	1008
800	1009
801	1012
802	1013
803	
804	1015
805	1016

Fragment	System Announcements That Use The Fragment
806	1017
807	1018
808	1019
809	1020
810	1021
811	1022
812	1023
813	1024
814	1025
815	1026
816	1027
817	1028
818	1029
819	1030
820	1031
821	1032
822	1033
823	1037
824	
825	1039
826	1040
827	1041
828	1042
829	1043
830	1044
831	1045
832	1047
833	1054, 1055, 1079
834	
835	1056

Fragment	System Announcements That Use The Fragment
836	1057
837	1059
838	1060
839	1061
840	1062
841	1063
842	1064
843	1065, 1068
844	1066
845	1067
846	1068
847	1069
848	1070
849	1069, 1070
850	1071
851	1072
852	926
853	1074
854	1075
855	1078, 1079
856	1076
857	1084
858	1086
859	1089
860	1090
861	1077
862	1080
863	1081
864	1082
865	1083

Fragment	System Announcements That Use The Fragment
866	1091
867	1079
868	1079, 1092
869	1092
870	1100
871	1101
872	1102

Index

A

- abbreviated announcements
 - example of use *1-1*
 - fragment composition *A-1*
 - fragment list *B-1*
- active announcement set *1-2*
- add fragment to announcement *2-5*
- administration
 - customizing system announcements *2-1*
- administrative announcement set *1-2*
- announcement data (adat) filesystems *1-1*
- announcement sets
 - abbreviated *1-1*
 - active *1-2*
 - administrative *1-2*
 - distribution on disks *1-3*
 - verbose *1-1*
- announcements
 - abbreviated fragments *B-1*
 - announcement/fragment cross-reference *D-1*
 - defined *1-1*
 - fragment composition *A-1*
 - verbose fragments *C-1*

B

- backing up announcement sets *1-3*

C

- Call Answer
 - re-recording default greeting *2-1*
 - restoring customized greeting after an upgrade *2-7*
- changing fragments
 - default Call Answer greeting *2-1*
 - default Voice Mail greeting *2-1*
- cross-referenced fragment/announcement table *D-1*
- customizing system announcements
 - overview of process *1-1, 1-3*
 - procedures *2-1*

D

- delete fragment from announcement *2-4*

F

- filesystems
 - announcement data (adat) *1-1*
- fragments
 - add to an announcement *2-5*
 - defined *1-1*
 - delete from announcement *2-4*
 - fragment/announcement cross-reference *D-1*
 - re-recording *2-1*

G

- greetings
 - re-recording default system greetings *2-1*
 - restoring customized greetings after an upgrade *2-7*

R

- re-recording default greeting *2-1*
- re-recording fragments *2-1*
- restoring customized announcements after an upgrade *2-7*

S

- system announcements
 - abbreviated fragments *B-1*
 - fragment composition *A-1*
 - verbose fragments *C-1*

T

- terse announcements, *see* abbreviated announcements

U

upgrades

restoring customized announcements *2-7*

V

verbose announcements

example of use *1-1*

fragment composition *A-1*

fragment list *C-1*

Voice Mail

re-recording default greeting *2-1*

restoring customized greeting after an upgrade
2-7