

BELL SYSTEM PRACTICES
Station Installation and Maintenance

ADDENDUM C44.103
Issue 1, 1-15-42
AT&T Co Standard

Persall

TELEPHONE BOOTHS 1, 2, 5, 6 AND 7 TYPES DESCRIPTION AND SUPPLIES

1. GENERAL

1.01 This addendum supplements Section C44.103, Issue 1. It is issued to include in the list of supplies the material and piece parts used when rubber floors in 5 and 6 type booths are replaced with linoleum floor covering and to include a black finished No. 167A backboard.

1.02 The following items should be included in Paragraph 3, Supplies:

Backboards: **167A-3 or 167A-13 Backboards.** Black or bronze finished metal backboard used to mount coin collector in corner of 1, 2, 5, 6 and 7 type booths. Black finish furnished unless otherwise specified. Supersedes 153A backboard.

Cement, Linoleum: **No. 310 Wall Adhesive.** Furnished in 1 pint container. This amount is sufficient for cementing the linoleum base plates, felt base and linoleum floor in one booth.

Floor Covering: **Linoleum Assembly P-350909.** This includes the following:

Base Plate, P-350894. Linoleum, for back of booth, one required.

Base Plate, P-350895. Linoleum, for sides of booth, two required.

Floor, P-350896. Linoleum, one required.

Moulding, P-350897. Black enameled steel for use at rear floor line corner, one required.

Moulding, P-350898. Black enameled steel for left side, one required.

Moulding, P-350899. Black enameled steel for right side, one required.

Corner Angle, P-350900. Black enameled steel, for rear side wall corners, two required.

Felt Base, P-350901. For use under linoleum floor, one required.

Plug, P-350903. Linoleum disk, for use in center depression of steel base.

Screws, P-350927. 3/4" No. 6 R.H.I. wood screws for fastening moulding and corner angles, 16 required.