

## Feature operation

Call Forward			
Activate	Fwd		► Fwd
Deactivate	► Fwd		
Reinstate	Fwd	► Fwd	
View number	Display	► Fwd	
Call Pickup			
		Pickup	
Call Waiting			
Answer	 (Hold)	Call Waiting	
Return to first call	 (Goodbye)		
Conference			
	Conf		► Conf
Handsfree			
Activate	 (Handsfree)	 (Goodbye)	(to end the call)
Switch to handset			
Handset to handsfree	 (Handsfree)		
Activate Headset			
	 (Headset)	 (Goodbye)	(to end the call)
Hold			
Place a call on hold	 (Hold)		
Return to a held call			
Last Number Redial			
			
Ring Again			
Activate	RngAgn		
When notified		► RngAgn	
Deactivate	► RngAgn		
Transfer			
	Trans		► Trans
Adjust volume			
	 (Volume +)	or	 (Volume -)
Legend			
Icon	Action		
( )	Indicates the key cap text label. For example, (Message).		
	Lift the handset, press the line (DN) key or the <b>Handset</b> key.		
	Replace the handset, or press  to end the call.		
	Dial a number.		

## Legend (continued)

Icon	Action		
	Press the <b>Services</b> key once for Call Platform features, or press the <b>Services</b> key twice to access local tools menu options.		
	Press the <b>Up/Down Navigation</b> keys		
	Press the <b>Enter</b> key		
	Press the <b>Headset</b> key.		
	Press the <b>Handsfree</b> key.		
	Press the <b>Mute</b> (on/off) key.		

## Services and Telephone Options menus

Services menu			
			
<p><b>Note:</b> The <b>Services</b> menu contains the <b>Telephone Options</b>, <b>Password Admin</b>, and <b>Virtual Office</b>. Some options are not available on all IP Phone 1210 phones. Consult your system administrator.</p>			

The following are the most commonly used options:

Telephone Options menu			
Volume adjustment			
Pick one of:			
Ringer			
Handset Listen			Select
Handsfree Listen			
Headset Listen			
Buzzer			
Contrast adjustment			
			Select
Language			
			Select
<p><b>Note:</b> This language setting controls the language used by features on your phone only. To set the language used elsewhere on your phone, press <b>Services</b> twice, select 1. Preferences, and select 2. Language.</p>			
Date/Time format			
			Select
Local DialPad Tone			
			Select
Ring type			
	Play		Select
OnHook default path			
			Select

**Note:** The **Directory** key provides access to the Corporate Directory, Personal Directory, Redial List, and Callers List. For additional information about your IP Phone 1210, consult the *Nortel IP Phone 1210 User Guide*.

# Nortel IP Phone 1210



To provide feedback or report a problem in this document, go to [www.nortel.com/documentfeedback](http://www.nortel.com/documentfeedback).

## LEGAL NOTICE

While the information in this document is believed to be accurate and reliable, except as otherwise expressly agreed to in writing NORTEL PROVIDES THIS DOCUMENT "AS IS" WITHOUT WARRANTY OR CONDITION OF ANY KIND, EITHER EXPRESS OR IMPLIED. The information and/or products described in this document are subject to change without notice.

Date: March 2008  
Document Release: Standard 01.03  
Document Number: NN43140-100  
Copyright © 2005–2008 Nortel Networks.  
All Rights Reserved.

\* Nortel, the Nortel logo, and the Globemark are trademarks of Nortel Networks.

# NORTEL

[www.nortel.com](http://www.nortel.com)

## IP Phone 1210

For Nortel Communication Server 1000

## Quick Reference Card

