




Gateway W350I Heatsink Fan Replacement

If you have a broken heatsink fan, use this step-by-step guide to explain how to replace the heatsink fan in your Gateway W350I laptop.

Written By: Aaron Austin




INTRODUCTION

This repair will be needed in circumstances where the heatsink fan is not turning on and causing the computer to power itself down. Replacing the heatsink fan with a new one should correct the overheating power downs.

TOOLS:

- Small Phillips Head Screwdriver (1)
- Tweezers (1)
- iFixit Opening Tools (1)

Step 1 — Battery Access




- Turn the laptop upside down and position it as shown in the image.

Step 2 — Unlocking the Battery




- Slide the locking switch towards the open lock picture.
- Hold the release switch in the unlocked position while simultaneously pushing the battery away from the laptop.
- Once the laptop is disengaged, completely remove the battery from the laptop.

Step 3 — Remove Bottom Cover





- Remove the single 3mm Phillips #0 screw holding on the plastic cover.
- Use a plastic opening tool to gently pry off the plastic cover.

Step 4 — Remove Screws & Tape



- Remove all four 3mm Phillips #0 screws holding in the fan.
- Remove the tape from the top of the fan

Step 5 — Removing Heat-Sink Fan



- Gently remove the fan from the metal housing.
- Disconnect the cable with tweezers.

To reassemble your device, follow these instructions in reverse order.