



How to Reset the SMC on MacBooks

This guide shows you how to reset the SMC (System Management Controller) on the MacBook in case of logic board or battery issues.

Written By: mikeyd123

INTRODUCTION

If you have done a logic board or battery replacement, you can reset your MacBook's SMC. You may also use this as a first-aid measure if you're having power issues with your MacBook.

Step 1 — Does your MacBook have a T2 security chip?



- These MacBooks have a T2 security chip:
 - MacBook Air introduced in 2018 or later
 - MacBook Pro introduced in 2018 or later
- If it has a T2 chip you can reset the SMC as follows (if not, skip this step):
 - Hold the "Control" and "Option" (Alt) on the left side of your keyboard and the "Shift" on the right side of your keyboard for 7 seconds.
 - Then additionally press and hold the power button and keep holding all four keys for another 7 seconds, then release them.
 - Press the power button after few seconds to turn on your MacBook.

Step 2 — Does your MacBook have a non-removable battery?



- These models have a non-removable battery ([per Apple definition](#)):
 - MacBook Pro (Early 2009) and later
 - all models of MacBook Air
 - MacBook (Late 2009)
 - MacBook (Retina, 12-inch, Early 2015) and later
- Proceed with the next step to reset your SMC.
- For other models skip this and the next step.

Step 3 — If the battery is non-removable



- Shut down your Mac.
- Unplug the MagSafe or USB-C power adapter from your computer.
- Using the built-in keyboard, press Shift-Control-Option on the left side of the keyboard, then press the power button at the same time. Hold these keys and the power button for 10 seconds.
- Release all keys.
- Reconnect the power adapter.
- Press the power button again to turn on your Mac.

Step 4 — If the battery is removable



- Shut down your Mac.
- Disconnect the MagSafe power adapter from your computer.
- Remove the battery.
- Press and hold the power button for 5 seconds.
- Reconnect the battery and MagSafe power adapter.
- Press the power button to turn on your Mac.
- The LED on the MagSafe power adapter might change colors or temporarily turn off when you reset the SMC.

The SMC of your MacBook has now been reset.