



Huawei Union Motherboard Replacement

This guide will show you how to replace the Motherboard for the Huawei Union in a few short and simple steps.

Written By: Brittany Achor



INTRODUCTION

Use this guide if your Huawei Union will not charge when plugged into a charger or begins losing charge faster than previously observed.

TOOLS:

- [Spudger](#) (1)
- [Phillips #00 Screwdriver](#) (1)
- [Magnetic Project Mat](#) (1)

Step 1 — Battery



- Wedge your thumb nail, or the flat end of a spudger, into the bottom left corner and pry off.

Step 2



- Use the flat end of a spudger, or fingernail, to lift up the battery and pull out.

Step 3 — Camera Lens Panel



- Remove the thirteen 3mm Phillips #00 screws from the back panel.

Step 4



- Use the flat end of a spudger to pry off the back panel.

Step 5 — Motherboard



- Remove a single 3mm Phillips #00 screw from the motherboard.

Step 6



- Using the flat end of a spudger to disconnect the motherboard ribbon cable.

Step 7



- Firmly hold the second ribbon cable's plastic film cover and pull up to disconnect.

Step 8



- Wedge the flat end of a spudger underneath the motherboard and pry upwards to separate it from the frame.

To reassemble your device, follow these instructions in reverse order.

