



# MacBook Air 13" Retina 2018 Teardown

Teardown of the MacBook Air 2018, performed November 7th, 2018.

Written By: Taylor Dixon



## INTRODUCTION

After years of neglect, Apple has finally updated the widely-beloved MacBook Air. Does this new lightweight have what it takes to keep up with ultraportables of 2018? Or is it just [full of hot air](#)? Let's open it up and find out.

Follow us on [Facebook](#), [Instagram](#), and [Twitter](#) to keep up with all the latest teardowns. Subscribe to our [newsletter](#) to have teardowns delivered right to your inbox.

## TOOLS:

- [P5 Pentalobe Screwdriver Retina MacBook Pro and Air \(1\)](#)
- [T3 Torx Screwdriver \(1\)](#)
- [T5 Torx Screwdriver \(1\)](#)
- [T8 Torx Screwdriver \(1\)](#)
- [Tweezers \(1\)](#)
- [Spudger \(1\)](#)

## Step 1 — MacBook Air 13" Retina 2018 Teardown




- Let's clear the Air about some of these specs:
  - 13.3" LED-backlit IPS Retina display; 2560 x 1600 resolution (227 ppi)
  - 1.6 GHz dual-core Intel Core i5 (Turbo Boost up to 3.6 GHz) with integrated Intel UHD Graphics 617
  - Apple T2 custom security chip / coprocessor
  - 8 GB of 2133 MHz LPDDR3 SDRAM
  - 128 GB PCIe-based SSD
  - 802.11ac Wi-Fi and Bluetooth 4.2
  - Two Thunderbolt 3 (USB-C) ports supporting charging, DisplayPort, Thunderbolt, and USB 3.1 Gen 2

## Step 2




- Before venturing inside, we take a quick survey of some of the the new Air's external features.
- On its underbelly we find some fine print, and some color-matched pentalobe screws.
  - ⓘ Looks like we've got some new numbers! Model A1932 and EMC 3184.
- Opening it up, we're greeted with a [familiar](#) 3rd-gen butterfly keyboard, and we immediately have MacBook Pro flashbacks.
- The Air bears a remarkable resemblance to the [Touch Bar-less 13" MacBook Pro](#)—apart from thickness and Touch ID, they are nigh indistinguishable.
- ...and despite the "Air" nomenclature, this makes the [12" MacBook](#) look like a lightweight by comparison.

## Step 3




- Of course, no external survey would be complete without a little X-ray reconnaissance.
- With the help of our friends at [Creative Electron](#), we get a peek at what's to come.

## Step 4





- One last detour before we head inside: we can't resist popping off our [favorite](#) command key for a peek at the ~~noise dampening~~ ingress-resisting membrane.
  - Love it or hate it, it looks like [butterfly](#) is here to stay.
- After a few twists of our [pentalobe driver](#), one good tug pops the lower case free of its two clips, and we're in.
  - **i** This simple procedure brings a smile to our face in comparison to some of the booby-trapped lids we've found on [MacBooks](#) and [MacBook Pros](#) lately.
- Inside, we spy: a small logic board, one lonely fan, a pair of large elongated speakers, and an interesting radiator-esque heat sink.

## Step 5




- Just six Torx screws and a few cable connectors stand between us and logic board removal—not bad! Certainly nothing our [Marlin Screwdriver Set](#) can't handle.
- Out it comes! The Air's logic board is not [mustachioed](#) like the Pro's, nor is it quite so [minuscule](#) as the MacBook's.
- *i* So far this is easy, but we'd prefer to see upgradeable components or straightforward battery access—AKA device-life extenders—over board access at this point.
- Next we snag the daughterboard, which hosts a (highly endangered) headphone jack and some connectors for the speaker and Touch ID sensor.
- Also residing on this board: a [Cirrus Logic CS42L83A audio codec](#).

## Step 6




- This board may be small, but it's still packing some decent processing power:
  - Intel [SREKQ](#) Core i5-8210Y processor
  - Apple APL1027 339S00535 T2 coprocessor
  - SanDisk SDSGFBF12 043G flash storage (128 GB total)
  - Intel [JHL7540](#) Thunderbolt 3 controller
  - 338S00267-A0 (likely an Apple PMIC)

## Step 7




- We flip the board to find even more silicon:
  - 2x SKhynix H9CCNNNCPTAL LPDDR3 RAM (8 GB total)
  - Murata 339S00446 1ZE SS8915047 (likely a Wi-Fi module)
  - Intersil 95828A HRTZ X829PMJ
  - NXP 80V18 secure NFC module
  - Macronix [MX25U3235F](#) serial multi I/O flash memory
  - Texas Instruments CD32-15C00 power controller
  - Texas Instruments TPS51980A synchronous buck converter

## Step 8



- Opposite the headphone jack, we spy some super modular Thunderbolt ports!
- This MacBook is off to a good start as far as we're concerned—all the ports sit on their own boards and are easily replaceable.
- Finally we meet the part responsible for blowing the air in this ... Air.
- *(i)* The upgraded 7-watt processors must produce a bit of extra heat—[Apple's prior Lightweight champs](#) went completely fanless.

## Step 9



- Continuing the repair-friendly (or at least friendlier) trend, we find stretchy adhesive pull tabs under these elongated speakers!
- We don't *love* adhesive—reusable screws are nearly always better—but hey, pulling out this [iPhone-esque](#) stretch-release stuff is loads better than [gooey solvents and blind prying](#).
- Plus, the mere presence of stretch-release adhesive generally means that someone at least thought about possible repair and disassembly situations.

**i** Are you there, Apple? It's us, iFixit. Have you heard our pleas?

## Step 10



- Moving on, we direct our attention to the trackpad.
- Unlike the newer [MacBooks Pro](#), which have first-step replaceable trackpads, this trackpad shares a cable with the keyboard, which is pinned under the logic board.
-  Looks like any trackpad repairs will have to go through logic board removal first.
- As the trackpad comes out, we can't help but think of a [certain TIE fighter...](#)

## Step 11




- Thanks to our friends at [MacRumors](#), we had a hunch that removing this battery might be less nightmarish than in [some Retinas we know](#).
- Sure enough, we find four screws and six friendly pull-to-remove adhesive strips securing this AirPower Air's power pack.
- A sturdy frame, vaguely like those in [Airs of old](#), supports the gaggle of battery cells and makes removal a snap.
- Here it is: the 49.9 Wh power plant. In case you're keeping track, that's slightly smaller than Dell's new [XPS 13](#) (52 Wh), but larger than Microsoft's [Surface Laptop 2](#) (45.2 Wh) and HP's upcoming [Spectre x360](#) (43.7 Wh).  
*(i)* All of these devices boast 10+ hour battery life, but the Air's competition manages to do so while *also* running faster, more power-intensive Intel U-series processors.

## Step 12



- Things are starting to look Air-y inside this golden chassis—we can almost see the finish line!
- Still lingering above the battery cavern are the metal antenna bracket and the new (modular!) Touch ID sensor, each secured by Torx screws.
- FYI, the Touch ID sensor *can* come out directly after the [smaller audio board](#) is removed—we just chose to let it [linger](#).
- A few more Torx screws later, the display is free! This new Retina panel is almost the same as the one found on the MacBook Pro line, differing mainly in peak brightness (a mere 300 nits vs. the Pro's 500) and [P3 color gamut support](#).

## Step 13



- We'll just let this MacBook Air out a little so you can admire its particles!
- Featuring modular ports and pull-to-release adhesive, the new MacBook Air stands out against a trend of declining repairability in Apple's laptops.
- Unfortunately, you'll still have to work around pentalobes, and neither storage nor RAM is upgradable. Though this update seems to favor experienced technicians more than the average DIYer, we're hoping it's the first step back toward repairable MacBooks.

## Step 14 — Final Thoughts



- The MacBook Air with Retina Display 2018 earns a **3 out of 10** on our repairability scale (10 is the easiest to repair):
  - Many components are modular and straightforward to access—including the ports, fan, and speakers.
  - Apart from the pesky pentalobe screws, this laptop opens about as easily as any.
  - The battery is secured with a combination of screws and repair-friendly stretch-release adhesive—but you'll have to remove the logic board and speakers for access.
  - The keyboard is integrated into the top case, requiring a full teardown for service.
  - Soldered, non-serviceable, non-upgradeable storage and RAM is a serious bummer on a \$1,200+ laptop.