



# iMac Intel 27" EMC 2390 RAM Replacement

Replace the RAM in your iMac Intel 27" EMC 2390.

Written By: Walter Galan



# INTRODUCTION

Upgrade RAM modules for an instant boost in speed.

## TOOLS:

- Phillips #1 Screwdriver (1)
- Spudger (1)

## PARTS:

- iMac Intel 27" (Core i3) EMC 2390 (Mid 2010) Memory Maxxer RAM Upgrade Kit (1)
- iMac Intel 27" (Core i5 or i7) EMC 2390 (Mid 2010) Memory Maxxer RAM Upgrade Kit (1)
- PC3-10600 2 GB RAM Chip (1)
- PC3-10600 4 GB RAM Chip (1)
- PC3-10600 8 GB RAM Chip (1)

## Step 1 — Access Door



- Loosen the three Phillips screws securing the access door to the bottom edge of your iMac.
- These screws will remain captive in the access door.
- Remove the access door from your iMac.
- ★ During reassembly, fasten the access door loosely and align it with the pocket cut into the outer case of the iMac before fully tightening the screws.

## Step 2 — RAM



- Use your fingers or the tip of a spudger to slide the black plastic RAM tray pull tab out of the RAM slot.

## Step 3



- Pull the black plastic tab away from the iMac to eject the RAM chip from its socket.
- The RAM modules are firmly seated and may require a fair amount of force to remove.
- Use your fingers to slide the RAM chip out of its socket.

*(i)* If necessary, repeat this process for the other RAM module(s).

To reassemble your device, follow these instructions in reverse order.